Preface
- Purpose and Scope
- Intended Audience
- How to Use This Book
- Special Features
- Acknowledgments
- Historical Development of Transformers
  - Early Discoveries and Foundations
  - The Birth of Practical Transformers
  - The War of Currents and Transformer Triumph
  - Evolution and Refinement
  - Modern Developments
- Importance in Electrical Power Systems
  - Enabling Efficient Power Transmission
  - System Protection and Control
  - Isolation and Power Quality
  - Enabling Renewable Integration
- Overview of Transformer Types and Applications
  - By Power Rating
  - By Cooling Method
  - By Application
  - By Construction
- Current State of Transformer Technology
  - Efficiency and Losses
  - Monitoring and Diagnostics
  - Materials and Manufacturing
  - Environmental Considerations
- Future Trends and Developments
  - Smart Transformers
  - Solid-State Transformers
  - Advanced Materials
  - Integration with Renewable Energy and Storage
  - Digital Twins and Lifecycle Management
- Structure and Organization of This Book
- Front Matter
- Chapter 1: Fundamentals of Transformers
- Chapter 2: Working Principles of Transformers
- Chapter 3: Construction and Components
- Chapter 4: Types of Transformers
- Chapter 5: Transformer Operation
- Chapter 6: Transformer Losses and Efficiency
- Chapter 7: Transformer Testing
- Chapter 8: Three-Phase Transformers
- Chapter 9: Special Transformers
- Chapter 10: Applications of Transformers
- Chapter 11: Modern Trends and Future Developments

Appendices
Back Matter
Chapter 1: Fundamentals of Transformers
Chapter 2: Working Principles of Transformers
Chapter 3: Construction and Components
Chapter 4: Types of Transformers
Chapter 5: Transformer Operation
Chapter 6: Transformer Losses and Efficiency
Chapter 7: Transformer Testing
Chapter 8: Three-Phase Transformers
Chapter 9: Special Transformers
Chapter 10: Applications of Transformers
Chapter 11: Modern Trends and Future Developments
Symbols
  General Electrical Quantities
  Magnetic Quantities
  Transformer-Specific Symbols
  Thermal Quantities
  Material Properties
Abbreviations
  General Terms
  Transformer Types and Components
  Cooling Systems
  Testing and Diagnostics
  Insulating Materials and Fluids
  Standards and Organizations
  Fault Gases and DGA
  Smart Grid and Monitoring
  Three-Phase Connections
1.1 Definition and Basic Concepts
1.2 Historical Development
  Early Discoveries and Foundations
  First Practical Transformers
  The War of Currents
  Evolution Through the 20th Century
  Modern Innovations
1.3 Importance in Electrical Power Systems
  Enabling Efficient Power Transmission
  System Isolation and Protection
  Voltage Regulation and Power Quality
  Enabling Interconnected Power Systems
  Economic Implications
  Critical Infrastructure Protection
1.4 Overview of Transformer Applications
  Power System Applications
  Industrial Applications
  Commercial and Residential Applications
  Specialized Applications

Scientific and Research Applications
1.5 Basic Transformer Theory
Faraday’s Law of Electromagnetic Induction
Mutual Induction
Basic Transformer Operation
Voltage Transformation
Current Transformation
EMF Equation of a Transformer
Importance of Alternating Current
2.1 Faraday’s Law of Electromagnetic Induction
2.1.1 Statement of Faraday’s Law
2.1.2 Lenz’s Law
2.1.3 Application to Transformers
2.2 Mutual Induction
2.2.1 Definition and Basic Concept
2.2.2 Mathematical Expression
2.2.3 Coefficient of Coupling
2.2.4 Mutual Induction in Transformer Operation
2.3 EMF Equation and Turns Ratio
2.3.1 Transformer EMF Equation
2.3.2 Turns Ratio and Voltage Ratio
2.3.3 Current Ratio
2.3.4 Impedance Transformation
2.4 Significance of Alternating Current (AC)
2.4.1 Why Transformers Require AC
2.4.2 AC vs. DC in Transformer Operation
2.4.3 Historical Impact on Power Systems
2.4.4 Frequency Considerations
2.5 Ideal Transformer Concept
2.5.1 Characteristics of an Ideal Transformer
2.5.2 Equations Governing Ideal Transformer Operation
2.5.3 Phasor Diagram of an Ideal Transformer
2.5.4 Limitations of the Ideal Transformer Model
2.5.5 Practical Significance
3.1 Magnetic Core: Materials and Designs
3.1.1 Core Materials
3.1.2 Core Designs
3.1.3 Lamination Techniques
3.1.4 Core Assembly Methods
3.2 Windings: Types and Arrangements
3.2.1 Winding Materials
3.2.2 Winding Types
3.2.3 Winding Arrangements
3.2.4 Winding Insulation
3.2.5 Taps and Tap Changers
3.3 Insulation Systems
3.3.1 Insulation Materials
3.3.2 Insulation Structures

3.3.3 Insulation Coordination
3.3.4 Aging and Lifetime
3.4 Cooling Systems
3.4.1 Cooling Methods Classification
3.4.2 Common Cooling Methods for Oil-Immersed Transformers
3.4.3 Cooling Systems for Dry-Type Transformers
3.4.4 Cooling System Components
3.4.5 Temperature Monitoring
3.5 Bushings and Terminals
3.5.1 Bushing Types
3.5.2 Bushing Components
3.5.3 Bushing Selection Criteria
3.5.4 Terminal Connections
3.5.5 Bushing Maintenance and Monitoring
3.6 Auxiliary Components
3.6.1 Conservator Tank
3.6.2 Breather
3.6.3 Buchholz Relay
3.6.4 Pressure Relief Devices
3.6.5 Sudden Pressure Relay
3.6.6 Oil Level Indicators
3.6.7 Temperature Indicators
3.6.8 Cooling Controls
3.6.9 De-energized Tap Changers (DETC)
3.6.10 On-Load Tap Changers (OLTC)
3.6.11 Bushing Current Transformers
3.6.12 Oil Sampling Valves
3.6.13 Radiator Isolation Valves
3.6.14 Ground Connections
3.6.15 Nitrogen Injection Fire Protection System
3.6.16 Online Monitoring Systems
4.1 Based on Voltage Level
4.1.1 Step-Up Transformers
4.1.2 Step-Down Transformers
4.1.3 Isolation Transformers
4.1.4 Variable Transformers
4.2 Based on Construction
4.2.1 Core Type Transformers
4.2.2 Shell Type Transformers
4.2.3 Berry Type Transformers
4.2.4 Toroidal Transformers
4.3 Based on Core Material
4.3.1 Iron Core Transformers
4.3.2 Ferrite Core Transformers
4.3.3 Toroidal Core Transformers
4.3.4 Air Core Transformers
4.3.5 Amorphous Metal Core Transformers
4.3.6 Nanocrystalline Core Transformers

4.4 Based on Purpose
4.4.1 Power Transformers
4.4.2 Distribution Transformers
4.4.3 Instrument Transformers
4.4.4 Auto-Transformers
4.4.5 Rectifier Transformers
4.4.6 Welding Transformers
4.4.7 Isolation Transformers
4.4.8 Phase-Shifting Transformers
4.5 Based on Phases
4.5.1 Single-Phase Transformers
4.5.2 Three-Phase Transformers
4.5.3 Three-Phase Transformer Connections
4.5.4 Special Three-Phase Configurations
4.5.5 Polyphase Transformers Beyond Three-Phase
4.6 Special Types
4.6.1 Autotransformers
4.6.2 Tap-Changing Transformers
4.6.3 Dry-Type Transformers
4.6.4 Pad-Mounted Transformers
4.6.5 Grounding Transformers
4.6.6 Mobile Transformers
4.6.7 Phase-Shifting Transformers
4.6.8 Converter Transformers
5.1 No-Load Operation
5.1.1 No-Load Current
5.1.2 Magnetic Flux in No-Load Condition
5.1.3 Phasor Diagram Under No-Load Condition
5.1.4 Core Saturation Effects
5.2 Load Operation
5.2.1 Effect of Secondary Current
5.2.2 Primary Current Under Load
5.2.3 Voltage Drops Under Load
5.2.4 Phasor Diagram Under Load Condition
5.3 Voltage Regulation
5.3.1 Definition and Formula
5.3.2 Factors Affecting Voltage Regulation
5.3.3 Calculation of Voltage Regulation
5.3.4 Improving Voltage Regulation
5.4 Parallel Operation of Transformers
5.4.1 Conditions for Parallel Operation
5.4.2 Load Sharing Between Parallel Transformers
5.4.3 Circulating Currents
5.4.4 Advantages and Limitations of Parallel Operation
5.4.5 Practical Considerations for Parallel Operation
5.5 Inrush Current Phenomenon
5.5.1 Causes of Inrush Current
5.5.2 Characteristics of Inrush Current

5.5.3 Factors Affecting Inrush Current
5.5.4 Mitigation Techniques
5.5.5 Practical Implications
6.1 Core Losses (Iron Losses)
6.1.1 Hysteresis Loss
6.1.2 Eddy Current Loss
6.1.3 Anomalous Loss (Excess Loss)
6.1.4 Total Core Loss
6.1.5 Core Loss Reduction Strategies
6.2 Copper Losses (Winding Losses)
6.2.1 Primary Winding Copper Loss
6.2.2 Secondary Winding Copper Loss
6.2.3 Total Copper Loss
6.2.4 Factors Affecting Copper Losses
6.2.5 Copper Loss Reduction Techniques
6.3 Stray Losses
6.3.1 Eddy Current Losses in Windings
6.3.2 Losses in Structural Components
6.3.3 Circulating Current Losses
6.3.4 Measurement and Estimation of Stray Losses
6.4 Efficiency Calculation
6.4.1 Efficiency Formula
6.4.2 Efficiency at Different Load Conditions
6.4.3 Factors Affecting Efficiency
6.4.4 Efficiency Standards
6.5 Maximum Efficiency Condition
6.5.1 Derivation of Maximum Efficiency Condition
6.5.2 Load Factor for Maximum Efficiency
6.5.3 Design Considerations for Maximum Efficiency
6.6 All-Day Efficiency
6.6.1 Definition and Calculation
6.6.2 Typical Load Cycle
6.6.3 Example Calculation
6.6.4 Importance of All-Day Efficiency
6.6.5 Improving All-Day Efficiency
6.7 Temperature Rise and Cooling Systems
6.7.1 Heat Generation and Temperature Rise
6.7.2 Temperature Limits
6.7.3 Cooling Methods
6.7.4 Thermal Modeling and Monitoring
6.7.5 Impact of Cooling on Efficiency
6.8 Economic Evaluation of Transformer Losses
6.8.1 Capitalization of Losses
6.8.2 Calculation of A and B Factors
6.8.3 Example of Economic Evaluation
6.8.4 Regulatory Aspects
6.8.5 Life Cycle Assessment
6.9 Recent Advances in Loss Reduction

6.9.1 Advanced Core Materials
6.9.2 Winding Innovations
6.9.3 Design Optimization
6.9.4 Smart Transformers
6.9.5 Future Directions
7.1 Open Circuit Test
7.1.1 Test Setup and Procedure
7.1.2 Measured Parameters and Calculations
7.1.3 Equivalent Circuit Parameters
7.1.4 Significance and Limitations
7.2 Short Circuit Test
7.2.1 Test Setup and Procedure
7.2.2 Measured Parameters and Calculations
7.2.3 Equivalent Circuit Parameters
7.2.4 Significance and Applications
7.2.5 Temperature Correction
7.3 Sumpner Test (Back-to-Back Test)
7.3.1 Test Setup and Procedure
7.3.2 Measured Parameters and Calculations
7.3.3 Advantages and Limitations
7.4 Polarity Test
7.4.1 Test Methods
7.4.2 Polarity Markings
7.4.3 Importance of Polarity
7.5 Ratio Test
7.5.1 Test Methods
7.5.2 Interpretation of Results
7.5.3 Applications
7.6 Insulation Resistance Test
7.6.1 Test Equipment and Setup
7.6.2 Test Procedure
7.6.3 Interpretation of Results
7.6.4 Factors Affecting Insulation Resistance
7.6.5 Applications and Limitations
7.7 Dissolved Gas Analysis (DGA)
7.7.1 Principle and Methodology
7.7.2 Interpretation Methods
7.7.3 Fault Types and Gas Patterns
7.7.4 Sampling Frequency and Trending
7.7.5 Limitations and Complementary Tests
7.8 Frequency Response Analysis (FRA)
7.8.1 Principle and Methodology
7.8.2 Test Procedure
7.8.3 Interpretation of Results
7.8.4 Types of Detectable Faults
7.8.5 Advantages and Limitations
7.8.6 Applications
7.9 Other Important Tests

7.9.1 Winding Resistance Measurement
7.9.2 Power Factor / Dissipation Factor Test
7.9.3 Excitation Current Test
7.9.4 Magnetic Balance Test
7.9.5 Oil Quality Tests
7.9.6 Partial Discharge Test
7.9.7 Furan Analysis
7.9.8 Thermal Imaging
7.10 Diagnostic Testing Programs
7.10.1 Types of Testing Programs
7.10.2 Test Frequency and Scheduling
7.10.3 Risk-Based Maintenance
7.10.4 Data Management and Analysis
7.10.5 Health Indices and Condition Assessment
7.10.6 Online Monitoring Systems
8.1 Introduction to Three-Phase Transformers
8.1.1 Comparison with Single-Phase Transformers
8.1.2 Applications of Three-Phase Transformers
8.2 Construction of Three-Phase Transformers
8.2.1 Core Types
8.2.2 Winding Arrangements
8.2.3 Cooling Systems
8.3 Three-Phase Transformer Connections
8.3.1 Star (Wye) Connection
8.3.2 Delta Connection
8.3.3 Zigzag Connection
8.3.4 Open-Delta (V-V) Connection
8.4 Vector Groups
8.4.1 Vector Group Notation
8.4.2 Common Vector Groups
8.4.3 Selection Criteria for Vector Groups
8.5 Parallel Operation of Three-Phase Transformers
8.5.1 Conditions for Parallel Operation
8.5.2 Load Sharing Between Parallel Transformers
8.5.3 Circulating Currents
8.5.4 Practical Considerations
8.6 Three-Phase Transformer Banks
8.6.1 Advantages and Disadvantages
8.6.2 Common Connections for Transformer Banks
8.6.3 Special Configurations
8.7 Testing of Three-Phase Transformers
8.7.1 Routine Tests
8.7.2 Type Tests
8.7.3 Special Tests
8.8 Applications and Practical Considerations
8.8.1 Selection Criteria
8.8.2 Installation Considerations
8.8.3 Maintenance Practices

8.9 Case Studies and Examples
8.9.1 Power Transmission Substation
8.9.2 Distribution Network
8.9.3 Industrial Application
8.10 Future Trends in Three-Phase Transformer Technology
8.10.1 Advanced Materials
8.10.2 Smart Features
8.10.3 Environmental Considerations
8.10.4 Efficiency Improvements
Chapter 9: Special Transformers
Chapter 10: Applications of Transformers
Chapter 11: Modern Trends and Future Developments
A
B
C
D
E
F
G
H
I
K
L
M
N
O
P
R
S
T
V
W
Y
Z

# Comprehensive Guide to Transformers in Electrical Engineering

# Principles, Design, Operation, and Applications

NinjaTech AI

2025

# Preface

## Purpose and Scope

This comprehensive guide to transformers in electrical engineering represents a culmination of extensive research, practical experience, and educational insights into one of the most fundamental components of electrical power systems. Transformers, despite being invented over a century ago, remain indispensable in modern electrical networks and continue to evolve with technological advancements.

The purpose of this book is to provide a thorough understanding of transformer principles, design, operation, testing, and applications. It bridges the gap between theoretical foundations and practical implementation, making it valuable for both academic study and professional reference. The content spans from basic electromagnetic principles to cutting-edge developments in smart transformer technology, offering readers a complete journey through the world of transformers.

## Intended Audience

This book is designed to serve multiple audiences:

- **Engineering students** at undergraduate and graduate levels studying electrical engineering, power systems, or energy conversion will find comprehensive coverage of transformer theory and applications with clear explanations and illustrative examples.
- **Practicing engineers** in power utilities, manufacturing, design, and maintenance will appreciate the practical insights, design considerations, testing procedures, and application-specific information.

- **Researchers and academics** will benefit from the in-depth treatment of advanced topics, emerging technologies, and future trends, supported by extensive references to current literature.
- **Technicians and field personnel** will find valuable information on transformer operation, testing, maintenance, and troubleshooting that can be directly applied in their daily work.

The material is structured to accommodate readers with varying levels of prior knowledge, from those seeking to build a foundation in transformer principles to experienced professionals looking to deepen their expertise in specific areas.

## How to Use This Book

The book is organized in a logical progression from fundamental concepts to specialized applications and future developments:

- **Chapters 1-2** establish the theoretical foundation, covering basic principles of electromagnetic induction and transformer operation.
- **Chapters 3-4** focus on transformer construction, components, and the various types of transformers encountered in electrical systems.
- **Chapters 5-6** delve into operational aspects, including voltage regulation, parallel operation, and efficiency considerations.
- **Chapter 7** provides comprehensive coverage of transformer testing and diagnostics, essential for quality assurance and maintenance.
- **Chapter 8** addresses three-phase transformers, their connections, and applications in power systems.
- **Chapter 9** explores special-purpose transformers designed for specific applications and requirements.
- **Chapter 10** examines the diverse applications of transformers across power generation, transmission, distribution, and various industries.
- **Chapter 11** looks toward the future, discussing emerging technologies, materials, and trends that will shape transformer development in the coming decades.

Each chapter includes clear explanations, illustrative diagrams, practical examples, and end-of-chapter problems to reinforce understanding. The appendices provide supplementary material,

including mathematical derivations, design examples, and reference information on standards and regulations.

Readers with specific interests may choose different paths through the book:

- Those seeking a comprehensive understanding should proceed sequentially through all chapters.
- Readers focused on practical applications might concentrate on Chapters 3-8 and 10.
- Those interested in emerging technologies should pay special attention to Chapters 9 and 11.
- Practicing engineers may use the book as a reference, consulting specific sections as needed.

## Special Features

This book includes several features designed to enhance the learning experience and practical value:

- **Detailed Illustrations**: Over 100 carefully crafted diagrams and schematics clarify complex concepts and construction details.
- **Practical Examples**: Real-world examples demonstrate the application of theoretical principles to actual transformer design and operation.
- **Case Studies**: Selected case studies highlight practical challenges and solutions in transformer applications.
- **Design Considerations**: Key design parameters and trade-offs are discussed to guide engineering decisions.
- **Testing Procedures**: Step-by-step testing protocols with interpretation guidelines assist in quality assurance and troubleshooting.
- **Historical Context**: Brief historical notes provide perspective on the evolution of transformer technology.
- **Emerging Technologies**: Coverage of recent innovations and research directions keeps readers informed of developments at the cutting edge of the field.

## Acknowledgments

The creation of this comprehensive work would not have been possible without the contributions and support of many individuals and organizations. I wish to express my sincere gratitude to:

The academic and research institutions that have advanced our understanding of transformer technology through rigorous investigation and innovation.

Industry partners who have shared practical insights, case studies, and real-world applications that enrich the content of this book.

Colleagues and reviewers who provided valuable feedback, technical corrections, and suggestions that significantly improved the manuscript.

Students whose questions and curiosity have continually challenged me to find clearer explanations and more effective teaching approaches.

My family, for their unwavering support and patience throughout the writing process.

Special thanks are due to [specific acknowledgments to be added].

Any errors or omissions remain solely my responsibility, and I welcome feedback from readers to improve future editions.

It is my sincere hope that this book will serve as a valuable resource for all who work with transformers, contributing to the continued advancement of this essential technology and its applications in our evolving electrical power systems.

[Author Name] [Date]# Introduction

# Historical Development of Transformers

The transformer stands as one of the most significant inventions in electrical engineering history, fundamentally enabling the widespread distribution and utilization of electrical power that has transformed modern society. The journey of transformer development represents a fascinating intersection of scientific discovery, engineering innovation, and practical application.

## Early Discoveries and Foundations

The foundations for transformer technology were laid in the early 19th century with the discovery of electromagnetic induction. In 1831, Michael Faraday demonstrated that a changing magnetic field could induce an electric current in a nearby conductor—the fundamental principle upon which all transformers operate. Joseph Henry independently made similar discoveries in the United States around the same time.

These scientific breakthroughs, however, did not immediately lead to practical transformer devices. For several decades, electrical systems primarily used direct current (DC), where transformers have no application. The development of alternating current (AC) systems was necessary before transformer technology could flourish.

## The Birth of Practical Transformers

The first practical transformer designs emerged in the 1870s and 1880s. In 1876, Russian engineer Pavel Yablochkov used “induction coils” to power his electric candles from a single AC source—an early application of transformer principles. In 1878, the Ganz Company in Hungary developed the ZBD transformer, named after its inventors Károly Zipernowsky, Ottó Bláthy, and Miksa Déri.

The watershed moment came in 1885 when William Stanley, working for George Westinghouse, designed and built the first commercially practical transformer in Great Barrington, Massachusetts. Stanley’s design featured an iron core made of E-shaped iron plates, with primary and secondary windings wrapped around the central leg. This design dramatically improved efficiency and established the basic form that transformers would take for decades to come.

## The War of Currents and Transformer Triumph

The 1880s and 1890s witnessed the famous “War of Currents” between Thomas Edison’s direct current systems and George Westinghouse’s alternating current approach, with Nikola Tesla as a key figure in AC development. The transformer played a decisive role in this technological contest.

Edison’s DC systems faced a fundamental limitation: voltage could not be easily changed, meaning that power had to be generated close to where it was used, requiring numerous small power plants. In contrast, AC systems with transformers could step up voltage for efficient long-distance transmission and then step it down for safe consumer use.

The decisive demonstration came in 1891 when the first long-distance transmission of AC power was achieved in Germany between Lauffen and Frankfurt, covering 175 kilometers. In 1893, the Westinghouse company’s AC system was selected to power the Chicago World’s Fair, and in 1895, the Adams Power Plant at Niagara Falls began transmitting AC power to Buffalo, New York. These successes firmly established AC as the dominant electrical system, with transformers as essential components.

## Evolution and Refinement

Throughout the 20th century, transformer technology underwent continuous refinement:

- Core materials evolved from solid iron to silicon steel laminations, then to grain-oriented silicon steel in the 1930s, and later to amorphous metals for high-efficiency designs.
- Insulation systems progressed from air and oil to paper-oil combinations, synthetic materials, and modern composite insulation systems.
- Cooling methods advanced from natural air cooling to oil immersion, forced oil circulation, and sophisticated directed flow designs.
- Manufacturing techniques improved with the development of wound cores, step-lap joints, and precision winding machines.
- Monitoring and protection systems evolved from simple thermometers and pressure relief devices to comprehensive digital monitoring systems.

By the mid-20th century, power transformers had reached capacities exceeding 1,000 MVA and voltage levels above 700 kV, enabling the creation of vast interconnected power grids spanning continents.

## Modern Developments

The late 20th and early 21st centuries have seen transformer technology continue to evolve in response to new challenges and opportunities:

- Environmental concerns have driven the development of biodegradable insulating fluids, dry-type designs, and more efficient cores to reduce energy losses.
- The digital revolution has enabled smart transformers with integrated monitoring, diagnostics, and communication capabilities.
- Power electronics integration has led to the development of solid-state transformers that combine traditional transformer functions with advanced control capabilities.
- Renewable energy integration has created new requirements for transformers in wind farms, solar installations, and energy storage systems.
- Resilience against climate change, cyber threats, and physical attacks has become an important design consideration.

Today’s transformers represent over 140 years of continuous development, combining time-tested principles with cutting-edge materials and technologies to meet the evolving needs of our electrical power systems.

## Importance in Electrical Power Systems

Transformers are often described as the “heart” of electrical power systems, and for good reason. Their unique ability to change voltage levels efficiently enables the entire structure of modern electrical networks:

### Enabling Efficient Power Transmission

Without transformers, our electrical grid as we know it could not exist. The fundamental challenge of power transmission is that electrical energy must travel hundreds or thousands of kilometers from generation sites to load centers. Transmitting this power at low voltage would result in prohibitive losses and require impossibly thick conductors.

Transformers solve this problem by stepping up voltage at generating stations (typically to 115-765 kV), dramatically reducing current and associated $I^2R$ losses. At substations near load centers, transformers then step down voltage to distribution levels (typically 4-35 kV), and finally to utilization voltages (120-480 V) for end users.

This voltage transformation capability enables the hierarchical structure of our entire power grid, with its distinct transmission, sub-transmission, distribution, and utilization levels.

### System Protection and Control

Beyond their voltage-changing function, transformers play crucial roles in system protection and control:

- Instrument transformers (current and potential transformers) enable the measurement of high currents and voltages at safe levels for metering and protection devices.
- Phase-shifting transformers control power flow between different parts of the grid.
- Grounding transformers establish system neutral points and control ground fault currents.
- Reactors (a specialized transformer type) limit fault currents and control voltage.

These specialized transformers form an essential part of the protection infrastructure that keeps our power systems stable and safe.

### Isolation and Power Quality

Transformers provide galvanic isolation between circuits, a critical safety feature that prevents the direct transfer of fault currents between systems operating at different voltage levels. This isolation also blocks the flow of DC currents and helps contain harmonics and other power quality disturbances.

In sensitive applications like medical equipment, data centers, and telecommunications, isolation transformers specifically designed to enhance power quality are essential components that protect equipment and ensure reliable operation.

### Enabling Renewable Integration

As our energy systems evolve toward greater sustainability, transformers are taking on new importance in renewable energy integration:

- Wind farm transformers must handle variable generation and often operate in harsh environments.
- Solar inverter transformers interface between DC generation and AC transmission systems.
- Grid-scale battery storage systems require bidirectional power flow capabilities.

The successful integration of these diverse energy sources depends on specialized transformer designs that can accommodate their unique characteristics.

## Overview of Transformer Types and Applications

The diversity of transformer types reflects their ubiquity and versatility in electrical systems:

### By Power Rating

- **Power Transformers**: Large units (typically >10 MVA) used in generation stations and transmission substations.
- **Distribution Transformers**: Medium-sized units (typically 5 kVA to 10 MVA) that supply distribution networks and end users.

- **Small Power Transformers**: Units below 5 kVA used in consumer electronics, appliances, and control systems.

## By Cooling Method

- **Dry-Type Transformers**: Air-cooled units used indoors where fire safety is paramount.
- **Liquid-Immersed Transformers**: Units cooled by mineral oil, natural esters, synthetic esters, or silicone fluids.
- **Gas-Insulated Transformers**: Units using $SF_6$ or other gases for insulation in specialized applications.

## By Application

- **Generator Step-Up Transformers**: Connect generators to transmission systems.
- **Transmission Transformers**: Interface between different voltage levels in the transmission network.
- **Distribution Transformers**: Supply end users from the distribution network.
- **Autotransformers**: Provide economical voltage transformation where galvanic isolation is not required.
- **Instrument Transformers**: Enable measurement of high currents and voltages.
- **Phase-Shifting Transformers**: Control power flow between network sections.
- **Rectifier Transformers**: Supply DC conversion systems in industrial processes.
- **Traction Transformers**: Power railway electrification systems.
- **Furnace Transformers**: Supply electric arc furnaces in steel production.
- **Mobile Transformers**: Provide temporary or emergency power.

## By Construction

- **Core-Type Transformers**: Windings surround the core limbs.
- **Shell-Type Transformers**: Core surrounds the windings.
- **Toroidal Transformers**: Windings wrapped around a ring-shaped core.
- **Autotransformers**: Primary and secondary share a common winding.
- **Air-Core Transformers**: Used in high-frequency applications without ferromagnetic cores.

This diversity of transformer types enables the optimization of designs for specific applications, balancing factors such as efficiency, cost, size, weight, and special performance requirements.

# Current State of Transformer Technology

Today's transformer technology represents a mature field with continuous incremental improvements rather than revolutionary changes. Key aspects of the current state include:

## Efficiency and Losses

Modern distribution transformers achieve efficiencies exceeding 99%, with premium designs approaching 99.5%. This high efficiency results from:

- Advanced core materials, including high-grade grain-oriented silicon steel and amorphous metals
- Optimized core construction with step-lap joints and wound cores
- Improved winding designs that minimize eddy current losses
- Enhanced cooling systems that maintain optimal operating temperatures

Efficiency standards continue to drive improvements, with regulations like the U.S. Department of Energy's efficiency requirements and the European Union's Ecodesign Directive establishing increasingly stringent targets.

## Monitoring and Diagnostics

The integration of sensors and digital technologies has transformed transformer monitoring:

- Online dissolved gas analysis (DGA) provides early warning of developing faults
- Fiber optic temperature sensors enable detailed thermal monitoring
- Partial discharge monitoring detects insulation deterioration
- Bushing monitoring systems track power factor and capacitance
- Advanced analytics and artificial intelligence help interpret complex data patterns

These capabilities enable condition-based maintenance strategies that optimize reliability while minimizing costs.

## Materials and Manufacturing

Manufacturing processes have become highly automated and precise:

- Computer-controlled winding machines ensure consistent tension and placement
- Vapor-phase drying processes thoroughly remove moisture from insulation

- Automated core cutting and stacking improve core performance
- Advanced testing at multiple production stages ensures quality
- 3D design tools and finite element analysis optimize designs before manufacturing

Material improvements continue, particularly in insulation systems, where thermally upgraded papers, natural and synthetic esters, and advanced composite materials are extending transformer life and improving environmental compatibility.

### Environmental Considerations

Environmental factors have become central to transformer design and operation:

- Biodegradable insulating fluids reduce environmental impact from spills
- Dry-type designs eliminate liquid insulation concerns in sensitive locations
- Reduced losses decrease carbon footprint during operation
- Design for recyclability facilitates end-of-life material recovery
- Noise reduction features minimize community impact
- $SF_6$-free designs address concerns about greenhouse gas emissions

These environmental improvements respond to both regulatory requirements and customer preferences for sustainable technologies.

## Future Trends and Developments

Looking ahead, several key trends are shaping the future of transformer technology:

### Smart Transformers

The integration of digital intelligence into transformers is creating “smart transformers” with capabilities far beyond traditional voltage transformation:

- Real-time condition monitoring and self-diagnostics
- Communication with grid management systems
- Adaptive control of voltage and power flow
- Integration with distributed energy resources
- Cybersecurity features to protect against digital threats
- Predictive maintenance capabilities

These smart transformers will be key components in the evolving smart grid, providing both intelligence and power transformation functions.

## Solid-State Transformers

Solid-state transformers (SSTs), also called power electronic transformers, represent a potential paradigm shift in transformer technology:

- Using power electronics and high-frequency transformers to achieve voltage transformation
- Providing additional functions like DC outputs, harmonic filtering, and power quality improvement
- Enabling more compact designs for space-constrained applications
- Facilitating integration of DC sources and loads
- Supporting microgrid and nanogrid architectures

While still primarily in the research and demonstration phase, SSTs may eventually replace conventional transformers in specific applications where their additional functionality justifies their higher cost and complexity.

## Advanced Materials

Material science continues to offer opportunities for transformer improvement:

- High-temperature superconducting (HTS) materials may enable more compact, efficient designs
- Nanocomposite insulation materials could improve thermal performance and aging characteristics
- Advanced magnetic materials beyond amorphous metals may further reduce core losses
- Biodegradable and renewable insulating materials will improve sustainability
- 3D-printed components may enable novel geometries and integrated functions

These material advances will likely yield incremental improvements rather than revolutionary changes, but their cumulative impact will be significant over time.

## Integration with Renewable Energy and Storage

As power systems evolve toward higher renewable penetration and distributed resources, transformers are adapting to new requirements:

- Bidirectional power flow capabilities for prosumer applications
- Enhanced harmonic handling for inverter-based resources
- Compact designs for integration with solar arrays and wind turbines

- Specialized designs for grid-scale battery storage
- Resilience features for microgrids and islanded operation

These specialized transformers will facilitate the ongoing energy transition toward more sustainable and distributed power systems.

### Digital Twins and Lifecycle Management

Digital twin technology—creating virtual models of physical transformers—is emerging as a powerful tool for asset management:

- Real-time simulation of transformer behavior under actual operating conditions
- Prediction of aging and remaining useful life
- Optimization of loading and maintenance schedules
- Scenario planning for system changes and contingencies
- Knowledge preservation as experienced personnel retire

Combined with advanced analytics and artificial intelligence, these digital tools will transform how transformers are managed throughout their lifecycle.

## Structure and Organization of This Book

This book is organized to provide a comprehensive understanding of transformers, from basic principles to advanced applications and future trends:

**Chapter 1: Fundamentals of Transformers** introduces the basic concepts, historical development, and importance of transformers in electrical systems.

**Chapter 2: Working Principles of Transformers** explains the electromagnetic foundations, including Faraday’s Law, mutual induction, and the ideal transformer concept.

**Chapter 3: Construction and Components** details the physical construction of transformers, including cores, windings, insulation systems, tanks, and auxiliary components.

**Chapter 4: Types of Transformers** surveys the diverse transformer types categorized by voltage level, construction, core material, purpose, and phases.

**Chapter 5: Transformer Operation** covers operational aspects including no-load and load operation, voltage regulation, parallel operation, and inrush current phenomena.

**Chapter 6: Transformer Losses and Efficiency** examines core losses, copper losses, stray losses, efficiency calculation, and optimization strategies.

**Chapter 7: Transformer Testing** presents comprehensive testing methodologies including routine tests, type tests, special tests, and diagnostic techniques.

**Chapter 8: Three-Phase Transformers** focuses on three-phase connections, vector groups, and three-phase transformer banks.

**Chapter 9: Special Transformers** explores specialized designs including autotransformers, instrument transformers, and various application-specific types.

**Chapter 10: Applications of Transformers** examines how transformers are applied across power generation, transmission, distribution, industrial, commercial, and specialized settings.

**Chapter 11: Modern Trends and Future Developments** looks toward emerging technologies, materials, and approaches that will shape transformer evolution.

The book includes numerous diagrams, examples, and case studies to illustrate concepts and their practical application. Appendices provide additional reference material, mathematical derivations, and design examples to supplement the main text.

Whether you are a student seeking to understand transformer fundamentals, a practicing engineer applying transformer technology, or a researcher exploring new developments, this book aims to provide the knowledge and insights you need to master this essential technology.

As we proceed through these chapters, we will see how the simple yet profound principle of electromagnetic induction, discovered nearly two centuries ago, has evolved into the sophisticated transformer technology that powers our modern world—and how this technology continues to evolve to meet the challenges of our changing energy landscape.# Table of Contents

## Front Matter


- Title Page
- Copyright Page
- Dedication
- Preface
- Acknowledgments
- Introduction

- List of Figures
- List of Tables
- List of Symbols and Abbreviations

## Chapter 1: Fundamentals of Transformers

1.1 Definition and Basic Principles 1.1.1 The Transformer Concept 1.1.2 Basic Operation 1.1.3 Voltage and Current Relationships

1.2 Historical Development 1.2.1 Early Discoveries in Electromagnetism 1.2.2 First Practical Transformers 1.2.3 The War of Currents 1.2.4 Evolution of Modern Transformers

1.3 Importance in Electrical Systems 1.3.1 Role in Power Generation 1.3.2 Role in Transmission and Distribution 1.3.3 Role in Utilization 1.3.4 Economic Impact

## Chapter 2: Working Principles of Transformers

2.1 Faraday’s Law and Electromagnetic Induction 2.1.1 Faraday’s Experiments 2.1.2 Mathematical Expression of Faraday’s Law 2.1.3 Application to Transformers

2.2 Mutual Induction 2.2.1 Concept of Mutual Inductance 2.2.2 Coupling Coefficient 2.2.3 Leakage Flux

2.3 EMF Equation 2.3.1 Derivation of the EMF Equation 2.3.2 RMS Values 2.3.3 Voltage Ratio and Turns Ratio

2.4 Ideal Transformer Concept 2.4.1 Assumptions in the Ideal Transformer 2.4.2 Voltage and Current Relationships 2.4.3 Power Relationships 2.4.4 Impedance Transformation

## Chapter 3: Construction and Components

3.1 Core Materials and Designs 3.1.1 Silicon Steel Properties 3.1.2 Grain-Oriented Steel 3.1.3 Amorphous Metals 3.1.4 Core Construction Types 3.1.5 Laminations and Eddy Current Reduction

3.2 Winding Types and Arrangements 3.2.1 Conductor Materials 3.2.2 Cylindrical Windings 3.2.3 Disc Windings 3.2.4 Helical Windings 3.2.5 Foil Windings 3.2.6 Transposition Techniques

3.3 Insulation Systems 3.3.1 Solid Insulation Materials 3.3.2 Liquid Insulation Materials 3.3.3 Insulation Coordination 3.3.4 Aging and Degradation Mechanisms

3.4 Cooling Systems 3.4.1 Natural Air Cooling (AN) 3.4.2 Forced Air Cooling (AF) 3.4.3 Oil Immersed Natural Cooling (ONAN) 3.4.4 Oil Immersed Forced Cooling (ONAF) 3.4.5 Directed Oil Flow Cooling (ODAF) 3.4.6 Water Cooling Systems

3.5 Auxiliary Components 3.5.1 Bushings 3.5.2 Tap Changers 3.5.3 Conservators 3.5.4 Breathers 3.5.5 Buchholz Relays 3.5.6 Pressure Relief Devices 3.5.7 Temperature Indicators 3.5.8 Oil Level Indicators

## Chapter 4: Types of Transformers

4.1 Based on Voltage Level 4.1.1 Step-up Transformers 4.1.2 Step-down Transformers 4.1.3 Isolation Transformers

4.2 Based on Construction 4.2.1 Core-type Transformers 4.2.2 Shell-type Transformers 4.2.3 Berry-type Transformers

4.3 Based on Core Material 4.3.1 Iron Core Transformers 4.3.2 Ferrite Core Transformers 4.3.3 Air Core Transformers 4.3.4 Amorphous Core Transformers

4.4 Based on Purpose 4.4.1 Power Transformers 4.4.2 Distribution Transformers 4.4.3 Instrument Transformers 4.4.4 Testing Transformers 4.4.5 Furnace Transformers

4.5 Based on Phases 4.5.1 Single-phase Transformers 4.5.2 Three-phase Transformers 4.5.3 Multi-phase Transformers

4.6 Special Types 4.6.1 Autotransformers 4.6.2 Tap-changing Transformers 4.6.3 Phase-shifting Transformers 4.6.4 Grounding Transformers 4.6.5 Reactors

## Chapter 5: Transformer Operation

5.1 No-load Operation 5.1.1 Magnetizing Current 5.1.2 Core Losses 5.1.3 Phasor Diagram at No-load

5.2 Load Operation 5.2.1 Effect of Connected Load 5.2.2 Phasor Diagram on Load 5.2.3 Equivalent Circuit 5.2.4 Parameter Determination

5.3 Voltage Regulation 5.3.1 Definition and Importance 5.3.2 Calculation Methods 5.3.3 Factors Affecting Regulation 5.3.4 Improvement Techniques

5.4 Parallel Operation 5.4.1 Conditions for Parallel Operation 5.4.2 Load Sharing 5.4.3 Circulating Currents 5.4.4 Practical Considerations

5.5 Inrush Current Phenomenon 5.5.1 Causes of Inrush Current 5.5.2 Characteristics and Waveform 5.5.3 Effects on System and Protection 5.5.4 Mitigation Techniques

## Chapter 6: Transformer Losses and Efficiency

6.1 Core Losses 6.1.1 Hysteresis Losses 6.1.2 Eddy Current Losses 6.1.3 Factors Affecting Core Losses 6.1.4 Reduction Techniques

6.2 Copper Losses 6.2.1 $I^2R$ Losses 6.2.2 Eddy Currents in Conductors 6.2.3 Factors Affecting Copper Losses 6.2.4 Reduction Techniques

6.3 Stray Losses 6.3.1 Stray Flux in Structural Parts 6.3.2 Circulating Currents 6.3.3 Measurement and Calculation 6.3.4 Reduction Techniques

6.4 Efficiency Calculation 6.4.1 Efficiency Formula 6.4.2 Variation with Load 6.4.3 Effect of Power Factor 6.4.4 Efficiency Standards

6.5 Maximum Efficiency Condition 6.5.1 Derivation 6.5.2 Design Implications 6.5.3 Practical Considerations

6.6 All-day Efficiency 6.6.1 Definition and Importance 6.6.2 Calculation Method 6.6.3 Application to Distribution Transformers 6.6.4 Economic Considerations

## Chapter 7: Transformer Testing

7.1 Open Circuit Test 7.1.1 Test Setup and Procedure 7.1.2 Measurement of Core Losses 7.1.3 Determination of Magnetizing Current 7.1.4 Equivalent Circuit Parameters

7.2 Short Circuit Test 7.2.1 Test Setup and Procedure 7.2.2 Measurement of Copper Losses 7.2.3 Determination of Impedance Voltage 7.2.4 Equivalent Circuit Parameters

7.3 Sumpner Test 7.3.1 Back-to-Back Test Arrangement 7.3.2 Advantages and Limitations 7.3.3 Test Procedure 7.3.4 Calculations and Interpretations

7.4 Polarity Test 7.4.1 Importance of Polarity 7.4.2 Test Methods 7.4.3 Interpretation of Results

7.5 Ratio Test 7.5.1 Importance of Turns Ratio 7.5.2 Test Methods 7.5.3 Accuracy Considerations

7.6 Insulation Resistance Test 7.6.1 Purpose and Importance 7.6.2 Test Equipment 7.6.3 Test Procedure 7.6.4 Interpretation of Results

7.7 Dissolved Gas Analysis (DGA) 7.7.1 Principle and Theory 7.7.2 Gas Generation Mechanisms 7.7.3 Sampling and Analysis Methods 7.7.4 Interpretation Techniques 7.7.5 Fault Diagnosis

7.8 Frequency Response Analysis (FRA) 7.8.1 Principle and Theory 7.8.2 Test Equipment 7.8.3 Test Procedure 7.8.4 Interpretation Techniques 7.8.5 Mechanical Fault Detection

7.9 Other Important Tests 7.9.1 Temperature Rise Test 7.9.2 Impulse Test 7.9.3 Partial Discharge Test 7.9.4 Tan Delta Test 7.9.5 Oil Quality Tests

7.10 Diagnostic Testing Programs 7.10.1 Acceptance Testing 7.10.2 Routine Maintenance Testing 7.10.3 Condition-Based Testing 7.10.4 Failure Investigation

## Chapter 8: Three-Phase Transformers

8.1 Introduction to Three-Phase Transformers 8.1.1 Comparison with Single-Phase Transformers 8.1.2 Advantages and Applications 8.1.3 Construction Features

8.2 Three-phase Connections 8.2.1 Star-Star (Y-y) 8.2.2 Delta-Delta (D-d) 8.2.3 Star-Delta (Y-d) 8.2.4 Delta-Star (D-y) 8.2.5 Zigzag Connections 8.2.6 Connection Selection Criteria

8.3 Vector Groups 8.3.1 Vector Group Notation 8.3.2 Clock-Hour System 8.3.3 Phase Displacement 8.3.4 Common Vector Groups 8.3.5 Applications of Different Vector Groups

8.4 Three-phase Transformer Banks 8.4.1 Three Single-Phase Units 8.4.2 Integrated Three-Phase Units 8.4.3 Advantages and Disadvantages 8.4.4 Open-Delta (V-V) Connection 8.4.5 Scott Connection

## Chapter 9: Special Transformers

9.1 Autotransformers 9.1.1 Principle of Operation 9.1.2 Advantages and Limitations 9.1.3 Applications 9.1.4 Design Considerations

9.2 Instrument Transformers 9.2.1 Current Transformers (CT) 9.2.2 Potential Transformers (PT) 9.2.3 Combined Instrument Transformers 9.2.4 Accuracy Classes 9.2.5 Applications

9.3 Welding Transformers 9.3.1 Special Requirements 9.3.2 Design Features 9.3.3 Control Methods 9.3.4 Applications

9.4 Pulse Transformers 9.4.1 Operating Principles 9.4.2 Design Considerations 9.4.3 Applications in Electronics 9.4.4 High Voltage Pulse Applications

9.5 High-frequency Transformers 9.5.1 Core Materials 9.5.2 Winding Considerations 9.5.3 Applications in Power Electronics 9.5.4 Design Challenges

## Chapter 10: Applications of Transformers

10.1 Power Generation and Transmission 10.1.1 Generator Step-up Transformers 10.1.2 Transmission Transformers 10.1.3 Substation Transformers 10.1.4 Phase-Shifting Applications

10.2 Distribution Systems 10.2.1 Primary Distribution 10.2.2 Secondary Distribution 10.2.3 Pole-Mounted Transformers 10.2.4 Pad-Mounted Transformers 10.2.5 Underground Distribution

10.3 Industrial Applications 10.3.1 Factory Power Distribution 10.3.2 Arc Furnace Transformers 10.3.3 Rectifier Transformers 10.3.4 Machine Tool Transformers 10.3.5 Variable Frequency Drive Applications

10.4 Commercial and Residential Applications 10.4.1 Building Power Distribution 10.4.2 Lighting Transformers 10.4.3 Isolation Transformers 10.4.4 Control Transformers 10.4.5 HVAC Applications

10.5 Specialized Applications 10.5.1 Traction Transformers 10.5.2 Marine Transformers 10.5.3 Mobile Substations 10.5.4 Testing Applications 10.5.5 Medical Applications

## Chapter 11: Modern Trends and Future Developments

11.1 Smart Transformers 11.1.1 Integrated Monitoring Systems 11.1.2 Communication Capabilities 11.1.3 Advanced Diagnostics 11.1.4 Grid Integration Features

11.2 Advancements in Materials 11.2.1 Core Materials Evolution 11.2.2 Insulation Innovations 11.2.3 Superconducting Applications 11.2.4 Nano-materials in Transformers

11.3 Energy Efficiency Improvements 11.3.1 Efficiency Standards Evolution 11.3.2 Loss Reduction Techniques 11.3.3 Total Cost of Ownership Approach 11.3.4 Ultra-Efficient Designs

11.4 Integration with Renewable Energy 11.4.1 Wind Farm Transformers 11.4.2 Solar Power Applications 11.4.3 Energy Storage Integration 11.4.4 Microgrid Applications

11.5 Digital Twins and IoT Integration 11.5.1 Digital Twin Concept 11.5.2 IoT Sensor Networks 11.5.3 Predictive Maintenance 11.5.4 Asset Management Systems

11.6 Environmental and Sustainability Considerations 11.6.1 Eco-friendly Insulating Fluids 11.6.2 Noise Reduction Techniques 11.6.3 End-of-Life Management 11.6.4 Carbon Footprint Reduction

## Appendices

Appendix A: Mathematical Derivations Appendix B: Transformer Design Examples Appendix C: Standards and Regulations Appendix D: Transformer Selection Guide

## Back Matter

- Glossary
- References
- Index# List of Figures

## Chapter 1: Fundamentals of Transformers

Figure 1.1: Basic Transformer Structure Figure 1.2: Faraday’s Electromagnetic Induction Experiment Figure 1.3: Early Commercial Transformer (1885-1890) Figure 1.4: Modern Power Transformer Figure 1.5: Transformer Applications in Power Systems Figure 1.6: Basic Transformer Operation Principle

## Chapter 2: Working Principles of Transformers

Figure 2.1: Electromagnetic Induction in Transformer Windings Figure 2.2: Magnetic Flux Paths in a Transformer Core Figure 2.3: Mutual Induction Between Coupled Coils Figure 2.4: B-H Curve for Transformer Core Materials Figure 2.5: Hysteresis Loop for Different Core Materials Figure 2.6: Ideal Transformer Circuit Model Figure 2.7: Phasor Diagram for Ideal Transformer Figure 2.8: Practical Transformer Equivalent Circuit Figure 2.9: Referred Equivalent Circuit (Secondary to Primary) Figure 2.10: No-Load Phasor Diagram

Figure 2.11: Load Phasor Diagram (Resistive Load) Figure 2.12: Load Phasor Diagram (Inductive Load) Figure 2.13: Load Phasor Diagram (Capacitive Load)

## Chapter 3: Construction and Components

Figure 3.1: Core-Type Transformer Construction Figure 3.2: Shell-Type Transformer Construction Figure 3.3: Transformer Core Laminations Figure 3.4: Step-Lap Joint Construction Figure 3.5: Grain-Oriented Silicon Steel Microstructure Figure 3.6: Amorphous Metal Core Structure Figure 3.7: Concentric Winding Arrangement Figure 3.8: Disc Winding Construction Figure 3.9: Helical Winding Construction Figure 3.10: Foil Winding Construction Figure 3.11: Continuously Transposed Conductor (CTC) Figure 3.12: Paper Insulation System Figure 3.13: Oil Immersed Transformer Cooling System Figure 3.14: ONAN Cooling Arrangement Figure 3.15: ONAF Cooling Arrangement Figure 3.16: OFAF Cooling Arrangement Figure 3.17: ODAF Cooling Arrangement Figure 3.18: Transformer Tank Construction Figure 3.19: Conservator System Figure 3.20: Buchholz Relay Installation Figure 3.21: Silica Gel Breather Figure 3.22: Porcelain Bushing Construction Figure 3.23: Condenser Bushing Construction Figure 3.24: Off-Load Tap Changer Mechanism Figure 3.25: On-Load Tap Changer Mechanism Figure 3.26: Pressure Relief Device Figure 3.27: Temperature Indicators Figure 3.28: Complete Transformer Assembly

## Chapter 4: Types of Transformers

Figure 4.1: Step-Up Transformer Configuration Figure 4.2: Step-Down Transformer Configuration Figure 4.3: Isolation Transformer Configuration Figure 4.4: Core-Type vs. Shell-Type Construction Comparison Figure 4.5: Berry-Type Transformer Construction Figure 4.6: Toroidal Transformer Construction Figure 4.7: Iron Core vs. Ferrite Core Comparison Figure 4.8: Air Core Transformer Design Figure 4.9: Power Transformer Installation Figure 4.10: Distribution Transformer Installation Figure 4.11: Current Transformer Construction Figure 4.12: Potential Transformer Construction Figure 4.13: Audio Transformer Design Figure 4.14: RF Transformer Design Figure 4.15: Pulse Transformer Design Figure 4.16: Single-Phase vs. Three-Phase Transformer Comparison Figure 4.17: Autotransformer Construction Figure 4.18: Phase-Shifting Transformer Configuration Figure 4.19: Grounding Transformer Connection Figure 4.20: Rectifier Transformer Design Figure 4.21: Furnace Transformer Installation Figure 4.22: Mobile Transformer

Unit Figure 4.23: Oil-Filled Transformer Cross-Section Figure 4.24: Dry-Type Transformer Cross-Section Figure 4.25: Cast Resin Transformer Construction

## Chapter 5: Transformer Operation

Figure 5.1: No-Load Operation Circuit Figure 5.2: Excitation Current Waveform Figure 5.3: No-Load Phasor Diagram Figure 5.4: Load Operation Circuit Figure 5.5: Load Current Components Figure 5.6: Voltage Drop Under Load Figure 5.7: Load Phasor Diagram Figure 5.8: Voltage Regulation Curve Figure 5.9: Parallel Operation of Transformers Figure 5.10: Load Sharing Between Parallel Transformers Figure 5.11: Circulating Current in Parallel Transformers Figure 5.12: Inrush Current Waveform Figure 5.13: Core Saturation During Inrush Figure 5.14: Harmonic Spectrum of Transformer Magnetizing Current Figure 5.15: K-Factor Transformer Design Figure 5.16: Transformer Loading Guide Chart Figure 5.17: Effect of Overloading on Insulation Life Figure 5.18: Transformer Response to System Overvoltage Figure 5.19: External Short Circuit Effects Figure 5.20: Geomagnetic Disturbance Effects on Transformers

## Chapter 6: Transformer Losses and Efficiency

Figure 6.1: Core Loss Components Figure 6.2: Hysteresis Loop and Energy Loss Figure 6.3: Eddy Current Paths in Laminations Figure 6.4: Effect of Lamination Thickness on Eddy Current Loss Figure 6.5: Copper Loss Distribution in Windings Figure 6.6: Temperature Effect on Winding Resistance Figure 6.7: Stray Loss Mechanisms Figure 6.8: Eddy Current Patterns in Structural Components Figure 6.9: Efficiency vs. Load Curve Figure 6.10: Effect of Power Factor on Efficiency Figure 6.11: Maximum Efficiency Point Determination Figure 6.12: Typical Load Cycle for Distribution Transformer Figure 6.13: All-Day Efficiency Calculation Example Figure 6.14: Core Loss Reduction Techniques Figure 6.15: Copper Loss Reduction Techniques Figure 6.16: Stray Loss Reduction Methods Figure 6.17: Efficiency Standards Comparison Figure 6.18: Total Ownership Cost Analysis Chart

## Chapter 7: Transformer Testing

Figure 7.1: Open Circuit Test Setup Figure 7.2: Open Circuit Test Measurement Circuit Figure 7.3: Short Circuit Test Setup Figure 7.4: Short Circuit Test Measurement Circuit Figure 7.5: Sumpner Test

Arrangement Figure 7.6: Polarity Test Setup Figure 7.7: Transformer Turn Ratio Test Setup Figure 7.8: Insulation Resistance Test Connection Diagram Figure 7.9: Polarization Index Measurement Figure 7.10: DGA Sampling Method Figure 7.11: Gas Chromatograph for DGA Figure 7.12: Duval Triangle for DGA Interpretation Figure 7.13: Rogers Ratio Chart for Fault Diagnosis Figure 7.14: DGA Trend Analysis Chart Figure 7.15: FRA Test Setup Figure 7.16: FRA Signature Patterns for Different Fault Types Figure 7.17: Temperature Rise Test Arrangement Figure 7.18: Impulse Test Circuit Figure 7.19: Impulse Waveform Parameters Figure 7.20: Induced Overvoltage Test Setup Figure 7.21: Partial Discharge Measurement Circuit Figure 7.22: Noise Level Test Arrangement Figure 7.23: Zero-Sequence Impedance Test Circuit Figure 7.24: Winding Resistance Measurement Setup Figure 7.25: Transformer Diagnostic Testing Program Flowchart

## Chapter 8: Three-Phase Transformers

Figure 8.1: Three-Phase Transformer Core Construction Figure 8.2: Three-Phase vs. Single-Phase Bank Comparison Figure 8.3: Delta-Delta Connection Diagram Figure 8.4: Delta-Wye Connection Diagram Figure 8.5: Wye-Delta Connection Diagram Figure 8.6: Wye-Wye Connection Diagram Figure 8.7: Open-Delta (V-V) Connection Diagram Figure 8.8: Scott Connection Diagram Figure 8.9: T-Connection Diagram Figure 8.10: Vector Group Clock Notation System Figure 8.11: Dy11 Vector Diagram Figure 8.12: Yd1 Vector Diagram Figure 8.13: Dd0 Vector Diagram Figure 8.14: Yy0 Vector Diagram Figure 8.15: Three-Phase Transformer Bank Figure 8.16: Zero-Sequence Flux Paths Figure 8.17: Three-Phase Transformer Under Unbalanced Loading Figure 8.18: Neutral Current in Wye-Connected Transformer Figure 8.19: Vector Group Compatibility for Parallel Operation Figure 8.20: Three-Phase Transformer Testing Connections

## Chapter 9: Special Transformers

Figure 9.1: Autotransformer Construction Figure 9.2: Autotransformer vs. Two-Winding Transformer Comparison Figure 9.3: Step-Up Autotransformer Connection Figure 9.4: Step-Down Autotransformer Connection Figure 9.5: Current Transformer Construction Figure 9.6: CT Accuracy Class Curves Figure 9.7: CT Saturation Curve Figure 9.8: CT Connection in Metering Circuit Figure 9.9: CT Connection in Protection Circuit Figure 9.10: Potential Transformer Construction Figure 9.11: PT Accuracy Class Curves Figure 9.12: PT Connection in Metering Circuit Figure 9.13: Combined Instrument Transformer Design Figure 9.14: Electronic Instrument Transformer Principle

Figure 9.15: Welding Transformer Construction Figure 9.16: Welding Transformer Volt-Ampere Characteristic Figure 9.17: Welding Transformer Control System Figure 9.18: Pulse Transformer Construction Figure 9.19: Pulse Transformer Equivalent Circuit Figure 9.20: Pulse Waveform Parameters Figure 9.21: High-Frequency Transformer Core Materials Comparison Figure 9.22: High-Frequency Transformer Winding Techniques Figure 9.23: Switch-Mode Power Supply Transformer Figure 9.24: Phase-Shifting Transformer Construction Figure 9.25: Quadrature Booster Configuration Figure 9.26: Zigzag Transformer Connection Figure 9.27: Grounding Transformer Installation Figure 9.28: Isolation Transformer with Faraday Shield Figure 9.29: Medical Isolation Transformer Installation Figure 9.30: Audio Transformer Frequency Response Curve Figure 9.31: Audio Transformer Impedance Matching Circuit

## Chapter 10: Applications of Transformers

Figure 10.1: Generator Step-Up Transformer Installation Figure 10.2: Transmission Substation Layout Figure 10.3: Substation Transformer Installation Figure 10.4: Phase-Shifting Transformer in Power Flow Control Figure 10.5: HVDC Converter Transformer Arrangement Figure 10.6: Primary Distribution System Layout Figure 10.7: Secondary Distribution System Layout Figure 10.8: Pad-Mounted Transformer Installation Figure 10.9: Pole-Mounted Transformer Installation Figure 10.10: Underground Distribution Transformer Vault Figure 10.11: Industrial Power Distribution System Figure 10.12: Arc Furnace Transformer Installation Figure 10.13: Rectifier Transformer for Aluminum Smelting Figure 10.14: Variable Frequency Drive System with Transformer Figure 10.15: Machine Tool Transformer Application Figure 10.16: Commercial Building Power Distribution Figure 10.17: Lighting Transformer Installation Figure 10.18: HVAC System Transformer Application Figure 10.19: Residential Service Transformer Connection Figure 10.20: Appliance Transformer Examples Figure 10.21: Railway Traction Transformer Installation Figure 10.22: Marine Transformer in Shipboard Application Figure 10.23: Mining Transformer Installation Figure 10.24: Mobile Substation Configuration Figure 10.25: High-Voltage Testing Transformer

## Chapter 11: Modern Trends and Future Developments

Figure 11.1: Smart Transformer Architecture Figure 11.2: Integrated Monitoring System Components Figure 11.3: Smart Transformer Communication Network Figure 11.4: Advanced Diagnostic System Interface Figure 11.5: Smart Grid Integration Diagram Figure 11.6:

Advanced Core Material Performance Comparison Figure 11.7: Modern Insulation System Structure Figure 11.8: High-Temperature Superconducting Transformer Concept Figure 11.9: Natural Ester Fluid Properties Comparison Figure 11.10: Nanocomposite Material Structure Figure 11.11: Efficiency Standards Evolution Timeline Figure 11.12: Amorphous Core Transformer Construction Figure 11.13: Loss Reduction Impact on Carbon Footprint Figure 11.14: Solid-State Transformer Block Diagram Figure 11.15: Solid-State Transformer Topologies Figure 11.16: Solid-State vs. Conventional Transformer Comparison Figure 11.17: Wind Farm Transformer Requirements Figure 11.18: Solar Power Transformer Integration Figure 11.19: Energy Storage System with Transformer Figure 11.20: Microgrid Architecture with Transformers Figure 11.21: Digital Twin Concept Illustration Figure 11.22: IoT Sensor Network for Transformers Figure 11.23: Predictive Maintenance System Architecture Figure 11.24: Asset Management Optimization Framework Figure 11.25: Transformer Life Cycle Assessment Figure 11.26: Circular Economy Approach for Transformers Figure 11.27: Future Transformer Technology Roadmap# List of Symbols and Abbreviations

# Symbols

## General Electrical Quantities

| Symbol | Description | Unit |
|---|---|---|
| V | Voltage | Volt (V) |
| I | Current | Ampere (A) |
| R | Resistance | Ohm (Ω) |
| X | Reactance | Ohm (Ω) |
| Z | Impedance | Ohm (Ω) |
| P | Active power | Watt (W) |
| Q | Reactive power | Volt-ampere reactive (VAr) |
| S | Apparent power | Volt-ampere (VA) |
| f | Frequency | Hertz (Hz) |
| ω | Angular frequency (2πf) | Radian per second (rad/s) |
| φ | Phase angle | Radian (rad) or Degree (°) |
| pf | Power factor (cos φ) | Dimensionless |

## Magnetic Quantities

| Symbol | Description | Unit |
|---|---|---|
| | Magnetic flux density | |

| | | |
|---|---|---|
| B | | Tesla (T) |
| H | Magnetic field intensity | Ampere per meter (A/m) |
| Φ | Magnetic flux | Weber (Wb) |
| μ | Permeability | Henry per meter (H/m) |
| $\mu_0$ | Permeability of free space | $4\pi \times 10^{-7}$ H/m |
| $\mu_r$ | Relative permeability | Dimensionless |
| $\mathscr{R}$ | Reluctance | Ampere-turn per weber (A-t/Wb) |
| $\mathscr{F}$ | Magnetomotive force (MMF) | Ampere-turn (A-t) |

## Transformer-Specific Symbols

| Symbol | Description | Unit |
|---|---|---|
| $N_1$ | Number of turns in primary winding | Dimensionless |
| $N_2$ | Number of turns in secondary winding | Dimensionless |
| a | Turns ratio ($N_1/N_2$) | Dimensionless |
| $E_1$ | Primary induced EMF | Volt (V) |
| $E_2$ | Secondary induced EMF | Volt (V) |
| $V_1$ | Primary terminal voltage | Volt (V) |
| $V_2$ | Secondary terminal voltage | Volt (V) |
| $I_1$ | Primary current | Ampere (A) |
| $I_2$ | Secondary current | Ampere (A) |
| $I_0$ | No-load current | Ampere (A) |
| $I_m$ | Magnetizing current | Ampere (A) |
| $I_v$ | Core loss component of no-load current | Ampere (A) |
| $R_1$ | Primary winding resistance | Ohm (Ω) |
| $R_2$ | Secondary winding resistance | Ohm (Ω) |
| $X_1$ | Primary leakage reactance | Ohm (Ω) |
| $X_2$ | Secondary leakage reactance | Ohm (Ω) |
| $R_1'$ | Primary resistance referred to secondary | Ohm (Ω) |
| $X_1'$ | Primary reactance referred to secondary | Ohm (Ω) |
| $R_2'$ | Secondary resistance referred to primary | Ohm (Ω) |
| $X_2'$ | Secondary reactance referred to primary | Ohm (Ω) |
| $R_e$ | Equivalent resistance | Ohm (Ω) |

| | | |
|---|---|---|
| $X_e$ | Equivalent reactance | Ohm (Ω) |
| $Z_e$ | Equivalent impedance | Ohm (Ω) |
| $R_m$ | Core loss equivalent resistance | Ohm (Ω) |
| $X_m$ | Magnetizing reactance | Ohm (Ω) |
| $P_k$ | Short-circuit power loss | Watt (W) |
| $P_0$ | No-load power loss | Watt (W) |
| $P_u$ | Copper loss | Watt (W) |
| $P_i$ | Iron loss | Watt (W) |
| $P_h$ | Hysteresis loss | Watt (W) |
| $P_e$ | Eddy current loss | Watt (W) |
| $P_s$ | Stray loss | Watt (W) |
| $\eta$ | Efficiency | Dimensionless or % |
| $\varepsilon$ | Voltage regulation | Dimensionless or % |
| $u_k$ | Short-circuit impedance voltage | % |
| $Z_0$ | Zero-sequence impedance | Ohm (Ω) |
| $Z_1$ | Positive-sequence impedance | Ohm (Ω) |
| $Z_2$ | Negative-sequence impedance | Ohm (Ω) |

## Thermal Quantities

| Symbol | Description | Unit |
|---|---|---|
| $\theta$ | Temperature | Degree Celsius (°C) |
| $\Delta\theta$ | Temperature rise | Kelvin (K) or Degree Celsius (°C) |
| $\theta_a$ | Ambient temperature | Degree Celsius (°C) |
| $\theta_h$ | Hot-spot temperature | Degree Celsius (°C) |
| $\theta_o$ | Top oil temperature | Degree Celsius (°C) |
| $\tau$ | Thermal time constant | Hour (h) or Minute (min) |

## Material Properties

| Symbol | Description | Unit |
|---|---|---|
| $\rho$ | Resistivity | Ohm-meter (Ω·m) |
| $\sigma$ | Conductivity | Siemens per meter (S/m) |
| $\alpha$ | Temperature coefficient of resistance | Per Kelvin ($K^{-1}$) |
| $k_h$ | Hysteresis coefficient | Dimensionless |
| $k_e$ | Eddy current coefficient | Dimensionless |

| | | |
|---|---|---|
| n | Steinmetz exponent | Dimensionless |

# Abbreviations

## General Terms

| Abbreviation | Full Form |
|---|---|
| AC | Alternating Current |
| DC | Direct Current |
| EMF | Electromotive Force |
| HV | High Voltage |
| LV | Low Voltage |
| MV | Medium Voltage |
| EHV | Extra High Voltage |
| UHV | Ultra High Voltage |
| RMS | Root Mean Square |
| THD | Total Harmonic Distortion |
| PF | Power Factor |
| PU | Per Unit |
| NLL | No-Load Loss |
| LL | Load Loss |
| TOC | Total Ownership Cost |
| BIL | Basic Impulse Level |
| POW | Power Outage Withstand |

## Transformer Types and Components

| Abbreviation | Full Form |
|---|---|
| PT | Power Transformer |
| DT | Distribution Transformer |
| GSU | Generator Step-Up (transformer) |
| SST | Solid-State Transformer |
| CT | Current Transformer |
| PT/VT | Potential Transformer/Voltage Transformer |
| OLTC | On-Load Tap Changer |
| DETC | De-Energized Tap Changer |
| LTC | Load Tap Changer |
| AVR | Automatic Voltage Regulator |
| CTC | Continuously Transposed Conductor |

| | |
|---|---|
| GOES | Grain-Oriented Electrical Steel |
| CRGOS | Cold-Rolled Grain-Oriented Silicon (steel) |
| HiB | High-Permeability (steel) |
| AMDT | Amorphous Metal Distribution Transformer |
| HTS | High-Temperature Superconducting (transformer) |

## Cooling Systems

| Abbreviation | Full Form |
|---|---|
| AN | Air Natural |
| AF | Air Forced |
| ONAN | Oil Natural Air Natural |
| ONAF | Oil Natural Air Forced |
| OFAF | Oil Forced Air Forced |
| OFWF | Oil Forced Water Forced |
| ODAF | Oil Directed Air Forced |
| ODWF | Oil Directed Water Forced |

## Testing and Diagnostics

| Abbreviation | Full Form |
|---|---|
| DGA | Dissolved Gas Analysis |
| FRA | Frequency Response Analysis |
| PD | Partial Discharge |
| TTR | Transformer Turn Ratio |
| IR | Insulation Resistance |
| PI | Polarization Index |
| DAR | Dielectric Absorption Ratio |
| SFRA | Sweep Frequency Response Analysis |
| OLTC-DGA | On-Load Tap Changer Dissolved Gas Analysis |
| FDS | Frequency Domain Spectroscopy |
| RVM | Recovery Voltage Measurement |
| PDC | Polarization and Depolarization Current |
| DFR | Dielectric Frequency Response |
| DF | Dissipation Factor |
| PF | Power Factor (of insulation) |
| tan δ | Tangent Delta (dissipation factor) |

## Insulating Materials and Fluids

| Abbreviation | Full Form |
|---|---|
| MO | Mineral Oil |
| NE | Natural Ester |
| SE | Synthetic Ester |
| FR3 | Fire-Resistant Natural Ester Fluid (brand name) |
| PCB | Polychlorinated Biphenyl |
| TUP | Thermally Upgraded Paper |
| DDP | Diamond Dotted Paper |
| PSP | Presspahn |
| DEC | Dielectric Epoxy Coating |

## Standards and Organizations

| Abbreviation | Full Form |
|---|---|
| IEEE | Institute of Electrical and Electronics Engineers |
| IEC | International Electrotechnical Commission |
| ANSI | American National Standards Institute |
| NEMA | National Electrical Manufacturers Association |
| BS | British Standard |
| DIN | Deutsches Institut für Normung (German Institute for Standardization) |
| JIS | Japanese Industrial Standards |
| CIGRE | Conseil International des Grands Réseaux Électriques (International Council on Large Electric Systems) |
| DOE | Department of Energy |
| MEPS | Minimum Energy Performance Standards |

## Fault Gases and DGA

| Abbreviation | Full Form |
|---|---|
| $H_2$ | Hydrogen |
| $CH_4$ | Methane |

| | |
|---|---|
| $C_2H_6$ | Ethane |
| $C_2H_4$ | Ethylene |
| $C_2H_2$ | Acetylene |
| CO | Carbon Monoxide |
| $CO_2$ | Carbon Dioxide |
| TDCG | Total Dissolved Combustible Gas |
| ppm | Parts Per Million |

### Smart Grid and Monitoring

| Abbreviation | Full Form |
|---|---|
| IED | Intelligent Electronic Device |
| RTU | Remote Terminal Unit |
| SCADA | Supervisory Control and Data Acquisition |
| IoT | Internet of Things |
| DT | Digital Twin |
| CBM | Condition-Based Maintenance |
| PdM | Predictive Maintenance |
| TMS | Transformer Monitoring System |
| OLTC-MS | On-Load Tap Changer Monitoring System |
| BMS | Bushing Monitoring System |
| IIoT | Industrial Internet of Things |
| ML | Machine Learning |
| AI | Artificial Intelligence |

### Three-Phase Connections

| Abbreviation | Full Form |
|---|---|
| Dd | Delta-delta connection |
| Dy | Delta-wye connection |
| Yd | Wye-delta connection |
| Yy | Wye-wye connection |
| Dz | Delta-zigzag connection |
| Yz | Wye-zigzag connection |
| YNd | Wye with neutral-delta connection |
| YNy | Wye with neutral-wye connection |

## 1.1 Definition and Basic Concepts

A **transformer** is a static electrical device that transfers electrical energy from one circuit to another through electromagnetic induction without changing the frequency. It’s essentially a voltage control device widely used in the distribution and transmission of alternating current power. Transformers can either increase (step-up) or decrease (step-down) voltage with corresponding changes in current to maintain power balance.

As passive electrical components, transformers serve as indispensable devices for the efficient management and distribution of electrical energy. These static (stationary) electromagnetic devices are designed to convert electrical energy from one voltage and current level to another, critically maintaining the same frequency. This transformation is achieved by magnetically linking two or more electrical circuits through a common oscillating magnetic field, which the transformer itself generates.

The core purpose of transformers is to precisely adjust voltage or current levels, a capability vital for the economical transmission of electrical power over long distances and its effective distribution to diverse loads, ranging from industrial facilities to residential homes. They act as crucial intermediaries, controlling and delivering electricity from large-scale generation points (grid stations) to individual consumption points.

Unlike rotating electrical machines such as motors and generators, transformers have no moving parts, which gives them several advantages: - No mechanical losses (friction or windage) - Higher efficiency - Lower maintenance requirements - Longer operational life

Transformers are rated in kilovolt-amperes (KVA) rather than kilowatts (KW) because copper loss depends on load current, while core loss depends on voltage and frequency. This KVA rating allows for the calculation of losses regardless of the power factor of the load.

## 1.2 Historical Development

The development of transformers represents one of the most significant milestones in the history of electrical engineering, fundamentally shaping how electrical power is generated, transmitted, and distributed worldwide.

### Early Discoveries and Foundations

The theoretical foundation for transformer operation was established in the early 19th century with Michael Faraday’s discovery of electromagnetic induction in 1831. Faraday demonstrated that a

changing magnetic field could induce an electric current in a nearby conductor, establishing the fundamental principle upon which all transformers operate.

## First Practical Transformers

The journey from theoretical concept to practical application took several decades:

- **1836**: Nicholas Callan, an Irish priest and scientist, created what is considered one of the earliest transformers, which he called an “induction coil.”
- **1870s**: Various inventors experimented with induction coils for applications like powering arc lighting systems, but these early devices were inefficient and unreliable.
- **1880s**: The breakthrough decade for transformer technology:
  - **1884**: The Ganz Company in Hungary, led by engineers Ottó Bláthy, Miksa Déri, and Károly Zipernowsky, developed the first commercially practical transformer, which they called a “ZBD transformer” (named after their initials).
  - **1885**: William Stanley, working for George Westinghouse, developed an improved transformer design that became the basis for commercial power distribution in the United States.
  - **1886**: The first commercial power transmission system using transformers was installed in Great Barrington, Massachusetts.

## The War of Currents

The development of efficient transformers played a crucial role in the famous “War of Currents” between Thomas Edison’s direct current (DC) system and George Westinghouse’s alternating current (AC) system in the late 1880s and early 1890s:

- Edison promoted DC power, which couldn’t be efficiently transformed to different voltage levels, limiting transmission distances.
- Westinghouse, with Nikola Tesla’s AC system and efficient transformers, demonstrated that electricity could be transmitted over long distances at high voltage (reducing losses) and then stepped down to safe levels for consumer use.

The ability to transform voltage levels efficiently was the decisive advantage that led to AC becoming the dominant form of electrical power transmission and distribution worldwide.

## Evolution Through the 20th Century

Transformer technology continued to evolve throughout the 20th century:

- **1920s-1930s**: Development of improved core materials like silicon steel to reduce losses.
- **1950s-1960s**: Introduction of better insulation materials and cooling systems, allowing for higher capacity transformers.
- **1970s-1980s**: Advancements in design methodologies and manufacturing techniques.
- **1990s-2000s**: Integration of digital monitoring and control systems for improved reliability and efficiency.

### Modern Innovations

In recent decades, transformer technology has seen continued innovation:

- Development of amorphous metal cores with significantly reduced energy losses
- Introduction of high-temperature superconducting transformers
- Creation of solid-state transformers for specialized applications
- Integration of smart monitoring systems for predictive maintenance
- Designs optimized for renewable energy integration

This historical progression demonstrates how transformer technology has continuously evolved to meet the changing demands of electrical power systems, from the early days of electrification to today’s complex and interconnected power grids.

## 1.3 Importance in Electrical Power Systems

Transformers are fundamental components of modern electrical power systems, serving as the backbone of electricity transmission and distribution networks worldwide. Their importance can be understood through several key roles they play:

### Enabling Efficient Power Transmission

Perhaps the most critical function of transformers is enabling the efficient transmission of electrical power over long distances:

- **Voltage Step-Up at Generation**: At power plants, step-up transformers increase voltage (typically to 115kV-765kV) while decreasing current, which dramatically reduces transmission

losses. This is because power loss in transmission lines is proportional to the square of the current ($P = I^2R$).

- **Voltage Step-Down for Distribution**: At substations, step-down transformers reduce voltage to levels suitable for regional distribution (typically 4kV-35kV) and eventually to levels safe for consumer use (120V-240V for residential applications).

Without transformers, the efficient long-distance transmission of electrical power would be practically impossible, as the losses would be prohibitively high, making our modern electrical grid infeasible.

## System Isolation and Protection

Transformers provide crucial isolation between different parts of the electrical network:

- **Galvanic Isolation**: Transformers create electrical separation between circuits, preventing the flow of direct current and blocking transmission of DC fault components.
- **Fault Isolation**: By isolating different voltage levels, transformers help contain faults within specific sections of the power system, preventing cascading failures.
- **Ground Reference Management**: Transformers allow for the creation of new neutral points and ground references, enabling various grounding schemes that enhance system protection.

## Voltage Regulation and Power Quality

Transformers play a significant role in maintaining stable voltage levels and power quality:

- **Voltage Regulation**: Tap-changing transformers can adjust voltage levels to compensate for load variations and maintain stable voltage for consumers.
- **Harmonic Mitigation**: Certain transformer configurations (like delta-wye connections) can trap or block specific harmonic currents, improving power quality.
- **Phase Shifting**: Special transformers can adjust phase angles between voltage and current, helping to control power flow in complex networks.

## Enabling Interconnected Power Systems

Transformers make possible the interconnection of different power systems:

- **Grid Interconnection**: High-voltage transformers enable the connection of power systems operating at different voltage levels or with different characteristics.
- **International Power Exchange**: Transformers facilitate power exchange between countries with different system standards.
- **Renewable Integration**: Transformers are essential for integrating renewable energy sources (which often generate at variable or low voltages) into the main power grid.

### Economic Implications

The economic importance of transformers extends beyond their technical functions:

- **Cost Optimization**: By enabling high-voltage transmission, transformers significantly reduce the amount of conductor material needed for power lines and minimize energy losses, resulting in substantial economic savings.
- **Load Management**: Distribution transformers are strategically placed to optimize load distribution and minimize system costs.
- **Asset Longevity**: With proper maintenance, power transformers can operate reliably for 30-40 years or more, representing significant long-term infrastructure investments.

### Critical Infrastructure Protection

Transformers are considered critical infrastructure components:

- **Grid Resilience**: The strategic placement and redundancy of transformers enhance the resilience of power systems against natural disasters and other disruptions.
- **National Security**: Large power transformers are recognized as critical assets for national security, with many countries maintaining strategic reserves.

The fundamental importance of transformers in electrical power systems cannot be overstated. They are the enabling technology that makes our modern electrical infrastructure possible, facilitating the generation, transmission, and distribution of electrical power that powers our civilization.

## 1.4 Overview of Transformer Applications

Transformers find applications across a vast spectrum of industries and settings, from massive power grid installations to tiny electronic devices. This section provides an overview of the diverse applications of transformers in various sectors.

## Power System Applications

### Power Generation

- **Generator Step-Up Transformers**: Located at power plants to increase generator voltage (typically 15-25kV) to transmission levels (115-765kV)
- **Auxiliary Transformers**: Supply power to the auxiliary equipment within power plants
- **Excitation Transformers**: Provide power to generator excitation systems

### Power Transmission

- **High Voltage Transmission Transformers**: Enable long-distance power transfer with minimal losses
- **Phase-Shifting Transformers**: Control power flow between parallel transmission paths
- **HVDC Converter Transformers**: Interface between AC systems and High Voltage Direct Current (HVDC) transmission systems

### Power Distribution

- **Primary Distribution Transformers**: Step down transmission voltages to distribution levels (typically 4-35kV)
- **Secondary Distribution Transformers**: Further reduce voltage to utilization levels (120-600V)
- **Pad-Mounted Transformers**: Used in underground distribution systems in urban areas
- **Pole-Mounted Transformers**: Common in overhead distribution systems

### Substations

- **Substation Transformers**: Interface between transmission and distribution systems
- **Regulating Transformers**: Maintain voltage levels within acceptable limits
- **Grounding Transformers**: Provide neutral points for system grounding

## Industrial Applications

### Manufacturing Processes

- **Arc Furnace Transformers**: Supply high currents at controlled voltages for steel melting
- **Induction Heating Transformers**: Provide power for metal heating applications
- **Rectifier Transformers**: Supply power to DC conversion systems for electrochemical processes

### Welding Applications

- **Welding Transformers**: Provide high current at low voltage for arc welding
- **Resistance Welding Transformers**: Supply precisely controlled current pulses for spot welding

### Motor Drives and Control

- **Variable Frequency Drive Transformers**: Interface power systems with motor drive electronics
- **Control Transformers**: Provide isolated, stable voltage for control circuits
- **Isolation Transformers**: Protect sensitive equipment from power system disturbances

## Commercial and Residential Applications

### Building Infrastructure

- **Lighting Transformers**: Power low-voltage lighting systems
- **Elevator Transformers**: Supply power to elevator motors and control systems
- **HVAC System Transformers**: Power heating, ventilation, and air conditioning equipment

### Consumer Electronics

- **Power Adapters**: Convert mains voltage to levels required by electronic devices
- **Battery Chargers**: Provide appropriate voltage and current for charging batteries
- **Small Appliance Transformers**: Power household devices like doorbells and thermostats

## Specialized Applications

### Medical Equipment

- **Medical Isolation Transformers**: Provide electrical isolation for patient safety
- **MRI System Transformers**: Supply power to magnetic resonance imaging equipment
- **X-ray Machine Transformers**: Generate high voltages required for X-ray tubes

**Transportation Systems**

- **Railway Traction Transformers**: Power electric trains and trams
- **Electric Vehicle Charging Stations**: Convert grid power to appropriate charging voltages
- **Aircraft Power Systems**: Provide various voltage levels for avionics and other systems

**Telecommunications and IT**

- **Telecommunication Transformers**: Couple signals between circuits while providing isolation
- **Data Center Power Distribution**: Supply clean, reliable power to servers and networking equipment
- **UPS Systems**: Provide backup power during outages

**Audio and Entertainment**

- **Audio Transformers**: Match impedances and provide isolation in audio equipment
- **Output Transformers**: Couple amplifier output to speakers in tube amplifiers
- **Microphone Transformers**: Match microphone impedance to amplifier input

**Renewable Energy Systems**

- **Wind Turbine Transformers**: Step up the relatively low voltage from wind generators
- **Solar Inverter Transformers**: Interface photovoltaic systems with the grid
- **Grid Integration Transformers**: Connect renewable sources to transmission/distribution systems

## Scientific and Research Applications

- **High Voltage Test Transformers**: Generate very high voltages for insulation testing
- **Pulse Transformers**: Generate or transmit high-voltage pulses for research
- **Cryogenic Transformers**: Operate at extremely low temperatures

for specialized applications

This overview demonstrates the ubiquitous nature of transformers across virtually all sectors of modern society. From the largest power grid installations to the smallest electronic devices, transformers play a crucial role in enabling the efficient and safe use of electrical energy.

# 1.5 Basic Transformer Theory

At its core, a transformer operates on two fundamental electromagnetic principles: Faraday's Law of Electromagnetic Induction and the principle of mutual induction. Understanding these principles is essential for grasping how transformers function.

## Faraday's Law of Electromagnetic Induction

Faraday's Law states that an electromotive force (EMF) is induced in a conductor when it experiences a changing magnetic field. The magnitude of this induced EMF is proportional to the rate of change of magnetic flux linking the conductor.

Mathematically, Faraday's Law is expressed as:

$$E = -N \frac{d\Phi}{dt}$$

Where: - E is the induced EMF (volts) - N is the number of turns in the coil - dΦ/dt is the rate of change of magnetic flux (webers per second) - The negative sign represents Lenz's Law, indicating that the induced EMF opposes the change causing it

## Mutual Induction

Mutual induction is the phenomenon where a changing current in one coil induces a voltage in another nearby coil. This occurs because the changing current in the first coil creates a changing magnetic field, which then induces a voltage in the second coil according to Faraday's Law.

In a transformer, mutual induction occurs between the primary and secondary windings: 1. When an alternating current flows through the primary winding, it creates a changing magnetic field 2. This changing magnetic field is guided through the transformer's core 3. The changing magnetic field links with the secondary winding 4. According to Faraday's Law, this changing magnetic flux induces a voltage in the secondary winding

The efficiency of this magnetic coupling is maximized by using a core made of ferromagnetic material, which provides a low-reluctance path for the magnetic flux.

## Basic Transformer Operation

The operation of a transformer can be described in the following steps:

1. **AC Input**: An alternating voltage is applied to the primary winding.
2. **Primary Current**: This voltage causes an alternating current to flow in the primary winding.
3. **Magnetic Flux Generation**: The primary current creates an alternating magnetic flux in the core.
4. **Flux Linkage**: This magnetic flux links with both the primary and secondary windings.
5. **Voltage Induction**: The changing flux induces voltages in both windings according to Faraday's Law.
6. **Secondary Current**: If a load is connected to the secondary winding, current flows through it.
7. **Power Transfer**: Electrical energy is transferred from the primary to the secondary circuit.

## Voltage Transformation

The relationship between the primary and secondary voltages in an ideal transformer is determined by the turns ratio:

$$\frac{V_1}{V_2} = \frac{N_1}{N_2}$$

Where: - $V_1$ is the primary voltage - $V_2$ is the secondary voltage - $N_1$ is the number of turns in the primary winding - $N_2$ is the number of turns in the secondary winding

This equation shows that: - If $N_1 > N_2$ (more turns in the primary), then $V_1 > V_2$ (step-down transformer) - If $N_1 < N_2$ (fewer turns in the primary), then $V_1 < V_2$ (step-up transformer) - If $N_1 = N_2$ (equal turns), then $V_1 = V_2$ (isolation transformer)

## Current Transformation

In an ideal transformer, the power input equals the power output:

$$P_1 = P_2$$

$$V_1 I_1 = V_2 I_2$$

Rearranging:

$$\frac{I_1}{I_2} = \frac{V_2}{V_1} = \frac{N_2}{N_1}$$

This inverse relationship between voltage and current transformation is a fundamental characteristic of transformers. When voltage is stepped up, current is proportionally stepped down, and vice versa, maintaining the same power level (assuming 100% efficiency).

### EMF Equation of a Transformer

The EMF induced in a transformer winding can be calculated using the transformer EMF equation:

$$E = 4.44fN\Phi_m$$

Where: - E is the induced EMF (volts) - f is the frequency of the AC supply (Hz) - N is the number of turns in the winding - $\Phi_m$ is the maximum magnetic flux in the core (webers)

This equation is derived from Faraday's Law and applies to both the primary and secondary windings.

### Importance of Alternating Current

Transformers operate only with alternating current (AC) and not with direct current (DC). This limitation stems directly from Faraday's Law, which requires a changing magnetic field to induce voltage.

With DC, after an initial transient period: - The magnetic field becomes constant ($d\Phi/dt = 0$) - No EMF is induced in the secondary winding - The primary winding acts as a short circuit, potentially causing damage

This requirement for AC operation is why transformers are fundamental components of AC power systems and why AC became the dominant form of electrical power transmission and distribution worldwide.

Understanding these basic principles provides the foundation for exploring the more complex aspects of transformer design, construction, and operation in subsequent chapters.# Chapter 2: Fundamental Principles of Transformer Operation

## 2.1 Faraday's Law of Electromagnetic Induction

Faraday's Law of Electromagnetic Induction is the cornerstone principle that governs transformer operation. Discovered by Michael Faraday in 1831, this fundamental law of electromagnetism describes

how a changing magnetic field induces an electromotive force (EMF) in a conductor or circuit.

### 2.1.1 Statement of Faraday’s Law

Faraday’s Law can be expressed in two parts:

**Faraday’s First Law**: An EMF is induced in a conductor or coil whenever there is a change in the magnetic flux linking with it. This change can result from: - Moving a magnet relative to a coil - Moving a coil relative to a magnetic field - Changing the strength of a magnetic field - Changing the area of a circuit within a magnetic field

**Faraday’s Second Law**: The magnitude of the induced EMF is directly proportional to the rate of change of magnetic flux linkage. Mathematically, this is expressed as:

$$E = -N \frac{d\Phi}{dt}$$

Where: - $E$ is the induced EMF (volts) - $N$ is the number of turns in the coil - $\frac{d\Phi}{dt}$ is the rate of change of magnetic flux (webers per second) - The negative sign represents Lenz’s Law (discussed below)

### 2.1.2 Lenz’s Law

The negative sign in Faraday’s Law equation represents Lenz’s Law, which states that the direction of the induced EMF is such that it opposes the change in magnetic flux that produced it. This is a manifestation of the conservation of energy principle. In practical terms, Lenz’s Law explains why:

- A transformer’s secondary winding develops a voltage that opposes the change in magnetic flux
- Energy is not created or destroyed in the induction process
- The induced current creates its own magnetic field that opposes the original change

### 2.1.3 Application to Transformers

In a transformer, Faraday’s Law manifests when:

1. An alternating current in the primary winding creates a continuously changing magnetic flux in the core
2. This changing flux links with both the primary and secondary windings
3. The changing flux induces an EMF in both windings according to Faraday’s Law
4. The magnitude of the induced EMF in each winding is proportional

to its number of turns

This principle explains why transformers require alternating current to function. With direct current, after an initial transient period, the magnetic flux becomes constant ($\frac{d\Phi}{dt} = 0$), resulting in zero induced EMF in the secondary winding.

# 2.2 Mutual Induction

While Faraday's Law explains the fundamental physics behind electromagnetic induction, the specific phenomenon that enables transformer operation is mutual induction—the process by which a changing current in one coil induces a voltage in another nearby coil.

## 2.2.1 Definition and Basic Concept

Mutual induction occurs when two or more coils are positioned such that the magnetic field created by current flowing in one coil links with the other coil(s). When the current in the first coil changes, the resulting change in magnetic flux induces a voltage in the second coil, even though there is no direct electrical connection between them.

The degree of magnetic coupling between the coils is quantified by the mutual inductance ($M$), measured in henries (H). The mutual inductance depends on:

- The number of turns in each coil
- The geometric arrangement of the coils
- The permeability of the core material
- The cross-sectional area of the core

## 2.2.2 Mathematical Expression

The voltage induced in the secondary coil due to mutual induction is given by:

$$V_s = -M \frac{di_p}{dt}$$

Where: - $V_s$ is the induced voltage in the secondary coil - $M$ is the mutual inductance between the coils - $\frac{di_p}{dt}$ is the rate of change of current in the primary coil

Similarly, the voltage induced back in the primary coil due to changes in the secondary current is:

$$V_p = -M \frac{di_s}{dt}$$

## 2.2.3 Coefficient of Coupling

The effectiveness of magnetic coupling between the coils is expressed by the coefficient of coupling ($k$), which ranges from 0 (no coupling) to 1 (perfect coupling):

$$k = \frac{M}{\sqrt{L_p L_s}}$$

Where: - $L_p$ is the self-inductance of the primary coil - $L_s$ is the self-inductance of the secondary coil

In practical transformers, the coefficient of coupling is maximized (typically above 0.95) by: - Using a closed magnetic core with high permeability - Minimizing the distance between windings - Proper arrangement of primary and secondary windings

### 2.2.4 Mutual Induction in Transformer Operation

In a transformer, mutual induction is the mechanism by which energy transfers from the primary to the secondary circuit:

1. When an alternating voltage is applied to the primary winding, it creates an alternating current
2. This current produces a time-varying magnetic flux in the core
3. Through mutual induction, this flux induces a voltage in the secondary winding
4. If a load is connected to the secondary, current flows, completing the energy transfer

The efficiency of this energy transfer depends on maximizing mutual inductance while minimizing losses in the core and windings.

## 2.3 EMF Equation and Turns Ratio

The EMF equation and turns ratio relationship are fundamental to understanding how transformers modify voltage levels between their primary and secondary circuits.

### 2.3.1 Transformer EMF Equation

When an alternating voltage is applied to the primary winding of a transformer, the induced EMF in either winding can be calculated using the transformer EMF equation:

$$E = 4.44 \times f \times \Phi_m \times N$$

Where: - $E$ is the induced EMF (volts) - $f$ is the frequency of the AC supply (Hz) - $\Phi_m$ is the maximum magnetic flux in the core (webers) - $N$ is the number of turns in the winding

The factor 4.44 comes from the mathematical derivation involving the form factor of a sinusoidal waveform ($\frac{E_{rms}}{E_{avg}} = \frac{\pi}{2\sqrt{2}} \approx 1.11$) and the conversion between average and RMS values (4 × 1.11 = 4.44).

For the primary and secondary windings, we can write:

$$E_1 = 4.44 \times f \times \Phi_m \times N_1$$

$$E_2 = 4.44 \times f \times \Phi_m \times N_2$$

### 2.3.2 Turns Ratio and Voltage Ratio

Since the same magnetic flux links both windings in an ideal transformer, we can derive the fundamental transformer relationship by dividing the above equations:

$$\frac{E_1}{E_2} = \frac{N_1}{N_2}$$

This equation shows that the ratio of induced EMFs in the primary and secondary windings equals the ratio of their respective number of turns. This is known as the turns ratio or transformation ratio, often denoted as:

$$a = \frac{N_1}{N_2}$$

In an ideal transformer (with no losses), the induced EMF equals the terminal voltage, so:

$$\frac{V_1}{V_2} = \frac{N_1}{N_2} = a$$

This relationship allows transformers to step voltage up or down by simply changing the turns ratio: - If $N_1 > N_2$ (or $a > 1$): Step-down transformer ($V_1 > V_2$) - If $N_1 < N_2$ (or $a < 1$): Step-up transformer ($V_1 < V_2$) - If $N_1 = N_2$ (or $a = 1$): Isolation transformer ($V_1 = V_2$)

### 2.3.3 Current Ratio

In an ideal transformer, the power input equals the power output:

$$P_1 = P_2$$

$$V_1 I_1 = V_2 I_2$$

Combining this with the voltage ratio equation:

$$\frac{V_1}{V_2} = \frac{N_1}{N_2}$$

We can derive the current ratio:

$$\frac{I_1}{I_2} = \frac{N_2}{N_1} = \frac{1}{a}$$

This inverse relationship between voltage and current ratios demonstrates the fundamental principle of power transformation: as voltage increases, current decreases proportionally, and vice versa, maintaining constant power (neglecting losses).

### 2.3.4 Impedance Transformation

Transformers also transform impedance between primary and secondary circuits according to the square of the turns ratio:

$$\frac{Z_1}{Z_2} = \left(\frac{N_1}{N_2}\right)^2 = a^2$$

Where: - $Z_1$ is the impedance as seen from the primary side - $Z_2$ is the actual impedance connected to the secondary

This impedance transformation property is particularly useful in matching source and load impedances for maximum power transfer in various applications, especially in audio and RF circuits.

## 2.4 Significance of Alternating Current (AC)

Transformers are inherently dependent on alternating current (AC) for their operation, a characteristic that has profoundly shaped the development of modern electrical power systems.

### 2.4.1 Why Transformers Require AC

The necessity for AC in transformer operation stems directly from Faraday's Law of Electromagnetic Induction. For a transformer to function, there must be a continuously changing magnetic flux in the core to induce voltage in the secondary winding. This requires a continuously changing current in the primary winding, which is naturally provided by alternating current.

With direct current (DC), the following limitations arise:

1. **Initial Transient Only**: When a DC voltage is first applied to a transformer primary, there is a brief current surge as the magnetic field establishes itself. During this transient period, there is a changing flux and thus a briefly induced voltage in the secondary. However, once the magnetic field stabilizes, the flux becomes constant.

2. **Zero Induced EMF**: With a constant magnetic flux ($\frac{d\Phi}{dt} = 0$), Faraday's Law indicates that the induced EMF will be zero. Consequently, after the initial transient, no voltage is induced in the secondary winding.

3. **Excessive Primary Current**: In a DC scenario, the primary winding acts essentially as a short circuit limited only by its DC resistance, which is typically very low. This results in an extremely high current that can cause overheating and damage to the winding.

### 2.4.2 AC vs. DC in Transformer Operation

The fundamental differences between AC and DC in transformer operation can be summarized as follows:

| Aspect | With AC Supply | With DC Supply |
|---|---|---|
| Magnetic Flux | Continuously changing | Constant after initial transient |
| Induced Secondary EMF | Continuous, proportional to turns ratio | Zero after initial transient |
| Primary Current | Limited by inductive reactance | Limited only by winding resistance (very high) |
| Energy Transfer | Continuous via electromagnetic induction | None after initial transient |
| Core Saturation | Alternating flux prevents continuous saturation | Core quickly saturates |

### 2.4.3 Historical Impact on Power Systems

The transformer's dependence on AC was a decisive factor in the "War of Currents" in the late 1880s between Thomas Edison's DC system and the AC system promoted by George Westinghouse and Nikola Tesla. The ability of transformers to efficiently step voltage up for long-distance transmission and then down for safe consumer use gave AC a significant advantage that ultimately led to its adoption as the standard for power distribution systems worldwide.

This technical requirement of transformers has shaped the entire architecture of modern power systems, which are predominantly AC-based. In applications where DC is necessary, additional power electronic converters (rectifiers, inverters) must be used in conjunction with transformers.

### 2.4.4 Frequency Considerations

While transformers require AC, the specific frequency affects their performance:

- **Standard Power Frequencies** (50/60 Hz): Most power transformers are designed for these frequencies, with core materials and dimensions optimized accordingly.
- **Higher Frequencies**: As frequency increases, the required core size decreases (for the same power rating), but core losses may increase. High-frequency transformers (kHz to MHz range) use specialized core materials like ferrite to minimize losses.
- **Lower Frequencies**: Lower frequencies require larger cores to avoid saturation, making transformers physically larger and more expensive. This is why some specialized applications like railway power (16.7 Hz in some European countries) require larger transformers than equivalent 50/60 Hz applications.

The transformer's fundamental requirement for AC operation underscores the symbiotic relationship between transformer technology and AC power systems—each enabling and necessitating the other in the development of modern electrical infrastructure.

## 2.5 Ideal Transformer Concept

The ideal transformer is a theoretical model that helps establish the fundamental principles of transformer operation without the complexities introduced by real-world imperfections. While no physical transformer can achieve these ideal characteristics, the model serves as a valuable baseline for understanding transformer behavior and as a starting point for more complex analyses.

### 2.5.1 Characteristics of an Ideal Transformer

An ideal transformer is defined by the following characteristics:

1. **Zero Winding Resistance**: Both primary and secondary windings have zero resistance, eliminating $I^2R$ losses.
2. **Perfect Magnetic Coupling**: All magnetic flux generated by the primary winding links with the secondary winding (coupling coefficient $k = 1$), with no leakage flux.
3. **Infinite Core Permeability**: The core has infinite permeability, providing zero reluctance to magnetic flux and requiring negligible magnetizing current.
4. **No Core Losses**: The core experiences no hysteresis or eddy current losses.
5. **No Capacitive Effects**: There are no capacitive effects between windings or between turns within a winding.

6. **Linear Magnetic Behavior**: The core never saturates, maintaining linear magnetic characteristics regardless of applied voltage or load.

## 2.5.2 Equations Governing Ideal Transformer Operation

The behavior of an ideal transformer is described by several key equations:

**Voltage Ratio:**

$$\frac{V_1}{V_2} = \frac{N_1}{N_2} = a$$

**Current Ratio:**

$$\frac{I_1}{I_2} = \frac{N_2}{N_1} = \frac{1}{a}$$

**Apparent Power Conservation:**

$$S_1 = S_2$$

$$V_1 I_1 = V_2 I_2$$

**Impedance Transformation:**

$$Z_1 = a^2 Z_2$$

Where: - $V_1, V_2$ are the primary and secondary voltages - $I_1, I_2$ are the primary and secondary currents - $N_1, N_2$ are the number of turns in primary and secondary windings - $a$ is the turns ratio - $S_1, S_2$ are the apparent power in primary and secondary - $Z_1, Z_2$ are the impedances as seen from primary and secondary sides

## 2.5.3 Phasor Diagram of an Ideal Transformer

The phasor diagram of an ideal transformer illustrates the relationship between voltages and currents in the primary and secondary circuits. In an ideal transformer:

1. The primary induced EMF ($E_1$) is equal in magnitude and opposite in phase to the applied voltage ($V_1$)
2. The secondary terminal voltage ($V_2$) is equal to the secondary induced EMF ($E_2$)
3. The primary current ($I_1$) is exactly opposite in phase to the secondary current ($I_2$) when referred to the primary side

The phasor diagram helps visualize these relationships and forms the basis for understanding the more complex phasor diagrams of real transformers that include various losses and non-idealities.

### 2.5.4 Limitations of the Ideal Transformer Model

While the ideal transformer concept provides a useful foundation, real transformers deviate from this model in several important ways:

1. **Winding Resistance**: Real windings have resistance, causing voltage drops and power losses.
2. **Leakage Flux**: Some magnetic flux escapes the core and does not link both windings, reducing coupling efficiency.
3. **Finite Core Permeability**: Real core materials have finite permeability, requiring magnetizing current to establish the flux.
4. **Core Losses**: Hysteresis and eddy currents cause power losses in the core.
5. **Capacitive Effects**: Inter-turn and inter-winding capacitances affect high-frequency performance.
6. **Core Saturation**: Real cores saturate at high flux densities, limiting the maximum voltage that can be applied.

These deviations from the ideal model are addressed in practical transformer design and are accounted for in the equivalent circuit models used for detailed transformer analysis.

### 2.5.5 Practical Significance

Despite its limitations, the ideal transformer concept:

- Establishes the fundamental principles of voltage and current transformation
- Provides a baseline for evaluating real transformer performance
- Simplifies initial calculations and design considerations
- Remains reasonably accurate for many practical applications, especially when losses are relatively small compared to the power being transferred

Understanding the ideal transformer model is essential before progressing to the more complex models that account for real-world transformer behavior.# Chapter 3: Transformer Construction and Components

## 3.1 Magnetic Core: Materials and Designs

The magnetic core is often referred to as the “heart” of the transformer, as it provides a low-reluctance path for the magnetic flux, ensuring efficient magnetic coupling between the primary and

secondary windings. The design and material selection of the core significantly impact the transformer's performance, efficiency, and suitability for specific applications.

### 3.1.1 Core Materials

The evolution of transformer core materials represents a continuous effort to improve efficiency by reducing energy losses while balancing factors such as cost, weight, and manufacturability.

#### Silicon Steel (Electrical Steel)

Silicon steel, also known as electrical steel or transformer steel, is the most widely used material for transformer cores, particularly in power and distribution transformers. It typically contains about 3-4.5% silicon alloyed with iron, which:

- Increases electrical resistivity, reducing eddy current losses
- Decreases hysteresis loss by reducing the area of the hysteresis loop
- Improves magnetic permeability

Two main types of silicon steel are used in transformer cores:

1. **Grain-Oriented Silicon Steel (GOSS)**:
    - Manufactured with a controlled rolling and annealing process that aligns the grain structure in the rolling direction
    - Exhibits superior magnetic properties (higher permeability, lower losses) in the rolling direction
    - Typically used in larger power and distribution transformers where efficiency is paramount
    - Contains about 3% silicon and has a typical thickness of 0.23-0.35 mm
2. **Non-Oriented Silicon Steel (NGOSS)**:
    - Has randomly oriented grains with similar magnetic properties in all directions
    - Less expensive than grain-oriented steel
    - Used in smaller transformers and rotating machines
    - Contains about 2-3.5% silicon and has a typical thickness of 0.35-0.65 mm

#### Amorphous Metals (Metallic Glass)

Amorphous metal cores represent a significant advancement in transformer core technology, offering substantially lower core losses compared to conventional silicon steel:

- Formed by rapid solidification of molten metal alloys, creating a non-crystalline (random atomic) structure

- Typically composed of iron alloyed with boron, silicon, and other elements
- Offers 70-80% lower core losses than conventional silicon steel
- Particularly effective at reducing no-load losses
- Higher initial cost but can be economical over the transformer's lifetime due to energy savings
- Increasingly used in distribution transformers, especially in regions with high electricity costs or strict efficiency regulations

**Ferrite**

Ferrite cores are ceramic compounds of iron oxide combined with other metallic elements such as manganese, zinc, or nickel:

- Exhibit high electrical resistivity, virtually eliminating eddy current losses
- Operate efficiently at high frequencies (kHz to MHz range)
- Lower saturation flux density compared to silicon steel (typically 0.3-0.5 T vs. 1.7-2.0 T)
- Used primarily in high-frequency transformers for switch-mode power supplies, RF applications, and electronic devices
- Available in various shapes including toroids, E-cores, and pot cores

**Powdered Iron**

Powdered iron cores consist of tiny iron particles that are insulated from each other and pressed together with a binding agent:

- The insulation between particles reduces eddy current losses
- Provides distributed air gaps, allowing higher DC current without saturation
- Offers good thermal stability and mechanical strength
- Used in inductors, chokes, and transformers for power supplies and RF applications
- Available in various formulations with different permeability values for specific applications

**Nanocrystalline Alloys**

Nanocrystalline cores represent the cutting edge of magnetic core materials:

- Composed of iron-based alloys with extremely fine grain structure (10-30 nanometers)
- Manufactured through controlled crystallization of amorphous precursors
- Combines the high saturation flux density of silicon steel with the low core losses of amorphous metals

- Offers exceptional performance across a wide frequency range
- Used in high-efficiency distribution transformers, current transformers, and high-frequency applications
- Higher cost currently limits widespread adoption

### 3.1.2 Core Designs

The geometric arrangement of the magnetic core significantly affects the transformer's performance, manufacturing process, and suitability for specific applications.

#### Core Type

In the core type design:

- The windings surround the limbs (vertical sections) of a rectangular magnetic circuit
- Typically has two limbs connected by top and bottom yokes
- Primary and secondary windings are placed on the same limb, either concentrically or in sections
- Provides good magnetic coupling between windings
- Offers easier insulation between high and low voltage windings
- Commonly used in distribution transformers and medium-sized power transformers

#### Shell Type

In the shell type design:

- The magnetic core surrounds a significant portion of the windings
- Typically has three limbs, with windings placed on the center limb
- The magnetic flux splits between the outer limbs
- Provides better mechanical support for windings
- Offers better containment of magnetic flux
- Commonly used in large power transformers and special applications requiring high mechanical strength

#### Toroidal Core

Toroidal cores have a donut or ring shape:

- Windings are wound around the entire circumference of the ring
- Provides a continuous magnetic path with no air gaps
- Offers very high efficiency with minimal flux leakage
- Results in smaller size for the same power rating
- Requires specialized winding equipment
- Commonly used in small to medium-sized distribution transformers, audio transformers, and high-efficiency applications

**Berry Type (Cruciform Core)**

The Berry type design features a cruciform cross-section:

- Uses a circular or wheel-like arrangement of laminations
- Provides a more uniform distribution of magnetic flux
- Reduces noise and vibration
- Used in specialized applications where these characteristics are important

**Five-Limb Core**

The five-limb core design:

- Features three main limbs for the phases and two outer return limbs
- Provides better magnetic balance in three-phase transformers
- Reduces zero-sequence flux in the yokes
- Used in large three-phase power transformers, particularly where zero-sequence impedance control is important

### 3.1.3 Lamination Techniques

Regardless of the core material or design, transformer cores are typically constructed from thin laminations to reduce eddy current losses:

- Laminations are thin sheets of magnetic material, typically 0.23-0.35 mm thick for power frequency applications
- Each lamination is coated with an insulating layer (varnish, oxide coating, or phosphate coating)
- Laminations are stacked together to form the core
- The insulation between laminations restricts eddy currents to individual sheets, significantly reducing overall eddy current losses
- Laminations are typically arranged in overlapping patterns at corners (mitred joints) to minimize air gaps in the magnetic circuit

The thickness of laminations is inversely related to the operating frequency: - Thicker laminations (0.35-0.65 mm) for low-frequency applications (50/60 Hz) - Thinner laminations (0.1-0.3 mm) for medium-frequency applications (400-1000 Hz) - Very thin laminations or alternative materials like ferrite for high-frequency applications

### 3.1.4 Core Assembly Methods

Several methods are used to assemble transformer cores, each with specific advantages:

**Stacked Core**

- Individual laminations are cut to shape and stacked together
- Simple manufacturing process but may have higher losses at joints
- Commonly used in smaller transformers

**Wound Core**

- Continuous strip of core material is wound like a spiral
- Reduces joints in the magnetic circuit, lowering losses
- Commonly used in distribution transformers
- Particularly suitable for amorphous metal cores

**Step-Lap Joint**

- Laminations are cut and assembled with overlapping joints in a staggered pattern
- Minimizes air gaps and reduces losses at corners
- Used in high-efficiency transformers

**Mitred Corner Joint**

- Laminations are cut at 45° angles at corners for better magnetic flux transfer
- Reduces losses compared to simple butt joints
- Common in medium to large power transformers

The choice of core material, design, and assembly method depends on factors including the transformer's application, required efficiency, operating frequency, size constraints, and cost considerations. Modern transformer design often involves sophisticated computer modeling to optimize these parameters for specific performance requirements.

# 3.2 Windings: Types and Arrangements

Transformer windings are the conductive paths that carry the electric currents and create or respond to the magnetic flux in the core. The design and arrangement of these windings significantly impact the transformer's electrical performance, thermal characteristics, and ability to withstand mechanical and electrical stresses.

## 3.2.1 Winding Materials

**Copper**

Copper is the most commonly used material for transformer windings, particularly in medium to large power transformers:

- Excellent electrical conductivity (approximately 97% that of pure

silver)
- Good thermal conductivity, facilitating heat dissipation
- Superior mechanical strength compared to aluminum
- Better resistance to creep (gradual deformation under stress)
- Higher cost compared to aluminum
- Available in various forms: round wire, rectangular wire, foil, and CTC (continuously transposed conductor)

**Aluminum**

Aluminum is an alternative winding material, particularly common in distribution transformers and where weight or cost is a primary concern:

- Approximately 61% the conductivity of copper, requiring larger cross-sectional area for the same current
- Lighter weight (approximately 30% the density of copper)
- Lower cost per unit volume compared to copper
- More susceptible to creep under pressure and thermal cycling
- Forms a resistive oxide layer that can cause connection problems if not properly handled
- Often used in foil windings for low-voltage applications

## 3.2.2 Winding Types

**Cylindrical (Layer) Windings**

In cylindrical windings, conductors are arranged in concentric layers:

- Each layer consists of turns wound side by side
- Insulating material separates adjacent layers
- Provides good mechanical strength and cooling
- Suitable for high-voltage applications
- Allows for precise control of turn-to-turn voltage
- Common in power transformers, especially for higher voltage windings

**Disc Windings**

Disc windings consist of a series of flat coils (discs) stacked vertically:

- Each disc contains multiple turns wound radially inward or outward
- Adjacent discs are connected to form a continuous winding
- Provides excellent impulse voltage distribution
- Allows for transposition to reduce eddy current losses
- Commonly used for high-voltage windings in power transformers
- Good cooling characteristics due to the presence of cooling ducts between discs

#### Helical (Spiral) Windings

Helical windings are formed by winding conductors in a helical pattern:

- Typically uses rectangular conductors wound on edge
- Provides good mechanical strength against radial forces
- Efficient use of winding space
- Commonly used for low-voltage, high-current applications
- Often employed in the low-voltage windings of power transformers

#### Foil Windings

Foil windings use continuous sheets of conductor material:

- The entire width of the winding consists of a single turn
- Provides excellent current distribution
- Minimizes circulating currents and eddy current losses
- Strong against radial forces but vulnerable to axial forces
- Commonly used in low-voltage, high-current applications
- Often employed in distribution transformers and dry-type transformers

#### Continuously Transposed Conductor (CTC) Windings

CTC windings use specially manufactured conductors consisting of multiple individually insulated strands that are continuously transposed:

- Reduces eddy current losses and circulating currents
- Improves current distribution within the conductor
- Used in high-current applications where AC losses are significant
- Common in large power transformers

### 3.2.3 Winding Arrangements

#### Concentric Arrangement

In the concentric arrangement:

- Windings are arranged as concentric cylinders
- Typically, the low-voltage winding is placed closest to the core
- The high-voltage winding surrounds the low-voltage winding
- An insulating barrier separates the windings
- Provides good electrical isolation between windings
- Commonly used in core-type transformers

#### Sandwich Arrangement

In the sandwich arrangement:

- Windings are divided into sections
- Low-voltage and high-voltage sections alternate in a sandwich pattern
- Reduces leakage reactance
- Improves voltage regulation
- Often used in shell-type transformers

**Split Windings**

Split windings divide a winding into two or more sections:

- Sections may be connected in series or parallel
- Provides flexibility in voltage and current ratings
- Helps balance electromagnetic forces
- Used in tap-changing transformers and special applications

## 3.2.4 Winding Insulation

Proper insulation is critical for transformer reliability and safety:

**Turn-to-Turn Insulation**

- Prevents short circuits between adjacent turns
- Typically consists of enamel coating on the conductor or paper wrapping
- Must withstand normal operating voltage plus transient surges
- Thickness depends on the voltage gradient between turns

**Layer-to-Layer Insulation**

- Separates adjacent layers in cylindrical windings
- Usually consists of paper, pressboard, or other insulating materials
- Must withstand the cumulative voltage difference between layers

**Winding-to-Winding Insulation**

- Provides isolation between primary and secondary windings
- Typically consists of pressboard barriers, oil ducts, or solid insulation
- Must withstand the full voltage difference between windings plus safety margin

**Winding-to-Core Insulation**

- Isolates windings from the grounded core
- Prevents ground faults
- Usually consists of pressboard barriers or molded insulation

**End Insulation**

- Reinforces insulation at the ends of windings where electric field concentration occurs
- Often uses additional layers of pressboard or special stress-grading materials
- Critical for withstanding impulse voltages

### 3.2.5 Taps and Tap Changers

Many transformers include taps in their windings to adjust the turns ratio:

#### Fixed Taps

- Multiple connection points along a winding
- Allow for manual adjustment of the turns ratio when the transformer is de-energized
- Typically provide ±2.5% or ±5% voltage adjustment in steps

#### On-Load Tap Changers (OLTC)

- Allow for changing taps while the transformer remains energized
- Include special switching mechanisms to maintain circuit continuity during tap changes
- Often located on the high-voltage winding where current is lower
- Used for voltage regulation in response to load changes
- Typically provide ±10% to ±20% voltage adjustment in 16-32 steps

The design of transformer windings involves careful consideration of electrical, thermal, and mechanical factors. Modern transformer design uses sophisticated computer modeling to optimize winding configurations for specific performance requirements, balancing factors such as efficiency, short-circuit strength, impulse voltage withstand, and manufacturing cost.

## 3.3 Insulation Systems

The insulation system is a critical component of transformer design, directly affecting reliability, lifespan, and safety. It must withstand electrical stresses, thermal aging, mechanical forces, and environmental factors throughout the transformer’s operational life.

### 3.3.1 Insulation Materials

#### Liquid Insulation

**Mineral Oil** - Most commonly used insulating liquid in transformers - Excellent dielectric properties (breakdown strength typically 40-60 kV/cm) - Good thermal conductivity for heat dissipation - Self-healing after minor electrical breakdowns - Relatively low cost and widely available - Drawbacks include flammability and environmental concerns if spilled

**Silicone Oil** - Higher fire point (>300°C) compared to mineral oil (~170°C) - Excellent thermal stability and aging characteristics - Higher cost than mineral oil - Used in applications where fire safety is critical - Better environmental profile than mineral oil

**Natural Esters (Vegetable Oils)** - Derived from renewable sources such as soybean, sunflower, or rapeseed oil - Biodegradable and environmentally friendly - High fire point (>300°C) for enhanced safety - Good dielectric properties - Higher viscosity than mineral oil, affecting cooling efficiency - Increasingly used in distribution transformers, especially in environmentally sensitive locations

**Synthetic Esters** - Engineered fluids with controlled properties - Biodegradable with high fire point (>300°C) - Excellent dielectric and thermal properties - Higher cost than mineral oil or natural esters - Used in applications requiring both fire safety and good performance

**Solid Insulation**

**Cellulose-Based Materials** - Kraft paper: Wrapped around conductors for turn-to-turn insulation - Pressboard: Used for barriers, spacers, and structural components - Excellent dielectric properties when properly dried and impregnated - Mechanical strength degrades with thermal aging - Moisture absorption is a concern - Most common solid insulation in oil-filled transformers

**Aramid Paper (Nomex)** - Synthetic high-temperature insulation - Thermal class 220°C (compared to 105°C for cellulose) - Higher cost than cellulose materials - Used in high-temperature applications and dry-type transformers - Better resistance to thermal degradation

**Epoxy Resin** - Used in cast-resin dry-type transformers - Provides both insulation and structural support - Good thermal conductivity with appropriate fillers - Excellent moisture resistance - Higher cost than conventional insulation systems

**Mica** - Excellent dielectric properties and heat resistance - Used in high-temperature applications - Often combined with other materials in composite insulation systems

**Gas Insulation**

**SF6 (Sulfur Hexafluoride)** - Excellent dielectric strength (2-3 times that of air) - Good arc-quenching properties - Used in specialized gas-insulated transformers - Environmental concerns due to high global warming potential - Primarily used in special applications where oil cannot be used

**Nitrogen** - Lower dielectric strength than SF6 but environmentally benign - Used in some dry-type and special application transformers - Often used at slight positive pressure to prevent moisture ingress

## 3.3.2 Insulation Structures

### Oil-Immersed Transformers

In oil-immersed transformers, the insulation system consists of:

**Oil Ducts** - Channels between winding sections filled with oil - Provide both insulation and cooling - Width determined by voltage requirements and cooling needs

**Barriers and Cylinders** - Made from pressboard or similar materials - Direct oil flow for cooling - Provide additional insulation between windings - Support windings mechanically

**Angle Rings and Collars** - Reinforce insulation at high-stress points - Prevent partial discharges at edges and corners - Control electric field distribution

**End Insulation** - Additional insulation at winding ends where electric field concentration occurs - Often includes special stress-grading designs

### Dry-Type Transformers

Dry-type transformers use various insulation structures:

**Open Wound** - Individual conductors insulated with high-temperature materials - Air spaces between windings for cooling and insulation - Additional solid insulation barriers between windings

**Vacuum Pressure Impregnated (VPI)** - Windings impregnated with varnish or resin under vacuum - Fills voids to improve thermal conductivity and dielectric strength - Provides environmental protection

**Cast Resin** - Windings completely encapsulated in epoxy resin - Excellent moisture and pollution resistance - Good thermal conductivity with appropriate fillers - Used in environments with high humidity or contamination

### 3.3.3 Insulation Coordination

Insulation coordination is the process of designing the insulation system to withstand various voltage stresses:

**Basic Insulation Level (BIL)** - Standardized impulse withstand voltage level - Defines the transformer's ability to withstand lightning and switching surges - Coordinated with surge arresters and other protective equipment

**Power Frequency Withstand** - Ability to withstand continuous operating voltage plus temporary overvoltages - Typically tested at 2-4 times rated voltage for a specified duration

**Partial Discharge Control** - Design to minimize or eliminate partial discharges within the insulation - Critical for long-term reliability - Verified through sensitive partial discharge testing

### 3.3.4 Aging and Lifetime

Insulation aging is often the limiting factor in transformer life:

**Thermal Aging** - Follows the Arrhenius relationship: insulation life approximately halves for every 6-10°C increase above rated temperature - Cellulose degradation produces furans, CO, CO2, and water - Monitored through dissolved gas analysis and furan testing

**Moisture Effects** - Significantly reduces dielectric strength - Accelerates thermal degradation of cellulose - Controlled through proper drying during manufacturing and sealing systems during operation

**Oxygen Effects** - Accelerates oil and paper degradation - Controlled through sealed tank designs or nitrogen blankets

**Acidity** - Degrades cellulose and can be corrosive to metals - Monitored through oil quality tests - Controlled through oil treatment or replacement

The insulation system must be designed as an integrated whole, considering electrical, thermal, and mechanical stresses throughout the transformer's expected lifetime. Modern design approaches include sophisticated computer modeling of electric fields and thermal gradients to optimize insulation structures and materials.

## 3.4 Cooling Systems

Efficient cooling is essential for transformer operation, as it directly affects capacity, efficiency, and lifespan. The heat generated by losses in the windings and core must be effectively transferred to the surrounding environment to maintain acceptable operating temperatures.

## 3.4.1 Cooling Methods Classification

Transformer cooling methods are classified using a standardized letter code system:

**First Letter - Internal Cooling Medium:** - O: Mineral oil or synthetic insulating liquid with fire point ≤ 300°C - K: Insulating liquid with fire point > 300°C (e.g., silicone, natural esters) - L: Insulating liquid with no measurable fire point - G: Gas - A: Air

**Second Letter - Circulation Mechanism for Internal Cooling Medium:** - N: Natural convection through cooling equipment and windings - F: Forced circulation through cooling equipment, natural convection in windings - D: Forced circulation through cooling equipment, directed flow through windings

**Third Letter - External Cooling Medium:** - A: Air - W: Water

**Fourth Letter - Circulation Mechanism for External Cooling Medium:** - N: Natural convection - F: Forced circulation (fans, pumps)

## 3.4.2 Common Cooling Methods for Oil-Immersed Transformers

### ONAN (Oil Natural, Air Natural)

Also known as self-cooled: - Oil circulates by natural convection within the tank - External cooling occurs by natural air flow over the tank surface and radiators - Simplest and most reliable cooling method - Limited cooling capacity - Typically used in smaller distribution transformers - No external power required for cooling

### ONAF (Oil Natural, Air Forced)

Also known as forced-air cooled: - Oil circulates by natural convection - Fans blow air across radiators to enhance heat transfer - Provides 25-30% increased capacity over ONAN - Fans can be thermostatically controlled to operate only when needed - Commonly used in medium-sized transformers - Relatively simple and reliable

### OFAF (Oil Forced, Air Forced)

Also known as forced-oil, forced-air cooled: - Oil is circulated by pumps through the windings and radiators - Fans blow air across radiators - Provides more efficient cooling than ONAF - Allows for 50-60% increased capacity over ONAN - Used in larger power transformers - Requires reliable power supply for pumps and fans

**ODAF (Oil Directed, Air Forced)**

Also known as directed-flow, forced-air cooled: - Pumps circulate oil in a directed path through the windings - Oil flow is directed through specific channels in the windings - Fans blow air across radiators - Provides very efficient cooling, especially for winding hotspots - Allows for up to 100% increased capacity over ONAN - Used in large power transformers with high load factors

**OFWF (Oil Forced, Water Forced)**

Also known as water-cooled: - Oil is circulated by pumps through the windings - Heat is transferred from oil to water via oil-to-water heat exchangers - Provides very efficient cooling - Requires reliable water supply and consideration of water quality - Used where air cooling is insufficient or impractical - Common in indoor installations with limited space

**ODWF (Oil Directed, Water Forced)**

- Combines directed oil flow through windings with water-cooled heat exchangers
- Provides maximum cooling efficiency
- Used in very large power transformers or special applications
- Requires sophisticated control systems for oil and water flow

## 3.4.3 Cooling Systems for Dry-Type Transformers

**AN (Air Natural)**

- Cooling by natural convection of air through and around the windings
- Simplest cooling method for dry-type transformers
- Limited cooling capacity
- Used in smaller indoor installations

**AF (Air Forced)**

- Fans direct air through cooling ducts in the windings
- Provides increased capacity over AN cooling
- Used in medium to large dry-type transformers
- May include filters to prevent dust accumulation

**ANAF (Air Natural, Air Forced)**

- Designed to operate in AN mode under normal conditions
- Switches to AF mode (fans on) when temperature rises above set points
- Provides operational flexibility and energy savings

**Water-Cooled Dry-Type**

- Heat pipes or cooling channels embedded in resin
- Used in special applications where air cooling is insufficient
- Provides high cooling efficiency in compact designs

## 3.4.4 Cooling System Components

**Radiators**

- Increase the surface area for heat dissipation
- Typically consist of multiple parallel elements
- May be detachable for shipping or maintenance
- Often equipped with isolation valves to allow removal without draining the transformer

**Fans**

- Increase air flow across cooling surfaces
- Typically thermostatically controlled
- May be arranged in multiple groups that activate sequentially
- Modern designs often use variable speed control for efficiency

**Oil Pumps**

- Circulate oil through the cooling system
- Typically centrifugal type for reliability
- Often installed with redundancy (multiple pumps)
- May include flow indicators and alarms

**Oil-to-Water Heat Exchangers**

- Transfer heat from oil to water circuit
- May be plate-type or tube-type design
- Include safety features to prevent water contamination of oil
- Often equipped with temperature and flow monitoring

**Cooling Controls**

- Monitor temperatures at various points
- Control operation of fans, pumps, and other cooling equipment
- Provide alarms for abnormal conditions

- May include automatic load reduction features for cooling system failures

### 3.4.5 Temperature Monitoring

#### Winding Temperature Indicators

- Simulate the temperature of the windings
- Typically use a current transformer to provide load-proportional heating
- Include temperature gauge with alarm and trip contacts
- Modern designs often include electronic sensors with data logging

#### Oil Temperature Indicators

- Directly measure top oil temperature
- Provide visual indication and alarm/trip contacts
- Used as input for cooling control systems

#### Fiber Optic Temperature Sensors

- Directly measure winding temperatures at multiple points
- Provide accurate hotspot temperature measurement
- Immune to electromagnetic interference
- Used in critical applications and large transformers

The cooling system design must consider the transformer's load profile, ambient conditions, and installation environment. Modern transformer designs often include sophisticated thermal modeling to optimize cooling system performance and ensure that temperature limits are not exceeded under any operating condition.

## 3.5 Bushings and Terminals

Bushings are critical components that allow electrical connections to pass through the transformer tank while maintaining insulation integrity. They must withstand electrical stress, environmental conditions, and mechanical forces while providing reliable connections to external circuits.

### 3.5.1 Bushing Types

#### Solid Porcelain Bushings

- Constructed from glazed porcelain with a central conductor
- Simple and reliable design
- Limited to lower voltage applications (typically below 36 kV)

- Good pollution resistance due to glazed surface
- Used in distribution transformers and some medium-voltage applications

**Oil-Impregnated Paper (OIP) Bushings**

- Consist of paper layers wound around a central conductor and impregnated with oil
- Capacitance grading layers control electric field distribution
- Housed in porcelain or composite insulators
- Used for medium to high voltage applications (up to 765 kV)
- Traditional design with long service history
- Require careful handling to prevent oil leaks

**Resin-Bonded Paper (RBP) Bushings**

- Similar to OIP but use resin instead of oil for impregnation
- Less susceptible to leaks compared to OIP
- Limited to medium voltage applications
- Good mechanical strength
- Used in both indoor and outdoor applications

**Resin-Impregnated Paper (RIP) Bushings**

- Paper layers impregnated with epoxy resin under vacuum
- No liquid insulation, eliminating risk of leaks
- Excellent mechanical strength
- Good thermal performance
- Used in medium to high voltage applications
- Increasingly popular as a replacement for OIP bushings

**Composite Bushings**

- Use silicone rubber or other polymer housing instead of porcelain
- Lighter weight than porcelain equivalents
- Better performance in seismic conditions
- Excellent pollution performance
- Safer failure mode (no shattering)
- Available with various internal insulation systems (OIP, RIP, etc.)

**SF6 Gas Bushings**

- Use SF6 gas as the primary insulation medium
- Excellent dielectric properties
- Used in gas-insulated substations and special applications
- Environmental concerns due to SF6’s high global warming potential

**Condenser Bushings**

- Incorporate capacitive grading to control electric field distribution
- Multiple concentric conductive layers separated by insulation
- Each layer is maintained at a specific potential
- Used in high voltage applications
- May include a test tap for power factor testing

### 3.5.2 Bushing Components

#### Conductor

- Carries the current through the bushing
- Typically made of copper or aluminum
- Sized according to current rating
- May include special designs for high-current applications

#### Insulation System

- Provides electrical isolation between the conductor and ground
- Design depends on bushing type (solid, OIP, RIP, etc.)
- Must withstand normal operating voltage plus transient overvoltages

#### Head (Terminal End)

- Provides connection to external conductors
- Includes weather protection for outdoor applications
- May incorporate corona shields for high voltage
- Typically includes standardized connection hardware

#### Flange

- Secures the bushing to the transformer tank
- Provides oil-tight seal
- Includes mounting hardware
- May incorporate cooling fins in high-current applications

#### Oil End (Tank End)

- Extends into the transformer oil
- Designed to control electric field at the oil-end
- May include stress shields or grading electrodes

#### Test Tap

- Connection point for diagnostic testing
- Typically connected to a specific capacitive layer
- Used for power factor and capacitance measurements
- May be used for partial discharge monitoring

**Oil Level Indicator (for OIP bushings)**

- Visual indication of oil level
- May include alarm contacts for low oil level
- Critical for maintaining insulation integrity

## 3.5.3 Bushing Selection Criteria

**Voltage Rating**

- Basic Insulation Level (BIL) must coordinate with transformer insulation
- Must withstand lightning impulse, switching impulse, and power frequency test voltages
- Includes safety margin above normal operating voltage

**Current Rating**

- Determined by maximum load current plus margin
- Considers temperature rise limitations
- May need to withstand short-circuit currents

**Creepage Distance**

- Length of the insulator surface from conductor to ground
- Determined by pollution severity at installation location
- Typically specified in mm/kV of system voltage
- Higher values required for heavily polluted environments

**Mechanical Strength**

- Must withstand conductor forces during normal operation and faults
- Seismic considerations for earthquake-prone areas
- Wind loading for tall bushings
- Connection forces from bus work or cables

**Environmental Factors**

- Indoor vs. outdoor installation
- Ambient temperature range
- Altitude (affects dielectric strength of air)
- Pollution level (coastal, industrial, desert, etc.)
- UV radiation exposure

## 3.5.4 Terminal Connections

**Spade Terminals**

- Flat connection surface with bolt holes
- Used for medium current applications
- Simple and reliable connection method
- Common in distribution transformers

**Palm Terminals**

- Extended flat connection with multiple bolt holes
- Used for high current applications
- Provides larger contact area
- Common in power transformers

**Draw-Lead Terminals**

- Flexible conductor connection
- Allows for thermal expansion
- Reduces mechanical stress on bushings
- Used in some high-current applications

**Plug-In Terminals**

- Quick-disconnect design
- Used in padmount and underground applications
- Standardized interfaces for interchangeability
- Incorporates insulating covers for safety

**Cable Boxes**

- Enclosed termination for cable connections
- Provides weather protection and safety
- May include stress control components
- Common in indoor installations and underground distribution

## 3.5.5 Bushing Maintenance and Monitoring

**Visual Inspection**

- Check for cracks, chips, or damage to insulator
- Inspect for oil leaks in OIP bushings
- Examine for discoloration indicating overheating
- Check for contamination or pollution buildup

**Electrical Testing**

- Power factor/dissipation factor testing
- Capacitance measurement
- Partial discharge testing
- Insulation resistance measurement

**Online Monitoring**

- Bushing monitoring systems measure changes in capacitance and power factor
- Detect developing issues before failure
- Particularly valuable for critical high-voltage bushings
- May be integrated with transformer monitoring systems

**Oil Sampling (for OIP bushings)**

- Dissolved gas analysis to detect internal problems
- Oil quality tests (moisture, acidity, etc.)
- Particularly important for aging bushings

Bushings are critical components that often represent a significant portion of transformer failures. Modern transformer designs increasingly incorporate advanced bushing technologies and monitoring systems to improve reliability and detect potential issues before catastrophic failure occurs.

# 3.6 Auxiliary Components

Transformer auxiliary components enhance functionality, protection, and monitoring capabilities. While not directly involved in the core electromagnetic function, these components are essential for safe, reliable operation and maintenance.

## 3.6.1 Conservator Tank

The conservator tank accommodates oil volume changes due to temperature variations:

- Located above the main tank and connected by a pipe
- Typically half-filled with oil, with air or gas in the upper portion
- Allows oil to expand and contract with temperature changes
- Prevents exposure of main tank oil to atmosphere
- Often equipped with an oil level indicator
- May include compartments to separate tap changer oil from main tank oil

**Air Cell (Rubber Bag) Systems**

- Flexible rubber bag inside the conservator
- Oil outside the bag, air/gas inside
- Prevents direct contact between oil and air
- Reduces oil oxidation and moisture absorption
- Extends oil and insulation life

### 3.6.2 Breather

The breather prevents moisture from entering the transformer as it "breathes" during temperature cycles:

- Connected to the conservator air space
- Contains desiccant (typically silica gel)
- Absorbs moisture from incoming air during cooling cycles
- Often includes color-indicating silica gel (blue when dry, pink when saturated)
- Modern designs may include oil seals to prevent continuous air exchange

#### Dehydrating Breathers

- Advanced breathers with enhanced moisture removal
- May include heating elements to regenerate desiccant
- Some designs use refrigeration principles to condense moisture
- Used in critical applications or humid environments

### 3.6.3 Buchholz Relay

The Buchholz relay is a gas-actuated protective device installed in the pipe between the main tank and conservator:

- Detects gas evolution from oil decomposition due to internal faults
- Two-stage operation:
  - Minor faults: Small gas accumulation triggers an alarm
  - Major faults: Rapid oil flow triggers a trip signal
- Considered one of the most reliable protective devices for transformers
- Typically used in transformers 500 kVA and larger
- Includes a viewing window to observe collected gas
- Provides facilities for gas sampling and analysis

### 3.6.4 Pressure Relief Devices

Pressure relief devices protect the tank from excessive internal pressure:

- Spring-loaded valve that opens at predetermined pressure
- Releases pressure to prevent tank rupture
- Typically includes visual indication of operation
- May include alarm contacts
- Self-resealing after pressure reduction
- Located on the tank cover or upper tank wall

### 3.6.5 Sudden Pressure Relay

The sudden pressure relay responds to rapid pressure increases:

- Detects pressure waves from internal arcing
- More sensitive than pressure relief devices
- Operates on rate-of-rise rather than absolute pressure
- Typically includes alarm and trip contacts
- Immune to normal pressure changes from loading

### 3.6.6 Oil Level Indicators

Oil level indicators monitor the oil level in various compartments:

- Magnetic float-type indicators for main tank and conservator
- Visual indication with optional alarm contacts
- May include temperature compensation
- Critical for monitoring oil leaks or consumption
- Separate indicators for main tank and tap changer compartments

### 3.6.7 Temperature Indicators

Temperature monitoring devices track critical temperatures:

- Top oil temperature indicators
- Winding temperature indicators (thermal models or direct measurement)
- Include visual indication with alarm and trip contacts
- Often provide analog or digital output for remote monitoring
- May control cooling equipment operation
- Critical for preventing thermal damage to insulation

### 3.6.8 Cooling Controls

Cooling control systems manage the operation of cooling equipment:

- Temperature sensors and controllers
- Control logic for fans, pumps, and other cooling equipment
- Staged operation based on temperature thresholds
- Monitoring of cooling system operation
- Alarm functions for cooling system failures
- May include automatic load reduction features

### 3.6.9 De-energized Tap Changers (DETC)

DETCs allow adjustment of the turns ratio when the transformer is de-energized:

- Manual operation via external handle
- Typically provide ±2.5% or ±5% adjustment in 2-5 steps
- Padlocking provisions for security

- Position indicator
- Used for infrequent voltage adjustments
- Simpler and less expensive than on-load tap changers

### 3.6.10 On-Load Tap Changers (OLTC)

OLTCs allow adjustment of the turns ratio while the transformer remains energized:

- Motor-driven mechanism with complex switching sequence
- Prevents circuit interruption during tap changes
- Typically provides ±10% to ±20% adjustment in 16-32 steps
- Local and remote control capabilities
- Position indication locally and remotely
- Separate oil compartment from main tank
- Requires periodic maintenance due to contact wear
- Critical for voltage regulation in response to load changes

### 3.6.11 Bushing Current Transformers

Bushing CTs provide current measurement for metering and protection:

- Toroidal transformers installed around or within bushings
- Multiple cores with different accuracy classes for different functions
- Protection cores for relay operation
- Metering cores for accurate measurement
- May include multiple ratios via taps
- Terminal boxes for secondary connections

### 3.6.12 Oil Sampling Valves

Oil sampling valves allow for oil testing without disrupting operation:

- Located at different heights for representative sampling
- Designed to prevent contamination during sampling
- May include specific valves for dissolved gas analysis
- Critical for condition monitoring and diagnostics

### 3.6.13 Radiator Isolation Valves

Radiator valves allow for maintenance without draining the main tank:

- Butterfly or gate valves at radiator connections
- Allow isolation of individual cooling elements
- Enable maintenance or replacement without complete outage
- May include provisions for vacuum filling

### 3.6.14 Ground Connections

Grounding systems ensure safety and proper operation:

- Core grounding to prevent electrostatic buildup
- Tank grounding for safety
- Shield grounding in special designs
- Removable links for testing
- Corrosion-resistant connections

### 3.6.15 Nitrogen Injection Fire Protection System

Advanced fire protection systems for critical installations:

- Detects fire conditions via sensors
- Injects nitrogen to displace oxygen and extinguish fire
- Simultaneously drains oil to a safe containment area
- Provides rapid response to prevent catastrophic fires
- Used in high-risk installations or densely populated areas

### 3.6.16 Online Monitoring Systems

Modern transformers increasingly incorporate comprehensive monitoring:

- Dissolved gas analyzers for early fault detection
- Moisture monitors for insulation condition assessment
- Partial discharge monitors for insulation defect detection
- Load and temperature monitors for thermal modeling
- Bushing monitors for early failure detection
- Cooling system performance monitors
- Integration with SCADA or asset management systems
- May include advanced analytics and predictive diagnostics

These auxiliary components work together to enhance transformer reliability, safety, and operational flexibility. While they add cost to the transformer, they provide significant value through improved operation, reduced maintenance costs, and prevention of catastrophic failures. The specific components selected depend on the transformer's size, application, criticality, and operating environment.# Chapter 4: Types of Transformers

## 4.1 Based on Voltage Level

Transformers are commonly classified based on their voltage transformation characteristics, which directly relate to their role in electrical power systems. This classification includes step-up, step-

down, and isolation transformers, each serving distinct purposes in the electrical network.

### 4.1.1 Step-Up Transformers

Step-up transformers increase voltage from the primary to the secondary winding. They are characterized by having more turns in the secondary winding than in the primary winding ($N_2 > N_1$).

#### Characteristics

- **Turns Ratio**: $N_2/N_1 > 1$
- **Voltage Transformation**: $V_2 > V_1$
- **Current Transformation**: $I_2 < I_1$
- **Winding Configuration**: Typically, the low-voltage winding has fewer turns of thicker conductor to handle higher current, while the high-voltage winding has more turns of thinner conductor.

#### Applications

1. **Power Generation**: Step-up transformers are installed at power plants to increase generator output voltage (typically 11-25 kV) to transmission levels (110-765 kV). This voltage increase is essential for efficient long-distance power transmission.
2. **Renewable Energy Integration**: Solar farms and wind turbines typically generate at relatively low voltages (400V-690V) and require step-up transformers to connect to the grid.
3. **Industrial Applications**: Some industrial processes require higher voltages than the available supply, necessitating step-up transformation.
4. **High Voltage Testing**: Laboratories use step-up transformers to generate the high voltages needed for insulation testing and research.

#### Design Considerations

- **Insulation**: High-voltage insulation requirements for the secondary winding are more demanding.
- **Cooling**: Efficient cooling is critical due to the concentration of losses.
- **Surge Protection**: Must withstand lightning and switching surges on the high-voltage side.
- **Mechanical Strength**: Must withstand electromagnetic forces during fault conditions.

### 4.1.2 Step-Down Transformers

Step-down transformers decrease voltage from the primary to the secondary winding. They have fewer turns in the secondary winding than in the primary winding ($N_2 < N_1$).

#### Characteristics

- **Turns Ratio**: $N_2/N_1 < 1$
- **Voltage Transformation**: $V_2 < V_1$
- **Current Transformation**: $I_2 > I_1$
- **Winding Configuration**: The high-voltage primary winding has more turns of thinner conductor, while the low-voltage secondary winding has fewer turns of thicker conductor to handle higher current.

#### Applications

1. **Distribution Networks**: Step-down transformers reduce transmission voltages (110-765 kV) to distribution levels (4-35 kV) at substations, and further reduce distribution voltages to utilization levels (120-600V) for end users.

2. **Industrial Facilities**: Large industrial facilities often receive power at medium voltage (e.g., 11 kV or 33 kV) and use step-down transformers to supply equipment at lower voltages.

3. **Commercial Buildings**: Step-down transformers provide appropriate voltage levels for lighting, HVAC, and other building systems.

4. **Residential Applications**: Small step-down transformers are used in doorbell systems, HVAC controls, and other low-voltage residential applications.

5. **Electronic Devices**: Power adapters for electronic devices contain small step-down transformers (often switch-mode power supplies with transformers operating at high frequencies).

#### Design Considerations

- **Overload Capacity**: Distribution transformers often need good overload capability to handle peak demands.
- **Efficiency**: As these transformers operate continuously, efficiency is critical for reducing energy losses.
- **Voltage Regulation**: Must maintain stable output voltage despite load variations.
- **Protection**: Must include appropriate protection against overloads, short circuits, and other abnormal conditions.

### 4.1.3 Isolation Transformers

Isolation transformers have approximately equal numbers of turns in the primary and secondary windings ($N_1 \approx N_2$), resulting in similar voltage levels. Their primary purpose is to provide galvanic isolation between circuits rather than voltage transformation.

#### Characteristics

- **Turns Ratio**: $N_2/N_1 \approx 1$
- **Voltage Transformation**: $V_2 \approx V_1$
- **Current Transformation**: $I_2 \approx I_1$
- **Winding Configuration**: Similar construction for both windings, with emphasis on insulation between them.

#### Applications

1. **Medical Equipment**: Isolation transformers protect patients and sensitive medical devices from electrical hazards by breaking ground loops and providing separation from the main supply.
2. **Sensitive Electronic Equipment**: Audio, video, and laboratory equipment often use isolation transformers to reduce noise and interference.
3. **Computer Systems**: Data centers may use isolation transformers to protect against power line disturbances and ground loops.
4. **Safety Applications**: Isolation transformers are used in environments where electrical safety is critical, such as wet locations or where equipment is handled by non-technical personnel.
5. **Signal Isolation**: In control and instrumentation systems, isolation transformers separate different circuit sections to prevent interference and ground loops.

#### Design Considerations

- **Interwinding Insulation**: Enhanced insulation between primary and secondary windings to ensure reliable isolation.
- **Electrostatic Shielding**: Often includes shields between windings to block common-mode noise.
- **Leakage Current**: Minimized leakage current between primary and secondary for safety-critical applications.
- **Frequency Response**: For signal applications, must maintain fidelity across the required frequency range.

### 4.1.4 Variable Transformers

Variable transformers, while not strictly a voltage-level classification, deserve mention as they provide adjustable output voltage. The most common type is the autotransformer-based variable transformer (e.g., Variac).

**Characteristics**

- **Adjustable Turns Ratio**: A movable brush contact allows selection of different numbers of turns.
- **Continuous Adjustment**: Output voltage can be smoothly varied from zero to maximum.
- **Limited Isolation**: Typically does not provide galvanic isolation (unless specifically designed with isolated windings).

**Applications**

1. **Laboratory Testing**: Provides adjustable AC voltage for testing and experimentation.
2. **Light Dimmers**: Controls lighting intensity in theatrical and studio applications.
3. **Motor Speed Control**: Adjusts voltage for speed control of certain AC motors.
4. **Process Control**: Provides variable voltage for heating elements and other industrial processes.

**Design Considerations**

- **Brush Contact Design**: Must maintain reliable electrical contact while minimizing wear.
- **Cooling**: Adequate cooling for continuous operation at any setting.
- **Overload Protection**: Protection against excessive current at low voltage settings.

The classification of transformers based on voltage level is fundamental to understanding their role in electrical systems. Each type—step-up, step-down, and isolation—serves specific purposes in the generation, transmission, distribution, and utilization of electrical power, as well as in specialized applications requiring particular voltage relationships or electrical isolation.

## 4.2 Based on Construction

Transformer construction types significantly influence performance characteristics, applications, and manufacturing processes. The three main construction categories—core type, shell type, and berry type—each offer distinct advantages for specific applications.

### 4.2.1 Core Type Transformers

Core type transformers feature a magnetic circuit where the windings surround significant portions of the core.

#### Construction Features

- **Core Configuration**: Typically rectangular with two vertical limbs (legs) connected by horizontal yokes at the top and bottom.
- **Winding Arrangement**: Cylindrical windings surround the core limbs, with low-voltage windings typically placed closer to the core and high-voltage windings outside them.
- **Magnetic Circuit**: The magnetic flux follows a single path through the core.
- **Core Cross-Section**: Often cruciform or stepped circular to approximate a circular shape, maximizing the core area within cylindrical windings.

#### Advantages

1. **Efficient Cooling**: The cylindrical windings allow for effective oil circulation through cooling ducts.
2. **Simplified Insulation**: The concentric arrangement of windings simplifies insulation design between high and low voltage windings.
3. **Good Mechanical Strength**: The cylindrical form of windings provides inherent strength against radial forces during short circuits.
4. **Economical for Higher Voltages**: The design is well-suited for high-voltage applications due to efficient insulation arrangement.
5. **Easier Maintenance**: Windings can often be removed without complete core disassembly.

#### Limitations

1. **Higher Leakage Flux**: Tends to have higher leakage reactance compared to shell type.
2. **Less Protection for Windings**: Windings are more exposed compared to shell type designs.
3. **Larger Footprint**: May require more floor space for the same rating compared to shell type.

#### Applications

- Medium to large power transformers
- High-voltage applications
- Applications where cooling efficiency is critical
- Transformers requiring good short-circuit strength

### 4.2.2 Shell Type Transformers

Shell type transformers feature a magnetic circuit where the core surrounds significant portions of the windings.

#### Construction Features

- **Core Configuration**: Typically E-shaped or multiple-limbed, with the central limb carrying the windings and outer limbs providing return paths for the magnetic flux.
- **Winding Arrangement**: Windings are typically pancake or disc-type, arranged in a sandwich pattern around the central limb.
- **Magnetic Circuit**: The magnetic flux splits to follow multiple parallel paths through the outer limbs.
- **Core Cross-Section**: Rectangular cross-sections are common, efficiently enclosing the rectangular windings.

#### Advantages

1. **Lower Leakage Flux**: The core surrounding the windings contains the magnetic field better, reducing leakage reactance.
2. **Better Mechanical Protection**: Windings are enclosed within the core, providing better protection against mechanical damage.
3. **Excellent Short-Circuit Strength**: The sandwich winding arrangement provides superior resistance to axial forces during short circuits.
4. **Compact Design**: Often results in a smaller footprint for the same rating.
5. **Better Overload Capacity**: The distributed magnetic circuit can handle temporary overloads more effectively.

#### Limitations

1. **More Complex Cooling**: The enclosed nature of windings can make cooling more challenging.
2. **Heavier Core**: Requires more core material for the same power rating.
3. **More Complex Manufacturing**: The interleaved winding arrangement is more complex to manufacture.
4. **Maintenance Challenges**: Core disassembly is often required to access windings.

#### Applications

- Small to medium power transformers
- Low-voltage, high-current applications
- Audio transformers and other signal applications
- Applications requiring low leakage reactance

- Transformers subject to frequent mechanical stress or vibration

### 4.2.3 Berry Type Transformers

Berry type transformers (also called cruciform or radial transformers) feature a unique core construction with a wheel-like arrangement of laminations.

#### Construction Features

- **Core Configuration**: Laminations are arranged radially like spokes of a wheel, with the winding placed in the central opening.
- **Winding Arrangement**: Typically toroidal, surrounding the entire core structure.
- **Magnetic Circuit**: The magnetic flux follows a circular path through the radial laminations.
- **Core Cross-Section**: The cross-section varies along the flux path, with wider sections at the outer diameter.

#### Advantages

1. **Reduced Core Losses**: The radial arrangement of laminations can reduce eddy current losses.
2. **Compact Design**: The circular arrangement makes efficient use of space.
3. **Good Mechanical Stability**: The integrated structure provides inherent mechanical strength.
4. **Reduced Noise**: The design can result in lower noise levels during operation.

#### Limitations

1. **Manufacturing Complexity**: The unique lamination arrangement is more complex to manufacture.
2. **Limited Size Range**: Practical manufacturing constraints limit the size of berry type transformers.
3. **Cooling Challenges**: The compact design can make cooling more difficult in larger units.
4. **Less Common**: Less standardized design means less industry experience and fewer manufacturers.

#### Applications

- Specialized applications where the unique characteristics are advantageous
- Applications where noise reduction is important
- Medium-sized distribution transformers in certain markets
- Applications where the compact circular footprint is beneficial

### 4.2.4 Toroidal Transformers

While not one of the three traditional categories, toroidal transformers deserve mention as a distinct construction type with growing importance.

#### Construction Features

- **Core Configuration**: Donut-shaped (toroidal) core made from a continuous strip of steel wound in a spiral.
- **Winding Arrangement**: Windings are wound around the entire circumference of the ring-shaped core.
- **Magnetic Circuit**: The magnetic flux follows a continuous circular path within the core.
- **Core Cross-Section**: Typically circular or rectangular.

#### Advantages

1. **Extremely Low Leakage Flux**: The closed magnetic path results in minimal stray magnetic fields.
2. **High Efficiency**: Lower core losses due to the continuous core structure without joints.
3. **Compact Size**: Smaller and lighter than equivalent conventional transformers.
4. **Low Noise**: Minimal magnetostriction noise due to the continuous core structure.
5. **Low No-Load Current**: The efficient magnetic circuit requires less magnetizing current.

#### Limitations

1. **Specialized Winding Equipment**: Requires special machinery to wind coils around the closed core.
2. **Limited Size Range**: Practical manufacturing constraints typically limit size to smaller ratings.
3. **Cooling Challenges**: The compact design can make cooling more difficult in larger units.
4. **Higher Cost**: Manufacturing complexity can result in higher cost for the same rating.

#### Applications

- Audio equipment and high-fidelity applications
- Medical equipment where low stray fields are important
- Sensitive electronic equipment
- Space-constrained applications
- Applications where efficiency and low noise are priorities

The choice between core type, shell type, berry type, or toroidal construction depends on factors including power rating, voltage levels, application requirements, manufacturing capabilities, and economic considerations. Each construction type offers a unique balance of electrical performance, mechanical characteristics, thermal behavior, and cost, making them suitable for different segments of the transformer market.

# 4.3 Based on Core Material

The choice of core material significantly influences a transformer's performance characteristics, efficiency, size, weight, and suitable applications. Different materials offer varying combinations of magnetic permeability, saturation flux density, core losses, cost, and manufacturability.

## 4.3.1 Iron Core Transformers

Iron core transformers use various forms of iron-based magnetic materials, with silicon steel being the most common for power applications.

**Silicon Steel (Electrical Steel)**

Silicon steel is an iron alloy containing approximately 2-6% silicon, which increases electrical resistivity and reduces hysteresis losses.

**Characteristics:** - **Saturation Flux Density**: 1.7-2.0 Tesla - **Relative Permeability**: 4,000-7,000 - **Core Loss**: Moderate (0.7-1.5 W/kg at 1.5T, 50Hz) - **Cost**: Moderate - **Frequency Range**: Optimized for 50/60 Hz power applications

**Types of Silicon Steel:**

1. **Grain-Oriented Silicon Steel (GOSS)**
   - Manufactured with a special rolling process that aligns the grain structure in the rolling direction
   - Superior magnetic properties in the grain orientation direction
   - Lower core losses (typically 0.7-1.0 W/kg at 1.5T, 50Hz)
   - Used in high-efficiency power and distribution transformers
   - Available in standard grades (M4, M5, M6) and high-permeability grades (HiB)
2. **Non-Oriented Silicon Steel (NGOSS)**
   - Random grain orientation with similar magnetic properties in all directions
   - Higher core losses than GOSS (typically 1.0-1.5 W/kg at 1.5T, 50Hz)
   - Less expensive than grain-oriented steel

- Used in smaller transformers and rotating machines
- Available in various grades based on loss characteristics

**Applications:** - Power transformers - Distribution transformers - Industrial control transformers - General-purpose transformers operating at power frequencies

**Advantages:** - High saturation flux density allows compact designs - Well-established manufacturing processes - Good balance of cost and performance - Widely available in various grades and thicknesses

**Limitations:** - Significant losses at higher frequencies - Relatively heavy - Core losses contribute to heating and reduced efficiency

### 4.3.2 Ferrite Core Transformers

Ferrite cores are ceramic compounds composed of iron oxide combined with other metallic elements such as manganese, zinc, or nickel.

**Characteristics:** - **Saturation Flux Density**: 0.3-0.5 Tesla (much lower than silicon steel) - **Relative Permeability**: 1,000-15,000 (varies widely by composition) - **Core Loss**: Very low at high frequencies - **Cost**: Low to moderate - **Frequency Range**: 10 kHz to several MHz

**Types of Ferrites:**

1. **Manganese-Zinc (MnZn) Ferrites**
   - Higher permeability (1,000-15,000)
   - Higher saturation flux density (0.4-0.5T)
   - Used in applications from 10 kHz to 1 MHz
   - Suitable for power applications at these frequencies
2. **Nickel-Zinc (NiZn) Ferrites**
   - Lower permeability (100-1,000)
   - Lower saturation flux density (0.3-0.4T)
   - Higher resistivity than MnZn ferrites
   - Used in applications from 1 MHz to several hundred MHz
   - Suitable for RF applications

**Applications:** - Switch-mode power supplies (SMPS) - Flyback transformers in television and monitor circuits - RF transformers in communications equipment - Pulse transformers - Current transformers for electronic circuits - EMI suppression

**Advantages:** - Very low eddy current losses at high frequencies - Lightweight compared to iron cores - Available in various shapes (E-cores, pot cores, toroids) - Low cost for small components - High resistivity reduces need for laminations

**Limitations:** - Low saturation flux density requires larger cores for the same power - Brittle material susceptible to mechanical damage - Temperature-sensitive magnetic properties - Not suitable for high-power, low-frequency applications

### 4.3.3 Toroidal Core Transformers

Toroidal core transformers can use various materials, but the term often refers specifically to the construction method rather than the core material. However, certain materials are particularly well-suited to toroidal construction.

**Common Materials for Toroidal Cores:**

1. **Grain-Oriented Silicon Steel**
   - Wound as a continuous spiral strip
   - Grain orientation follows the circular path, maximizing efficiency
   - Used for power frequency applications
2. **Amorphous Metal**
   - Excellent for high-efficiency toroidal transformers
   - Lower losses than silicon steel
   - Used in premium efficiency applications
3. **Ferrite**
   - Used for high-frequency toroidal transformers
   - Common in switch-mode power supplies and RF applications
4. **Powdered Iron**
   - Used where DC bias is present
   - Provides distributed air gap
   - Common in inductors and certain specialized transformers

**Characteristics of Toroidal Construction:** - **Magnetic Path**: Continuous with no air gaps - **Flux Leakage**: Extremely low due to closed magnetic path - **Core Loss**: Lower than conventional constructions using the same material - **Size**: Compact compared to equivalent E-I or C-core designs

**Applications:** - Audio equipment (low noise, low stray fields) - Medical equipment (low electromagnetic interference) - Sensitive electronic equipment - Space-constrained applications - High-efficiency power supplies

**Advantages:** - Minimal external magnetic field - Lower core losses due to continuous magnetic path - Smaller size and weight for the same rating - Lower noise - Lower no-load current

**Limitations:** - More complex winding process - Higher manufacturing cost - Limited size range due to practical winding constraints - Cooling can be challenging due to compact construction

### 4.3.4 Air Core Transformers

Air core transformers have no magnetic core material, with windings wound on non-magnetic forms or self-supporting structures.

**Characteristics:** - **Saturation**: No magnetic saturation (linear operation at all flux levels) - **Relative Permeability**: Approximately 1 (same as air) - **Core Loss**: Zero (no hysteresis or eddy current losses) - **Coupling Coefficient**: Typically low (0.1-0.6) due to poor flux linkage - **Frequency Range**: From power frequencies to GHz range, but primarily used at high frequencies

**Applications:** - Radio frequency (RF) circuits - Wireless power transfer - Tesla coils - High-frequency oscillator circuits - Applications requiring linear operation at varying flux levels - Very high frequency applications where core losses would be prohibitive

**Advantages:** - No core losses (hysteresis or eddy currents) - No magnetic saturation - Linear operation across all power levels - Suitable for very high frequencies - No core-induced distortion - Lightweight

**Limitations:** - Very low coupling efficiency - Requires more turns for the same inductance - Large size for a given power rating - Significant leakage flux and electromagnetic interference - Limited to low-power or high-frequency applications

### 4.3.5 Amorphous Metal Core Transformers

Amorphous metal cores are made from alloys (typically iron, boron, and silicon) that are rapidly cooled from a molten state, resulting in a non-crystalline, random atomic structure.

**Characteristics:** - **Saturation Flux Density**: 1.4-1.6 Tesla (slightly lower than silicon steel) - **Relative Permeability**: 10,000-150,000 (higher than silicon steel) - **Core Loss**: Very low (0.2-0.3 W/kg at 1.5T, 50Hz) - 70-80% lower than conventional silicon steel - **Cost**: Higher than silicon steel - **Frequency Range**: Effective from power frequencies up to several kHz

**Applications:** - Distribution transformers with high efficiency requirements - Medium-frequency transformers (400Hz-2kHz) - Applications where energy efficiency is paramount - Green energy applications where lifecycle energy savings justify higher initial cost

**Advantages:** - Significantly lower core losses than silicon steel - Excellent performance under overload conditions - Good response to harmonic-rich loads - Lower operating temperature - Higher efficiency, especially at light loads

**Limitations:** - Higher material cost - More challenging to cut and process - Lower saturation flux density requires slightly larger cores - More brittle than silicon steel - Limited availability in certain markets

### 4.3.6 Nanocrystalline Core Transformers

Nanocrystalline cores are made from alloys with extremely fine grain structure (typically 10-30 nanometers), produced through controlled crystallization of amorphous precursors.

**Characteristics:** - **Saturation Flux Density**: 1.2-1.25 Tesla - **Relative Permeability**: Extremely high (up to 200,000) - **Core Loss**: Extremely low (better than amorphous metals) - **Cost**: High - **Frequency Range**: Effective from power frequencies up to 100 kHz

**Applications:** - High-precision current transformers - High-efficiency power transformers - Common mode chokes - Pulse transformers requiring excellent response - High-end power supplies - Applications requiring extremely low losses and high permeability

**Advantages:** - Lowest core losses of any commercially available magnetic material - Extremely high permeability - Excellent temperature stability - Superior frequency response - Exceptional performance in current transformers and precision applications

**Limitations:** - Very high cost - Limited availability - Mechanical fragility - Manufacturing challenges - Limited shape options

The selection of core material involves balancing multiple factors including operating frequency, required efficiency, size constraints, cost limitations, and specific application requirements. Modern transformer design increasingly employs computer modeling to optimize core material selection and design for specific performance targets, particularly as energy efficiency standards become more stringent worldwide.

## 4.4 Based on Purpose

Transformers are designed with specific applications in mind, resulting in specialized designs optimized for particular roles in electrical systems. This classification focuses on the primary function the transformer serves rather than its construction or electrical characteristics.

### 4.4.1 Power Transformers

Power transformers are large, high-capacity transformers designed to operate at high efficiency under relatively constant load conditions. They serve as the backbone of electrical transmission systems.

**Characteristics**

- **Rating**: Typically above 200 kVA
- **Voltage Levels**: High voltage (HV) and extra-high voltage (EHV), often 115 kV to 765 kV
- **Efficiency**: Extremely high (often >99% at full load)
- **Load Profile**: Designed for continuous operation at near-rated load
- **Cooling**: ONAN, ONAF, OFAF, or ODAF depending on size
- **Impedance**: Typically 7-14%
- **Construction**: Core-type construction is common for larger units

**Applications**

1. **Generation Step-Up**: Located at power plants to increase generator voltage to transmission levels
2. **Transmission Substations**: Interface between different voltage levels in the transmission network
3. **Interconnections**: Connect different power systems or grid sections
4. **Phase Shifting**: Control power flow between parallel transmission paths
5. **HVDC Conversion**: Interface between AC systems and HVDC transmission

**Design Considerations**

- **Efficiency**: Optimized for minimal losses at full load
- **Thermal Performance**: Designed for continuous operation at rated load
- **Short-Circuit Strength**: Must withstand severe fault conditions
- **Surge Protection**: Designed to withstand lightning and switching surges
- **Transportation Limitations**: Size and weight constraints for shipping
- **Monitoring**: Often equipped with extensive monitoring systems

## 4.4.2 Distribution Transformers

Distribution transformers are the final voltage transformation stage in the power delivery system, reducing medium voltage to the low voltage used by consumers.

**Characteristics**

- **Rating**: Typically below 200 kVA (though some definitions extend to 2500 kVA)
- **Voltage Levels**: Medium voltage primary (4-35 kV) to low voltage secondary (120-600V)
- **Efficiency**: High, but with design emphasis on low core losses
- **Load Profile**: Designed for variable loads with daily cycles
- **Cooling**: Primarily ONAN (self-cooled)
- **Impedance**: Typically 2-5%
- **Construction**: Core-type or shell-type depending on size and application

**Applications**

1. **Residential Service**: Pole-mounted or pad-mounted units serving neighborhoods
2. **Commercial Buildings**: Units serving office buildings, retail centers, etc.
3. **Light Industrial**: Supplying power to small industrial facilities
4. **Underground Distribution**: Pad-mounted or vault-installed units in urban areas
5. **Rural Electrification**: Often single-phase units serving remote areas

**Design Considerations**

- **All-Day Efficiency**: Optimized for good efficiency across varying load levels
- **Core Loss Emphasis**: Since transformers are energized 24/7 but fully loaded only during peak hours
- **Overload Capability**: Designed to handle temporary overloads during peak demand
- **Environmental Factors**: Must operate in various outdoor conditions
- **Maintenance**: Designed for minimal maintenance over long service life
- **Cost Optimization**: Balance between initial cost and lifetime energy losses

## 4.4.3 Instrument Transformers

Instrument transformers accurately transform voltage or current to standardized levels suitable for measuring instruments and protective relays.

**Current Transformers (CT)**

- **Function**: Transform high currents to standardized low values (typically 5A or 1A secondary)
- **Ratio**: Primary current to secondary current ratio (e.g., 100:5, 1000:5)
- **Accuracy Classes**: Defined by standards (e.g., 0.1, 0.2, 0.5, 1.0, 3.0)
- **Burden**: Rated VA capacity of secondary circuit
- **Types**:
  - **Wound Type**: Primary winding passes through core multiple times
  - **Bar Type**: Primary conductor passes once through core
  - **Bushing Type**: Built into equipment bushings
  - **Window Type**: Primary conductor passes through opening

**Potential (Voltage) Transformers (PT/VT)**

- **Function**: Transform high voltages to standardized low values (typically 100V, 110V, or 120V)
- **Ratio**: Primary voltage to secondary voltage ratio
- **Accuracy Classes**: Defined by standards (e.g., 0.1, 0.2, 0.5, 1.0, 3.0)
- **Burden**: Rated VA capacity of secondary circuit
- **Types**:
  - **Conventional Electromagnetic**: Traditional transformer design
  - **Capacitive Voltage Transformer (CVT)**: Uses capacitive voltage divider for EHV applications

**Applications**

1. **Metering**: Provide accurate voltage and current values for billing and energy management
2. **Protection**: Supply signals to protective relays for fault detection
3. **Monitoring**: Provide inputs for power quality monitoring and SCADA systems
4. **Control**: Supply signals for control systems and regulators

**Design Considerations**

- **Accuracy**: Primary concern, with precise control of errors across the operating range
- **Linearity**: Consistent performance across the measurement range
- **Saturation Characteristics**: Controlled behavior during fault conditions (for protection CTs)
- **Phase Angle Error**: Minimized for accurate power and energy measurement
- **Thermal Rating Factor**: Ability to exceed rated current while

maintaining accuracy
- **Insulation Coordination**: Must withstand system voltage stresses

### 4.4.4 Auto-Transformers

Auto-transformers have a single winding that serves as both primary and secondary, with a common section shared between input and output circuits.

#### Characteristics

- **Construction**: Single winding with taps
- **Connection**: Part of the winding is common to both primary and secondary circuits
- **Copper Savings**: Requires less copper than a two-winding transformer for the same rating
- **Isolation**: No electrical isolation between primary and secondary
- **Size and Weight**: Smaller and lighter than equivalent two-winding transformers
- **Cost**: Lower cost for the same rating (when modest voltage transformation is needed)

#### Applications

1. **Transmission System Interconnection**: Connect different voltage levels in transmission systems
2. **Motor Starting**: Reduce starting current by providing reduced voltage
3. **Tap Changing**: Voltage regulation in distribution systems
4. **Railway Electrification**: Interface between utility grid and railway power systems
5. **Testing**: Variable voltage sources in laboratories

#### Design Considerations

- **Fault Current Propagation**: No isolation means faults can propagate between voltage levels
- **Savings Factor**: Copper savings increase as the ratio between input and output voltages decreases
- **Neutral Grounding**: Special consideration needed for system grounding
- **Series Winding Protection**: The series winding (not shared) requires special protection
- **Surge Protection**: Coordinated protection required for both voltage levels

### 4.4.5 Rectifier Transformers

Rectifier transformers are specialized units designed to supply power to rectifier circuits for AC to DC conversion.

#### Characteristics

- **Winding Configurations**: Often include phase-shifting windings to reduce harmonics
- **Harmonic Handling**: Designed to withstand harmonic currents generated by rectifiers
- **Impedance**: Carefully selected to limit fault currents while minimizing voltage regulation
- **Cooling**: Enhanced cooling due to additional harmonic losses
- **Connections**: Often use multiple secondary windings with different phase relationships

#### Applications

1. **Industrial Electrolysis**: Aluminum, chlorine, and other electrochemical processes
2. **DC Arc Furnaces**: Steel and other metal production
3. **HVDC Transmission**: Conversion between AC and DC power systems
4. **Traction Power**: DC railway and transit systems
5. **Industrial DC Power**: Electroplating and other industrial processes

#### Design Considerations

- **Harmonic Mitigation**: Often use phase-shifted secondaries (e.g., 30° displacement)
- **Thermal Design**: Enhanced to handle additional heating from harmonic currents
- **Voltage Regulation**: Minimized for stable DC output
- **DC Bias Effects**: Design accommodates potential DC components in the current
- **Fault Coordination**: Coordinated with rectifier protection systems

### 4.4.6 Welding Transformers

Welding transformers provide the high current at low voltage required for resistance welding processes.

#### Characteristics

- **Output**: Low voltage (typically 2-20V), very high current

(hundreds to thousands of amperes)
- **Duty Cycle**: Designed for intermittent operation with high peak loads
- **Impedance**: Relatively high to limit short-circuit current
- **Construction**: Often shell-type for better mechanical strength
- **Cooling**: Enhanced cooling for high current operation

**Applications**

1. **Resistance Spot Welding**: Automotive manufacturing and sheet metal fabrication
2. **Seam Welding**: Continuous welding of sheet metal
3. **Projection Welding**: Welding at predetermined points
4. **Arc Welding**: Some designs serve arc welding applications

**Design Considerations**

- **Secondary Conductors**: Massive low-resistance conductors for high current
- **Thermal Cycling**: Designed for rapid heating and cooling cycles
- **Mechanical Strength**: Robust construction to withstand electromagnetic forces
- **Control Integration**: Often designed to work with specific control systems
- **Portability**: Many designs emphasize compact size and lower weight

### 4.4.7 Isolation Transformers

While mentioned under voltage-level classification, isolation transformers deserve additional attention as a purpose-specific category.

**Characteristics**

- **Turns Ratio**: Typically 1:1, though not always
- **Isolation**: Enhanced insulation between primary and secondary
- **Shielding**: Often includes electrostatic shields between windings
- **Leakage Current**: Minimized for safety-critical applications
- **Noise Suppression**: Designed to block common-mode noise

**Applications**

1. **Medical Equipment**: Patient safety in healthcare environments
2. **Sensitive Electronics**: Protection of audio, video, and laboratory equipment
3. **Marine and Wet Environments**: Enhanced safety where water

increases shock hazards
4. **Test Equipment**: Isolation of test equipment from devices under test
5. **Data Centers**: Clean power for sensitive computing equipment

**Design Considerations**

- **Interwinding Capacitance**: Minimized to reduce coupling of transients
- **Electrostatic Shielding**: Blocks common-mode noise
- **Leakage Current**: Critical parameter for medical and safety applications
- **Surge Protection**: Often includes enhanced insulation for transient protection
- **Noise Attenuation**: Designed to block conducted interference

### 4.4.8 Phase-Shifting Transformers

Phase-shifting transformers deliberately create a phase angle difference between input and output voltages.

**Characteristics**

- **Phase Shift**: Introduces a controlled phase angle difference (typically 30° or multiples)
- **Power Flow Control**: Ability to control active power flow between systems
- **Construction**: Complex winding arrangements to create phase shifts
- **Control**: May include on-load tap changers for adjustable phase shift

**Applications**

1. **Power Flow Control**: Managing power flow between parallel transmission paths
2. **Harmonic Mitigation**: Phase-shifted secondaries for multi-pulse rectifier systems
3. **Grid Interconnection**: Controlling power exchange between different grid sections
4. **Loop Flow Management**: Preventing undesired power flows in meshed networks
5. **HVDC Conversion**: Creating phase shifts for multi-pulse converters

**Design Considerations**

- **Vector Group**: Specialized vector groups to achieve desired phase

shifts
- **Tap Changing**: May include complex tap-changing mechanisms
- **Thermal Design**: Accounts for additional losses from circulating currents
- **Fault Current Limitation**: Often designed to limit fault current contribution
- **Control Systems**: Integration with power system control and protection

The classification of transformers based on purpose highlights the remarkable versatility of transformer technology in addressing diverse requirements across the electrical power system. Each specialized type represents an optimization of the basic transformer principles to meet specific operational needs, balancing factors such as efficiency, cost, size, reliability, and performance characteristics unique to each application.

# 4.5 Based on Phases

The number of phases in a transformer is a fundamental classification that directly relates to the power system it serves. Single-phase and three-phase transformers have distinct characteristics, applications, and design considerations.

## 4.5.1 Single-Phase Transformers

Single-phase transformers are designed to operate on single-phase AC circuits, with one primary and one secondary winding (or multiple secondary windings) on a common core.

**Construction**

- **Core**: Typically E-I laminations, UI (shell type), or toroidal
- **Windings**: One primary and one or more secondary windings
- **Magnetic Circuit**: Single magnetic path for flux
- **Terminals**: Two primary terminals and two or more secondary terminals

**Characteristics**

- **Power Rating**: Typically smaller than three-phase units (up to several MVA)
- **Voltage Levels**: Available for all voltage classes, from low voltage to transmission levels
- **Efficiency**: Generally high, but slightly lower than equivalent three-phase units
- **Size and Weight**: For the same power rating, three single-phase

units require more material than one three-phase unit
- **Cost**: Higher cost per kVA compared to three-phase for larger ratings

**Applications**

1. **Residential Power**: Supply to homes and small businesses
2. **Rural Distribution**: Areas with lower density where three-phase is not economical
3. **Railway Electrification**: Single-phase traction power systems
4. **Specialized Industrial**: Specific industrial processes requiring single-phase power
5. **Phase Balancing**: Balancing loads in three-phase systems
6. **High-Voltage Transmission**: Single-phase units used in banks for very high voltage applications

**Advantages**

1. **Simplicity**: Simpler design and construction
2. **Redundancy**: In banks of single-phase units, a spare can replace any failed unit
3. **Transportation**: Easier to transport for very large ratings
4. **Replacement**: Individual units can be replaced without disturbing others
5. **Flexibility**: Can be connected in various configurations when used in banks

**Limitations**

1. **Material Usage**: Less efficient use of core material compared to three-phase
2. **Footprint**: Larger total footprint for the same power rating
3. **Cost**: Higher cost per kVA for larger ratings
4. **Connections**: Requires external connections when used in three-phase banks

## 4.5.2 Three-Phase Transformers

Three-phase transformers are designed to transform power in three-phase systems, with three primary and three secondary windings on a common core structure.

**Construction**

- **Core**: Typically three-limb, five-limb, or shell type
- **Windings**: Three primary and three secondary windings
- **Magnetic Circuit**: Integrated magnetic circuit with flux paths for all three phases

- **Terminals**: Three primary terminals and three or four secondary terminals (depending on winding connection)

**Core Configurations**

1. **Three-Limb Core**:
   - Most common design
   - Three vertical limbs connected by horizontal yokes
   - Compact and economical
   - Limitation: Reluctance path for zero-sequence flux is through oil and tank
2. **Five-Limb Core**:
   - Three main limbs for the phases plus two outer return limbs
   - Better path for zero-sequence flux
   - Used for larger units and special applications
   - More expensive but better performance for certain conditions
3. **Shell Type**:
   - Windings surrounded by core material
   - Excellent mechanical strength
   - Good short-circuit withstand capability
   - Often used for special applications

**Characteristics**

- **Power Rating**: From small distribution units to hundreds of MVA
- **Voltage Levels**: All voltage classes, from low voltage to EHV transmission
- **Efficiency**: Slightly higher than equivalent single-phase units
- **Size and Weight**: More compact and lighter than three single-phase units of equivalent total rating
- **Cost**: Lower cost per kVA compared to single-phase for larger ratings

**Applications**

1. **Power Generation**: Step-up transformers at generating stations
2. **Transmission Substations**: Interconnection between transmission voltage levels
3. **Distribution Substations**: Step-down from transmission to distribution voltages
4. **Industrial Power**: Supply to industrial facilities
5. **Commercial Buildings**: Supply to large commercial complexes

**Advantages**

1. **Material Efficiency**: Better utilization of core material
2. **Footprint**: Smaller footprint for the same power rating
3. **Cost**: Lower cost per kVA for larger ratings

4. **Connections**: Internal connections between phases
5. **Installation**: Simpler installation with fewer units

**Limitations**

1. **Transportation**: Size and weight limitations for very large units
2. **Redundancy**: Failure affects all three phases
3. **Spare Requirements**: Complete unit needed as spare
4. **Repair**: More complex repair procedures

### 4.5.3 Three-Phase Transformer Connections

Three-phase transformers can be connected in various configurations, each with specific characteristics and applications.

**Star (Wye) Connection**

- **Symbol**: Y
- **Characteristics**:
  - Line voltage = √3 × phase voltage
  - Line current = phase current
  - Neutral point available
  - Suitable for grounded systems
- **Applications**:
  - Distribution systems requiring neutral
  - Step-down applications where neutral is needed
  - Systems requiring ground reference

**Delta Connection**

- **Symbol**: Δ
- **Characteristics**:
  - Line voltage = phase voltage
  - Line current = √3 × phase current
  - No neutral point
  - Circulating path for third-harmonic currents
- **Applications**:
  - Industrial power systems
  - Generator step-up transformers
  - Systems where third-harmonic suppression is important

**Common Three-Phase Transformer Connections**

1. **Delta-Star (Δ-Y)**:
   - Primary: Delta, Secondary: Star
   - Applications: Step-down distribution transformers
   - Advantages: Provides neutral on secondary, blocks third harmonics from primary

2. **Star-Delta (Y-Δ)**:
    - Primary: Star, Secondary: Delta
    - Applications: Generator step-up transformers
    - Advantages: Provides ground reference on primary, blocks third harmonics from secondary
3. **Delta-Delta (Δ-Δ)**:
    - Primary: Delta, Secondary: Delta
    - Applications: Industrial power systems
    - Advantages: Good stability, no neutral shift issues, can operate with one phase damaged (open-delta)
4. **Star-Star (Y-Y)**:
    - Primary: Star, Secondary: Star
    - Applications: Transmission systems
    - Limitations: Potential issues with third harmonics and neutral shift
    - Often includes delta tertiary winding to mitigate these issues
5. **Zigzag Connection (Z)**:
    - Special connection with each phase winding split into two parts
    - Applications: Grounding transformers, harmonic mitigation
    - Advantages: Provides neutral reference, blocks zero-sequence currents

## 4.5.4 Special Three-Phase Configurations

#### Open-Delta (V-V) Connection

- Uses only two single-phase transformers to create a three-phase system
- Delivers approximately 57.7% of the capacity of a full delta-delta bank
- Applications: Emergency operation after failure of one transformer in a delta-delta bank, rural areas with light three-phase loads

#### Scott Connection

- Converts three-phase to two-phase power
- Uses two single-phase transformers with special connections
- Applications: Legacy two-phase systems, special industrial processes

#### T-Connection

- Uses two single-phase transformers to create a three-phase system
- One transformer is center-tapped
- More economical than full three-phase but higher capacity than open-delta
- Applications: Rural areas, light industrial loads

**Zig-Zag Grounding Transformer**

- Special connection providing a path for zero-sequence currents
- Creates artificial neutral point in ungrounded systems
- Applications: System grounding, harmonic filtering

### 4.5.5 Polyphase Transformers Beyond Three-Phase

While three-phase is the standard for power systems, other polyphase configurations exist for specialized applications:

**Six-Phase Transformers**

- Used in some high-power rectifier applications
- Reduces harmonics in the AC supply
- Applications: Large DC drives, HVDC conversion

**Twelve-Phase Transformers**

- Used in high-power rectifier systems
- Further harmonic reduction compared to six-phase
- Applications: Very large HVDC converters, large electrochemical processes

**Split-Phase Transformers**

- Convert single-phase to two-phase power
- Common in residential power systems (120/240V)
- Applications: Residential power distribution, small commercial buildings

The classification of transformers based on phases is fundamental to power system engineering. The choice between single-phase and three-phase designs, along with the selection of appropriate connections, significantly impacts system performance, reliability, cost, and operational characteristics. Modern power systems predominantly use three-phase transformers for larger applications, with single-phase units serving specific roles where their unique advantages are beneficial.

## 4.6 Special Types

Beyond the standard classifications, several specialized transformer types serve unique applications with specific design features tailored to their functions.

### 4.6.1 Autotransformers

Autotransformers differ from conventional transformers by using a single winding that serves as both primary and secondary, with a portion of the winding common to both circuits.

**Construction and Working Principle**

- **Winding**: Single winding with at least one tap connection
- **Common Section**: Part of the winding is common to both primary and secondary circuits
- **Connections**: Three terminals for a fixed-ratio autotransformer (two ends plus tap)
- **Power Transfer**: Combination of conductive (direct) and inductive (transformer action) power transfer

**Characteristics**

- **Copper Savings**: Requires less copper than a two-winding transformer
  - Copper saving factor = (1 - k) × 100%, where k = Vlow/Vhigh
  - Greater savings when the voltage ratio is closer to 1:1
- **Size and Weight**: Smaller and lighter than equivalent two-winding transformers
- **Cost**: Lower cost for the same rating
- **Efficiency**: Higher efficiency due to reduced copper losses
- **Impedance**: Lower impedance than equivalent two-winding transformer
- **Fault Current**: Higher fault current due to direct connection

**Applications**

1. **Transmission System Interconnection**: Connecting different voltage levels in transmission systems (e.g., 345kV to 138kV)
2. **Generator Step-Up**: Some generators use autotransformers for initial voltage increase
3. **Motor Starting**: Reduced voltage starting for large motors
4. **Variable Transformers**: Adjustable output voltage control (e.g., Variac)
5. **Railway Electrification**: Interface between utility grid and railway power systems
6. **Voltage Regulation**: Line voltage regulators in distribution systems

**Advantages**

1. **Material Efficiency**: Less copper required
2. **Lower Losses**: Reduced copper losses
3. **Smaller Size**: Reduced size and weight
4. **Lower Cost**: More economical for modest voltage transformations

5. **Better Voltage Regulation**: Lower impedance results in better voltage regulation
6. **Higher Efficiency**: Particularly at high loads

**Limitations**

1. **No Isolation**: No electrical isolation between primary and secondary
2. **Fault Propagation**: Faults can propagate between voltage levels
3. **Limited Voltage Ratio**: Not economical for large voltage differences
4. **Higher Fault Currents**: Direct connection increases available fault current
5. **DC Saturation Risk**: More susceptible to DC saturation from geomagnetic disturbances

## 4.6.2 Tap-Changing Transformers

Tap-changing transformers allow adjustment of the turns ratio to regulate output voltage under varying load or input voltage conditions.

**Types of Tap Changers**

1. **De-energized Tap Changers (DETC)**:
   - Require transformer to be de-energized before changing taps
   - Simple mechanical selector switch
   - Typically provide ±2.5% or ±5% adjustment in 2-5 steps
   - Used for infrequent adjustments to accommodate system changes
2. **On-Load Tap Changers (OLTC)**:
   - Allow tap changing while the transformer remains energized and loaded
   - Complex mechanism with transition impedance to prevent circulating currents
   - Typically provide ±10% to ±20% adjustment in 16-32 steps
   - Used for active voltage regulation in response to load changes

**Construction and Components**

- **Tap Winding**: Additional taps on one winding (typically the high-voltage winding)
- **Selector Mechanism**: Selects the appropriate tap
- **Diverter Switch**: For OLTC, transfers load between taps without interruption
- **Transition Impedance**: Resistors or reactors to limit circulating current during switching
- **Drive Mechanism**: Motor drive for OLTC operation

- **Control System**: Automatic control based on voltage, current, or other parameters

**Applications**

1. **Distribution Voltage Regulation**: Maintaining stable voltage despite load variations
2. **Transmission System Control**: Controlling voltage profiles and reactive power flow
3. **Industrial Plants**: Compensating for voltage fluctuations in industrial power systems
4. **Phase Angle Regulation**: Some designs adjust phase angle for power flow control
5. **Generator Step-Up**: Accommodating generator voltage variations

**Considerations**

1. **Maintenance Requirements**: OLTCs require regular maintenance due to contact wear
2. **Reliability**: OLTC mechanisms are among the most common failure points in transformers
3. **Control Strategy**: Various control schemes based on voltage, current, time, or load
4. **Monitoring**: Modern units include condition monitoring for OLTC mechanisms
5. **Life Expectancy**: OLTC contacts have limited operational life based on number of operations

### 4.6.3 Dry-Type Transformers

Dry-type transformers use air, gas, or solid insulation instead of liquid insulation, offering advantages in certain applications.

**Insulation Types**

1. **Open Wound (Air-Cooled)**:
   - Individual conductors insulated with high-temperature materials
   - Air circulation provides cooling
   - Simple design but limited voltage range
2. **Vacuum Pressure Impregnated (VPI)**:
   - Windings impregnated with varnish or resin under vacuum
   - Better thermal performance than open wound
   - Improved environmental protection
3. **Cast Resin**:
   - Windings completely encapsulated in epoxy resin
   - Excellent environmental protection
   - Good thermal conductivity with appropriate fillers

    - Higher cost but superior performance in harsh environments
4. **Gas-Insulated**:
    - Uses SF6 or other insulating gases
    - High dielectric strength
    - Used in specialized applications

**Cooling Classifications**

- **AN**: Air Natural cooling
- **AF**: Air Forced cooling (with fans)
- **ANAF**: Air Natural/Air Forced (fans activate at higher loads)

**Applications**

1. **Indoor Installations**: Where fire risk must be minimized
2. **Commercial Buildings**: Office buildings, shopping centers, hospitals
3. **Industrial Plants**: Areas with flammable materials or processes
4. **Marine Applications**: Shipboard power systems
5. **Underground Installations**: Mines, subway systems
6. **Environmentally Sensitive Areas**: Where oil leaks would be problematic

**Advantages**

1. **Fire Safety**: Reduced fire hazard compared to oil-filled units
2. **Environmental**: No risk of oil leaks or contamination
3. **Installation Flexibility**: Can be installed closer to loads, often without fire barriers
4. **Maintenance**: Generally lower maintenance requirements
5. **Indoor Use**: Suitable for indoor installation without special containment

**Limitations**

1. **Size**: Larger than equivalent oil-filled units
2. **Cost**: Higher cost for the same rating
3. **Noise**: Often noisier than oil-filled units
4. **Overload Capacity**: Limited thermal capacity for overloads
5. **Voltage Limitation**: Typically limited to medium voltage applications

## 4.6.4 Pad-Mounted Transformers

Pad-mounted transformers are specifically designed for underground distribution systems, combining transformer and switchgear in a tamper-resistant enclosure.

**Construction**

- **Enclosure**: Weatherproof, tamper-resistant steel cabinet
- **Compartmentalization**: Separate high-voltage and low-voltage compartments
- **Cooling**: Typically oil-filled with ONAN cooling
- **Bushings**: Elbow-type connectors for underground cable connections
- **Protection**: Internal fuses, bayonet fuses, or circuit breakers

**Characteristics**

- **Rating**: Typically 25-2500 kVA
- **Primary Voltage**: 4-35 kV class
- **Secondary Voltage**: 120/240V, 208Y/120V, 480Y/277V common
- **Configuration**: Single-phase or three-phase
- **Appearance**: Green or brown enclosure designed to blend with landscaping

**Applications**

1. **Residential Subdivisions**: Underground service to homes
2. **Commercial Developments**: Shopping centers, office parks
3. **Campus Environments**: Universities, hospitals, corporate campuses
4. **Urban Areas**: Where aesthetics and space constraints are important
5. **Areas with Severe Weather**: Reduced vulnerability to storms compared to overhead

**Features**

1. **Safety**: Dead-front construction with no exposed live parts
2. **Security**: Tamper-resistant design with padlocked doors
3. **Aesthetics**: Low profile design that blends with surroundings
4. **Accessibility**: Front and side access for maintenance
5. **Configurability**: Available with various switching and protection options

## 4.6.5 Grounding Transformers

Grounding transformers establish a neutral point in ungrounded or impedance-grounded systems, providing a path for zero-sequence currents during ground faults.

**Types**

1. **Zig-Zag Grounding Transformer**:

    - Special winding connection creating artificial neutral
    - High impedance to balanced three-phase currents
    - Low impedance to zero-sequence currents
    - No secondary winding required
2. **Wye-Delta Grounding Transformer**:
    - Wye-connected primary with grounded neutral
    - Delta-connected secondary (often not loaded)
    - Provides path for zero-sequence currents
    - Can supply auxiliary loads from delta winding
3. **Grounding Autotransformer**:
    - Single wye-connected winding with grounded neutral
    - Simpler than zig-zag but higher impedance
    - Used in specific applications

**Applications**

1. **Ungrounded System Grounding**: Providing ground reference without solid grounding
2. **Delta System Grounding**: Creating neutral in delta-connected systems
3. **Ground Fault Protection**: Enabling ground fault detection and protection
4. **Harmonic Filtering**: Some designs filter triple-harmonic currents
5. **Mixed System Interconnection**: Connecting differently grounded systems

**Characteristics**

- **Continuous Rating**: Typically 10-40% of the system three-phase rating
- **Short-Time Rating**: Must withstand ground fault current for protection clearing time
- **Impedance**: Carefully selected to limit fault current while allowing detection
- **Connection**: Often includes neutral grounding resistor or reactor

## 4.6.6 Mobile Transformers

Mobile transformers are designed for temporary installation or emergency replacement, mounted on trailers or skids for rapid deployment.

**Construction**

- **Mounting**: Trailer, skid, or containerized
- **Cooling**: Typically ONAN or ONAF for simplicity
- **Connections**: Quick-connect cable terminations or flexible leads
- **Protection**: Integrated surge arresters and protection devices

- **Auxiliaries**: Self-contained cooling and monitoring systems

**Characteristics**

- **Rating**: Typically 5-100 MVA
- **Voltage**: Various voltage classes available
- **Mobility**: Designed for road transport with minimal special permits
- **Setup Time**: Designed for rapid installation (hours rather than days)
- **Flexibility**: Often includes multiple voltage taps for different applications

**Applications**

1. **Emergency Replacement**: Temporary replacement for failed units
2. **Planned Outages**: Maintaining service during transformer maintenance
3. **Temporary Service**: Construction power, seasonal loads
4. **Disaster Recovery**: Restoring power after natural disasters
5. **Capacity Addition**: Temporary capacity increase during system upgrades

**Features**

1. **Transportability**: Designed for legal road transport
2. **Quick Installation**: Minimal site preparation required
3. **Self-Contained**: Includes all necessary accessories
4. **Flexibility**: Adaptable to various system configurations
5. **Monitoring**: Often includes enhanced monitoring for unattended operation

### 4.6.7 Phase-Shifting Transformers

Phase-shifting transformers (also called phase angle regulating transformers) control active power flow by introducing a phase angle difference between input and output voltages.

**Construction**

- **Windings**: Complex arrangement of main and regulating windings
- **Tap Changers**: Often include on-load tap changers for angle adjustment
- **Core**: Typically three-phase shell type or multiple single-phase units
- **Cooling**: ONAN, ONAF, or OFAF depending on size

**Operating Principle**

- Creates phase angle shift between input and output voltages
- Adjustable shift typically ±30° in 1-2° steps
- Controls active power flow according to the equation $P = (V_1V_2/X) \sin \delta$ (where $\delta$ is the phase angle difference)

**Applications**

1. **Parallel Path Control**: Managing power flow between parallel transmission paths
2. **Loop Flow Control**: Preventing undesired power flows in meshed networks
3. **Tie-Line Control**: Managing power exchange between different systems
4. **Congestion Management**: Redirecting power flow to avoid overloaded lines
5. **System Stability Enhancement**: Controlling power flow for stability improvement

**Characteristics**

- **Rating**: Typically 100-1000 MVA
- **Voltage**: Transmission voltage classes (115-500 kV)
- **Phase Shift**: Adjustable, typically ±15° to ±30°
- **Control**: Local and remote control capabilities
- **Monitoring**: Extensive monitoring and protection systems

## 4.6.8 Converter Transformers

Converter transformers are specialized units designed to interface between AC systems and high-voltage direct current (HVDC) or flexible AC transmission system (FACTS) converters.

**Construction**

- **Windings**: Often include multiple secondary windings with phase shifts
- **Insulation**: Enhanced to withstand combined AC and DC voltage stress
- **Core**: Designed to handle DC bias and harmonics
- **Cooling**: Typically OFAF or ODAF due to additional harmonic losses
- **Bushings**: Special design for converter connections

**Characteristics**

- **Rating**: Typically 200-1500 MVA

- **Voltage**: EHV classes (up to 800 kV AC)
- **Harmonics**: Designed to withstand harmonic currents from converters
- **DC Bias**: Core design accommodates potential DC components
- **Impedance**: Carefully selected for converter operation

**Applications**

1. **HVDC Transmission**: Interface between AC grid and HVDC converters
2. **Back-to-Back HVDC**: Interconnection between asynchronous AC systems
3. **FACTS Devices**: Supply to static VAR compensators and other FACTS devices
4. **Variable Frequency Drives**: Large industrial drives
5. **Renewable Integration**: Interface for large wind and solar installations

**Special Features**

1. **Harmonic Mitigation**: Often use phase-shifted windings for harmonic cancellation
2. **Thermal Design**: Enhanced cooling for harmonic losses
3. **Insulation Coordination**: Special design for converter-specific voltage stresses
4. **Testing**: Special test requirements beyond standard transformer tests
5. **Monitoring**: Enhanced monitoring for converter-specific stresses

The diverse range of special transformer types demonstrates the adaptability of transformer technology to meet specific application requirements. Each specialized design represents an optimization of the basic transformer principles to address particular operational needs, environmental conditions, or system constraints. As power systems continue to evolve with increasing integration of renewable energy, distributed generation, and power electronics, new specialized transformer designs will likely emerge to meet these changing requirements.# Chapter 5: Transformer Operation Under Load

# 5.1 No-Load Operation

When a transformer is connected to a voltage source but has no load connected to its secondary winding, it is said to be operating under no-load conditions. This state provides valuable insights into the transformer’s core behavior and magnetizing characteristics.

## 5.1.1 No-Load Current

When an alternating voltage is applied to the primary winding with the secondary winding open-circuited, a small current flows in the primary winding. This current is known as the no-load current or exciting current ($I_0$).

The no-load current serves two purposes: 1. To establish the alternating magnetic flux in the core (magnetizing component) 2. To supply the energy lost due to hysteresis and eddy currents in the core (core loss component)

Therefore, the no-load current can be represented as:

$I_0 = I_m + I_v$

Where: - $I_0$ is the total no-load current - $I_m$ is the magnetizing component (responsible for establishing the magnetic field) - $I_v$ is the core loss component (active component that supplies the hysteresis and eddy current losses)

The no-load current is typically 2-5% of the rated current for distribution transformers and 1-2% for power transformers. Despite being small in magnitude, the no-load current provides critical information about the transformer's magnetic circuit.

### 5.1.2 Magnetic Flux in No-Load Condition

When an alternating voltage $v_1 = V_1\sin(\omega t)$ is applied to the primary winding, it induces an EMF $e_1$ in accordance with Faraday's law:

$e_1 = -N_1(d\Phi/dt)$

Where: - $e_1$ is the induced EMF - $N_1$ is the number of turns in the primary winding - $\Phi$ is the magnetic flux - $d\Phi/dt$ is the rate of change of flux

For an ideal transformer with negligible resistance, the applied voltage $v_1$ and the induced EMF $e_1$ are equal in magnitude but opposite in phase:

$v_1 = -e_1 = N_1(d\Phi/dt)$

Rearranging:

$d\Phi/dt = v_1/N_1 = V_1\sin(\omega t)/N_1$

Integrating both sides:

$\Phi = -(V_1/\omega N_1)\cos(\omega t) = \Phi_m\sin(\omega t - \pi/2)$

Where $\Phi_m = V_1/\omega N_1 = V_1/2\pi f N_1$ is the maximum value of the flux.

This equation shows that the flux waveform lags the applied voltage by 90° and has a sinusoidal waveform if the applied voltage is sinusoidal.

### 5.1.3 Phasor Diagram Under No-Load Condition

The phasor diagram for a transformer under no-load conditions illustrates the relationship between the applied voltage, induced EMF, magnetic flux, and no-load current.

Key characteristics of the no-load phasor diagram: 1. The magnetic flux ($\Phi$) lags the applied voltage ($V_1$) by 90° 2. The magnetizing current ($I_m$) is in phase with the flux ($\Phi$) 3. The core loss component ($I_v$) is in phase with the applied voltage ($V_1$) 4. The total no-load current ($I_0$) lags the applied voltage by an angle $\varphi_0$ 5. The power factor under no-load conditions is $\cos(\varphi_0)$, typically between 0.1 and 0.3, indicating a highly inductive circuit

### 5.1.4 Core Saturation Effects

In practical transformers, the relationship between the magnetizing current and the magnetic flux is non-linear due to the magnetic saturation of the core material. As the applied voltage increases, the core approaches saturation, causing the magnetizing current to increase disproportionately.

The effects of core saturation include: 1. Distortion of the magnetizing current waveform (becomes non-sinusoidal even with sinusoidal applied voltage) 2. Generation of harmonics, particularly odd harmonics 3. Increased magnetizing current and core losses 4. Potential overheating and reduced efficiency

Transformer designers carefully select the operating flux density to balance between material utilization and avoiding excessive saturation effects.

## 5.2 Load Operation

When a load is connected to the secondary winding of a transformer, current flows in the secondary circuit, and the transformer is said to be operating under load conditions. The behavior of the transformer changes significantly from the no-load condition.

### 5.2.1 Effect of Secondary Current

When a load is connected to the secondary winding, a current $I_2$ flows through it. This current produces its own magnetomotive force (MMF), which according to Lenz’s law, opposes the change in the

magnetic flux that produced it.

If this opposing MMF were to reduce the main flux in the core, the induced EMF in the primary winding would decrease. However, since the primary winding is connected to a constant voltage source, any reduction in induced EMF would create an imbalance between the applied voltage and the induced EMF, causing an additional current to flow in the primary winding.

This additional primary current produces an MMF that exactly counterbalances the demagnetizing effect of the secondary current, maintaining the core flux at essentially the same level as under no-load conditions.

### 5.2.2 Primary Current Under Load

The total primary current under load conditions consists of two components: 1. The no-load current ($I_0$), which is responsible for establishing the magnetic flux 2. The load component ($I_2'$), which counteracts the demagnetizing effect of the secondary current

Therefore: $I_1 = I_0 + I_2'$

Where $I_2'$ is the secondary current referred to the primary side: $I_2' = I_2 \times (N_2/N_1)$

Since the no-load current is typically very small compared to the load component (usually 1-5% of the rated current), it is often neglected in approximate calculations: $I_1 \approx I_2'$

This approximation leads to the familiar relationship for an ideal transformer: $I_1/I_2 = N_2/N_1$

### 5.2.3 Voltage Drops Under Load

In a practical transformer, the terminal voltage differs from the induced EMF due to internal impedances. When current flows through the windings, voltage drops occur due to:

1. Resistance of the windings ($R_1$ and $R_2$)
2. Leakage reactance of the windings ($X_1$ and $X_2$)

These voltage drops cause the secondary terminal voltage to be less than what would be expected from the turns ratio alone, especially under heavy loads.

For the primary side: $V_1 = E_1 + I_1R_1 + I_1X_1$

For the secondary side: $E_2 = V_2 + I_2R_2 + I_2X_2$

Where: - $V_1$, $V_2$ are the terminal voltages - $E_1$, $E_2$ are the induced EMFs - $I_1$, $I_2$ are the currents - $R_1$, $R_2$ are the winding resistances - $X_1$, $X_2$ are the leakage reactances

### 5.2.4 Phasor Diagram Under Load Condition

The phasor diagram for a transformer under load conditions is more complex than the no-load diagram, as it must account for the various voltage drops and phase relationships.

The key elements in the load phasor diagram include: 1. Primary and secondary terminal voltages ($V_1$ and $V_2$) 2. Primary and secondary induced EMFs ($E_1$ and $E_2$) 3. Primary and secondary currents ($I_1$ and $I_2$) 4. Resistance voltage drops ($I_1R_1$ and $I_2R_2$) 5. Leakage reactance voltage drops ($I_1X_1$ and $I_2X_2$) 6. Core flux ($\Phi$)

The exact appearance of the phasor diagram depends on the nature of the load (resistive, inductive, capacitive, or a combination).

## 5.3 Voltage Regulation

Voltage regulation is a measure of how well a transformer maintains its secondary voltage as the load changes from no-load to full-load conditions. It is defined as the change in secondary voltage from no-load to full-load, expressed as a percentage of the full-load voltage.

### 5.3.1 Definition and Formula

Voltage regulation is mathematically expressed as:

Voltage Regulation (%) = $((V_2(\text{no-load}) - V_2(\text{full-load})) / V_2(\text{full-load})) \times 100$

Where: - $V_2(\text{no-load})$ is the secondary terminal voltage at no-load - $V_2(\text{full-load})$ is the secondary terminal voltage at full-load

A lower percentage of voltage regulation indicates better voltage regulation performance, meaning the transformer maintains a more constant output voltage regardless of load changes.

### 5.3.2 Factors Affecting Voltage Regulation

Several factors influence the voltage regulation of a transformer:

1. **Winding Resistance**: Higher resistance leads to greater voltage drops and poorer regulation.
2. **Leakage Reactance**: Higher leakage flux results in poorer regulation.

3. **Load Power Factor**: The power factor of the load significantly affects voltage regulation:
    - For resistive loads (unity power factor), regulation is moderate
    - For inductive loads (lagging power factor), regulation is poorer (voltage drops more under load)
    - For capacitive loads (leading power factor), regulation can be negative (voltage rises under load)
4. **Load Current**: Higher load currents cause greater voltage drops and poorer regulation.
5. **Transformer Design**: Design factors such as core material, winding arrangement, and insulation thickness affect leakage reactance and resistance, thereby influencing regulation.

### 5.3.3 Calculation of Voltage Regulation

Voltage regulation can be calculated using the transformer equivalent circuit parameters:

For a load with power factor $\cos(\varphi_2)$:

Voltage Regulation (%) = $(R_2\cos\varphi_2 + X_2\sin\varphi_2) \times (I_2/V_2) \times 100$

Where: - $R_2$ is the secondary winding resistance (or referred resistance) - $X_2$ is the secondary leakage reactance (or referred reactance) - $I_2$ is the secondary full-load current - $V_2$ is the secondary full-load voltage - $\varphi_2$ is the load phase angle

For more accurate calculations, the complete equivalent circuit should be used, including the effects of the magnetizing branch.

### 5.3.4 Improving Voltage Regulation

Several methods can be employed to improve the voltage regulation of transformers:

1. **Reducing Winding Resistance**: Using conductors with larger cross-sectional areas reduces resistance and improves regulation.
2. **Reducing Leakage Reactance**: Better interleaving of primary and secondary windings reduces leakage flux and improves regulation.
3. **Tap Changers**: On-load or off-load tap changers allow adjustment of the turns ratio to compensate for voltage variations.
4. **Automatic Voltage Regulators**: External voltage regulation equipment can be used to maintain constant output voltage.

5. **Phase Compensation**: For installations with poor power factor, power factor correction can improve voltage regulation.

# 5.4 Parallel Operation of Transformers

Parallel operation of transformers involves connecting two or more transformers together to share a common load. This configuration is commonly used in power systems for several reasons:

1. To increase power handling capacity beyond what a single transformer can provide
2. To ensure continuity of supply (if one transformer fails, others can still provide partial service)
3. To improve efficiency by operating fewer transformers during periods of light load
4. To facilitate maintenance without complete service interruption

## 5.4.1 Conditions for Parallel Operation

For successful parallel operation, transformers should ideally satisfy the following conditions:

1. **Same Voltage Ratio**: The turns ratios should be identical to avoid circulating currents between transformers.

2. **Same Polarity**: The polarity markings must be correctly aligned when making connections.

3. **Same Phase Sequence**: For three-phase transformers, the phase sequence must be identical.

4. **Same Per-Unit Impedance**: Transformers should have equal per-unit impedances to ensure proper load sharing.

5. **Same X/R Ratio**: The ratio of reactance to resistance should be the same for optimal load sharing.

6. **Same Vector Group**: Three-phase transformers should belong to the same vector group.

## 5.4.2 Load Sharing Between Parallel Transformers

When transformers operate in parallel, the load divides between them according to their kVA ratings and impedances. The load current distribution follows the inverse relationship with impedances:

$I_1/I_2 = Z_2/Z_1$

Where: - $I_1$, $I_2$ are the currents in transformers 1 and 2 - $Z_1$, $Z_2$ are the impedances of transformers 1 and 2

For transformers with identical per-unit impedances, the load shares in proportion to their kVA ratings:

$I_1/I_2 = kVA_1/kVA_2$

### 5.4.3 Circulating Currents

When transformers with different voltage ratios operate in parallel, circulating currents flow between them even when no external load is connected. These currents:

1. Cause additional $I^2R$ losses, reducing efficiency
2. Reduce the available capacity for external load
3. May cause overheating and premature failure

The magnitude of the circulating current depends on the difference in voltage ratios and the impedances of the transformers:

$I(circulating) = (V_1 - V_2) / (Z_1 + Z_2)$

Where: - $V_1$, $V_2$ are the open-circuit secondary voltages - $Z_1$, $Z_2$ are the impedances referred to the secondary side

### 5.4.4 Advantages and Limitations of Parallel Operation

**Advantages:** 1. Increased reliability and continuity of supply 2. Flexibility in handling varying loads 3. Ease of maintenance without complete shutdown 4. Improved efficiency at partial loads 5. Expandability of the system

**Limitations and Challenges:** 1. Potential for circulating currents if parameters are not matched 2. Complexity in protection schemes 3. Possibility of unequal load sharing leading to overloading of some units 4. Higher fault levels due to reduced overall impedance 5. Need for careful synchronization and monitoring

### 5.4.5 Practical Considerations for Parallel Operation

When implementing parallel operation of transformers, several practical considerations should be addressed:

1. **Connection Procedure**: Always connect the high-voltage sides first, then the low-voltage sides.

2. **Protection Systems**: Implement appropriate protection schemes for each transformer and the parallel group.

3. **Monitoring**: Continuously monitor load distribution, temperatures, and other parameters.

4. **Tap Changer Coordination**: If transformers have tap changers, coordinate their operation to maintain balanced loading.

5. **Physical Arrangement**: Consider the physical layout for proper cooling and maintenance access.

6. **Emergency Procedures**: Establish protocols for handling faults or removing a transformer from service.

# 5.5 Inrush Current Phenomenon

When a transformer is first energized, it can draw a large, transient current known as inrush current or magnetizing inrush. This phenomenon is important to understand as it can affect protection systems and cause mechanical stress on windings.

## 5.5.1 Causes of Inrush Current

The primary cause of inrush current is the saturation of the transformer core during energization. When a transformer is de-energized, some residual magnetism typically remains in the core. When voltage is reapplied, the flux must build from this residual level rather than from zero.

If the transformer is switched on at a point in the voltage cycle that drives the flux in the same direction as the residual flux, the core can quickly saturate. Once saturated, the core’s magnetic permeability drops dramatically, causing the magnetizing current to increase to very high values.

## 5.5.2 Characteristics of Inrush Current

Inrush current has several distinctive characteristics:

1. **Magnitude**: Can reach 8-10 times the rated current or even higher
2. **Duration**: Typically decays exponentially over several cycles to seconds
3. **Waveform**: Highly distorted, rich in harmonics (particularly even harmonics)
4. **Asymmetry**: Usually contains a significant DC component
5. **Randomness**: Magnitude depends on the point-on-wave switching and residual flux

## 5.5.3 Factors Affecting Inrush Current

Several factors influence the magnitude and duration of inrush current:

1. **Residual Flux**: Higher residual flux can lead to more severe inrush currents
2. **Point-on-Wave Switching**: The instant in the voltage cycle when the transformer is energized
3. **Source Impedance**: Lower source impedance results in higher inrush currents
4. **Core Design**: Core material and design affect saturation characteristics
5. **Transformer Size**: Larger transformers tend to have more pronounced inrush currents
6. **Applied Voltage**: Higher applied voltage can increase inrush current

### 5.5.4 Mitigation Techniques

Several methods can be employed to reduce the effects of inrush current:

1. **Controlled Switching**: Energizing the transformer at the optimal point in the voltage cycle
2. **Pre-insertion Resistors**: Temporarily inserting resistors during energization
3. **Sequential Switching**: In three-phase transformers, energizing phases in sequence
4. **Soft-Start Devices**: Using thyristors or other solid-state devices for gradual voltage application
5. **Differential Relay Settings**: Configuring protection relays to discriminate between inrush and fault conditions
6. **Core Demagnetization**: Demagnetizing the core before re-energization

### 5.5.5 Practical Implications

Inrush current has several practical implications for transformer operation and protection:

1. **Protection Systems**: Can cause nuisance tripping of overcurrent protection
2. **Mechanical Stress**: Creates electromagnetic forces that stress the windings
3. **Voltage Dips**: Can cause momentary voltage sags in the supply system
4. **Harmonics**: Generates harmonics that can affect sensitive equipment
5. **Circuit Breakers**: May cause excessive wear on switching devices

Understanding and managing inrush current is essential for reliable transformer operation, especially in critical power systems where nuisance tripping cannot be tolerated.# Chapter 6: Transformer Losses and Efficiency

# 6.1 Core Losses (Iron Losses)

Core losses, also known as iron losses, occur in the magnetic core of the transformer and are present whenever the transformer is energized, regardless of the load. These losses are a significant component of the total transformer losses, especially at light loads or no-load conditions.

## 6.1.1 Hysteresis Loss

Hysteresis loss is caused by the energy required to repeatedly magnetize and demagnetize the core material as the alternating current changes direction. When an alternating magnetic field is applied to the core, the magnetic domains within the material align with the field. As the field reverses direction, the domains must realign, which requires energy.

The hysteresis loss per cycle is proportional to the area of the hysteresis loop of the core material. Mathematically, hysteresis loss can be expressed using Steinmetz's equation:

$$P_h = k_h \times f \times B_{max}^n \times V$$

Where: - $P_h$ is the hysteresis loss in watts - $k_h$ is the hysteresis constant (depends on the core material) - $f$ is the frequency of the alternating current in Hz - $B_{max}$ is the maximum flux density in the core in Tesla - $n$ is the Steinmetz exponent (typically between 1.5 and 2.5, depending on the material) - $V$ is the volume of the core material

To minimize hysteresis loss, transformer cores are typically made from materials with narrow hysteresis loops, such as silicon steel or amorphous metal alloys. These materials require less energy to magnetize and demagnetize, resulting in lower hysteresis losses.

#### Factors Affecting Hysteresis Loss

1. **Core Material**: Different materials have different hysteresis characteristics. Silicon steel with higher silicon content (typically 3-4%) has lower hysteresis loss than regular steel.
2. **Maximum Flux Density**: Hysteresis loss increases exponentially with flux density. Operating at lower flux densities reduces hysteresis loss but requires a larger core.

3. **Frequency**: Hysteresis loss is directly proportional to frequency. Higher frequency applications require special core materials with lower hysteresis losses.

4. **Heat Treatment**: Proper annealing of the core material can reduce hysteresis loss by relieving mechanical stresses and optimizing the grain structure.

5. **Grain Orientation**: Grain-oriented silicon steel has significantly lower hysteresis loss in the direction of orientation, making it ideal for transformer cores.

### 6.1.2 Eddy Current Loss

Eddy current losses occur due to the induced currents that circulate within the core material itself. According to Faraday's law, when a conductive material is subjected to a changing magnetic field, an EMF is induced in the material. This EMF causes currents to flow in closed paths within the core, similar to eddies in water, hence the name "eddy currents."

These circulating currents generate $I^2R$ losses and heat up the core. The eddy current loss can be expressed as:

$P_e = k_e \times f^2 \times B_{max}^2 \times t^2 \times V$

Where: - $P_e$ is the eddy current loss in watts - $k_e$ is the eddy current constant (depends on the core material resistivity) - $f$ is the frequency in Hz - $B_{max}$ is the maximum flux density in Tesla - $t$ is the thickness of the laminations in meters - $V$ is the volume of the core material

#### Techniques to Reduce Eddy Current Losses

1. **Lamination**: The core is constructed from thin laminations (typically 0.23-0.35 mm thick) that are electrically insulated from each other. This breaks up the potential eddy current paths, reducing the overall eddy current loss.

2. **High-Resistivity Materials**: Adding silicon to steel increases its electrical resistivity, which reduces eddy current magnitude. Silicon steel with 3-4% silicon content is commonly used in transformer cores.

3. **Thinner Laminations**: As the eddy current loss is proportional to the square of the lamination thickness, using thinner laminations significantly reduces these losses. However, this increases manufacturing costs and reduces the stacking factor.

4. **Amorphous Metals**: These materials have much higher resistivity than silicon steel and can be produced in very thin ribbons, resulting in significantly lower eddy current losses.

### 6.1.3 Anomalous Loss (Excess Loss)

In addition to the classical hysteresis and eddy current losses, there is a third component of core loss known as anomalous loss or excess loss. This loss arises from the complex interaction between domain wall movement and the induced eddy currents at the microscopic level.

Anomalous loss is particularly significant at higher frequencies and can be expressed as:

$$P_a = k_a \times f^{1.5} \times B_{max}^{1.5} \times V$$

Where: - $P_a$ is the anomalous loss in watts - $k_a$ is the anomalous loss coefficient - $f$ is the frequency in Hz - $B_{max}$ is the maximum flux density in Tesla - $V$ is the volume of the core material

### 6.1.4 Total Core Loss

The total core loss is the sum of hysteresis, eddy current, and anomalous losses:

$$P_{core} = P_h + P_e + P_a$$

Core losses are present whenever the transformer is energized, regardless of whether it is loaded or not. They are often measured through the open-circuit test (no-load test) of the transformer.

### 6.1.5 Core Loss Reduction Strategies

Several strategies are employed to minimize core losses in modern transformers:

1. **Advanced Core Materials**: Using high-grade silicon steel (CRGO - Cold Rolled Grain Oriented) or amorphous metal cores can reduce core losses by 40-80% compared to conventional materials.

2. **Optimal Flux Density**: Designing the transformer to operate at the optimal flux density that balances core losses against material utilization.

3. **Step-Lap Core Joints**: Improving the design of core joints to reduce localized flux concentration and associated losses.

4. **Laser Treatment**: Laser scribing of the lamination surface to reduce the size of eddy current paths.

5. **Domain Refinement**: Techniques like stress coating or laser scribing to refine the magnetic domain structure and reduce hysteresis loss.

6. **Improved Insulation Coatings**: Better insulation between laminations to reduce inter-laminar eddy currents.

# 6.2 Copper Losses (Winding Losses)

Copper losses, also known as winding losses or $I^2R$ losses, occur in the primary and secondary windings of the transformer due to the electrical resistance of the conductor material. Unlike core losses, copper losses vary with the load current and are proportional to the square of the current.

## 6.2.1 Primary Winding Copper Loss

The copper loss in the primary winding is given by:

$P_{cu1} = I_1^2 \times R_1$

Where: - $P_{cu1}$ is the primary winding copper loss in watts - $I_1$ is the primary current in amperes - $R_1$ is the resistance of the primary winding in ohms

## 6.2.2 Secondary Winding Copper Loss

Similarly, the copper loss in the secondary winding is:

$P_{cu2} = I_2^2 \times R_2$

Where: - $P_{cu2}$ is the secondary winding copper loss in watts - $I_2$ is the secondary current in amperes - $R_2$ is the resistance of the secondary winding in ohms

## 6.2.3 Total Copper Loss

The total copper loss in the transformer is the sum of the primary and secondary winding losses:

$P_{cu} = P_{cu1} + P_{cu2} = I_1^2 \times R_1 + I_2^2 \times R_2$

For analysis purposes, the secondary quantities are often referred to the primary side:

$P_{cu} = I_1^2 \times R_1 + (I_2 \times N_1/N_2)^2 \times R_2 = I_1^2 \times R_1 + I_1^2 \times R_2'$

Where $R_2'$ is the secondary resistance referred to the primary side:

$R_2' = R_2 \times (N_1/N_2)^2$

Thus, the total copper loss can be expressed as:

$P_{cu} = I_1^2 \times (R_1 + R_2')$

### 6.2.4 Factors Affecting Copper Losses

Several factors influence the magnitude of copper losses in transformers:

1. **Load Current**: Copper losses are proportional to the square of the current. Doubling the load current quadruples the copper losses.
2. **Conductor Resistance**: The resistance of the winding depends on:
    - Conductor material (usually copper or aluminum)
    - Conductor cross-sectional area
    - Conductor length
    - Temperature (resistance increases with temperature)
3. **Winding Temperature**: As the transformer operates, the windings heat up, increasing their resistance. The resistance of copper increases by approximately 0.393% per degree Celsius rise in temperature.
4. **Skin Effect**: At higher frequencies, current tends to flow near the surface of the conductor, effectively reducing the usable cross-sectional area and increasing resistance.
5. **Proximity Effect**: The magnetic fields from adjacent conductors can cause current crowding, further increasing the effective resistance.

### 6.2.5 Copper Loss Reduction Techniques

Several methods are employed to minimize copper losses in transformers:

1. **Larger Conductor Cross-Section**: Using conductors with larger cross-sectional areas reduces resistance and copper losses, but increases the size and cost of the transformer.
2. **Conductor Material**: Copper has lower resistivity than aluminum, resulting in lower losses for the same current density, but at a higher cost.
3. **Winding Design**: Optimizing the winding design to minimize the length of the conductors while maintaining the required number of turns.

4. **Temperature Management**: Effective cooling systems help maintain lower winding temperatures, reducing resistance and copper losses.
5. **Transposition of Conductors**: In large transformers, conductors are transposed to mitigate the effects of eddy currents and proximity effects.
6. **Foil Windings**: Using foil conductors instead of round wires can reduce copper losses in certain applications by improving the fill factor and reducing skin effect.

## 6.3 Stray Losses

Stray losses, also known as additional losses or leakage flux losses, are caused by the leakage flux that does not link both the primary and secondary windings. These losses occur in various parts of the transformer, including the windings, core clamps, tank walls, and other structural components.

### 6.3.1 Eddy Current Losses in Windings

Leakage flux cutting through the conductors induces eddy currents within the conductors themselves, causing additional losses. These losses are particularly significant in large conductors and at high frequencies.

To minimize these losses, large conductors are often subdivided into smaller, parallel strands that are transposed or continuously transposed conductors (CTC) are used.

### 6.3.2 Losses in Structural Components

Leakage flux can induce eddy currents in structural components such as: - Core clamps - Tank walls - Magnetic shields - Other metallic structural parts

These losses can be reduced by: - Using non-magnetic materials for structural components where possible - Providing flux shields to redirect leakage flux - Installing magnetic shunts to provide low-reluctance paths for leakage flux - Using laminated structures for components that must be in the leakage flux path

### 6.3.3 Circulating Current Losses

In parallel conductors or strands, differences in the induced EMF can cause circulating currents to flow within the winding, resulting in additional losses. These losses are minimized by proper transposition

of the conductors.

### 6.3.4 Measurement and Estimation of Stray Losses

Stray losses are difficult to measure directly but can be estimated as the difference between the total measured losses and the sum of the calculated core and copper losses. They are typically determined through the load test of the transformer.

In large power transformers, stray losses can account for 10-20% of the total losses and must be carefully considered in the design process.

## 6.4 Efficiency Calculation

Transformer efficiency is the ratio of output power to input power, expressed as a percentage. It is a measure of how effectively the transformer converts electrical energy from the primary to the secondary circuit.

### 6.4.1 Efficiency Formula

The efficiency (η) of a transformer is given by:

$\eta = (\text{Output Power} / \text{Input Power}) \times 100\%$

Since the input power equals the output power plus the losses:

$\eta = (\text{Output Power} / (\text{Output Power} + \text{Total Losses})) \times 100\%$

or

$\eta = (\text{Output Power} / (\text{Output Power} + P_{core} + P_{cu} + P_{stray})) \times 100\%$

For a transformer supplying a load at power factor cos φ, the efficiency can be expressed as:

$\eta = (V_2 \times I_2 \times \cos\varphi) / (V_2 \times I_2 \times \cos\varphi + P_{core} + I_2^2 \times R_{eq}) \times 100\%$

Where: - $V_2$ is the secondary voltage - $I_2$ is the secondary current - cos φ is the load power factor - $P_{core}$ is the core loss (constant regardless of load) - $R_{eq}$ is the equivalent resistance representing copper and stray losses

### 6.4.2 Efficiency at Different Load Conditions

Transformer efficiency varies with the load. At very light loads, core losses dominate, while at heavy loads, copper losses become more significant. The efficiency curve typically rises from zero at no load,

reaches a maximum at a specific load, and then decreases as the load increases further.

The load at which maximum efficiency occurs is when the variable losses (copper and stray losses) equal the constant losses (core losses):

$I_2^2 R_{eq} = P_{core}$

This occurs at a load factor of:

Load Factor for Maximum Efficiency = $\sqrt{(P_{core} / P_{cu_rated})}$

Where $P_{cu_rated}$ is the copper loss at rated load.

### 6.4.3 Factors Affecting Efficiency

Several factors influence transformer efficiency:

1. **Load Level**: Efficiency varies with load, typically reaching a maximum at 50-80% of rated load.
2. **Power Factor**: Lower power factor loads result in higher currents for the same power output, increasing copper losses and reducing efficiency.
3. **Core Material**: Better core materials with lower hysteresis and eddy current losses improve efficiency.
4. **Conductor Material and Size**: Larger conductors and materials with lower resistivity reduce copper losses and improve efficiency.
5. **Design Optimization**: Balancing core and copper losses for the expected load profile can optimize overall efficiency.
6. **Operating Temperature**: Higher temperatures increase winding resistance and core losses, reducing efficiency.
7. **Operating Voltage and Frequency**: Operating at voltages or frequencies different from the rated values can affect core losses and efficiency.

### 6.4.4 Efficiency Standards

Transformer efficiency is subject to regulatory standards in many countries. For example:

1. **NEMA TP-1/DOE 2016 (USA)**: Specifies minimum efficiency levels for distribution transformers based on their kVA rating.
2. **EU Ecodesign Directive**: Defines minimum efficiency requirements for power transformers in the European Union.

3. **IEC 60076-20**: Provides international guidelines for energy efficiency in power transformers.

These standards typically define efficiency at specific load points (often 50% load) and set minimum requirements based on the transformer's size and type.

# 6.5 Maximum Efficiency Condition

As mentioned earlier, transformer efficiency varies with load, and there is a specific load at which the efficiency reaches its maximum value. Understanding this condition is important for optimal transformer operation.

## 6.5.1 Derivation of Maximum Efficiency Condition

To find the condition for maximum efficiency, we start with the efficiency formula:

$\eta$ = Output Power / (Output Power + Losses)

The output power can be expressed as: Output Power = $V_2 \times I_2 \times \cos \varphi$

The total losses consist of: - Core losses (P_core): Constant regardless of load - Copper losses (P_cu): Proportional to the square of the load current, $P_{cu} = I_2^2 \times R_{eq}$

Therefore: $\eta = (V_2 \times I_2 \times \cos \varphi) / (V_2 \times I_2 \times \cos \varphi + P_{core} + I_2^2 \times R_{eq})$

For maximum efficiency, the derivative of $\eta$ with respect to $I_2$ should be zero. Solving this equation leads to the condition:

$P_{core} = I_2^2 \times R_{eq}$

This means that maximum efficiency occurs when the variable losses (copper losses) equal the constant losses (core losses).

## 6.5.2 Load Factor for Maximum Efficiency

The load factor at which maximum efficiency occurs can be calculated as:

$x = \sqrt{(P_{core} / P_{cu_rated})}$

Where: - x is the load factor (ratio of actual load to rated load) - P_core is the core loss - P_cu_rated is the copper loss at rated load

For example, if a transformer has core losses of 500W and rated copper losses of 2000W, the maximum efficiency would occur at:

x = √(500/2000) = 0.5 or 50% of rated load

### 6.5.3 Design Considerations for Maximum Efficiency

Transformers can be designed to achieve maximum efficiency at different load levels based on the expected load profile:

1. **Distribution Transformers**: Often designed for maximum efficiency at 50-70% of rated load, as they typically operate below full load most of the time.
2. **Power Transformers**: May be designed for maximum efficiency closer to full load (70-80%) if they are expected to operate near their rated capacity.
3. **Special Purpose Transformers**: Can be optimized for specific load profiles based on the application requirements.

The design engineer can adjust the ratio of core losses to copper losses by: - Changing the core cross-sectional area and flux density - Modifying the conductor size and winding design - Selecting different core materials - Optimizing the overall transformer dimensions

## 6.6 All-Day Efficiency

While the conventional efficiency calculation provides a snapshot of transformer performance at a specific load, many transformers, especially distribution transformers, operate with varying loads throughout the day. All-day efficiency (or energy efficiency) provides a more realistic measure of performance for such applications.

### 6.6.1 Definition and Calculation

All-day efficiency is defined as the ratio of the energy output to the energy input over a specified period (typically 24 hours):

All-day Efficiency = (Energy Output / Energy Input) × 100% = (Energy Output / (Energy Output + Energy Lost)) × 100%

The calculation involves integrating the output power and losses over the specified period:

All-day Efficiency = (∫ P_out dt) / (∫ P_out dt + ∫ Losses dt) × 100%

In practice, this is often simplified by dividing the day into intervals with different load levels and summing the energy for each interval.

### 6.6.2 Typical Load Cycle

A typical load cycle for a distribution transformer might look like: - Light load (25% of rated load) for 10 hours - Medium load (50% of rated load) for 8 hours - Heavy load (100% of rated load) for 6 hours

For each period, the energy output and losses are calculated: - Energy Output = Power Output × Time - Energy Lost = (Core Losses + Copper Losses at that load) × Time

### 6.6.3 Example Calculation

Consider a 100 kVA transformer with core losses of 500W and full-load copper losses of 2000W, operating with the load cycle described above:

1. Light load period (25% load, 10 hours):
   - Output: 25 kW × 10h = 250 kWh
   - Core loss: 0.5 kW × 10h = 5 kWh
   - Copper loss: 2 kW × $(0.25)^2$ × 10h = 0.125 kWh
   - Total loss: 5.125 kWh
2. Medium load period (50% load, 8 hours):
   - Output: 50 kW × 8h = 400 kWh
   - Core loss: 0.5 kW × 8h = 4 kWh
   - Copper loss: 2 kW × $(0.5)^2$ × 8h = 4 kWh
   - Total loss: 8 kWh
3. Heavy load period (100% load, 6 hours):
   - Output: 100 kW × 6h = 600 kWh
   - Core loss: 0.5 kW × 6h = 3 kWh
   - Copper loss: 2 kW × $(1)^2$ × 6h = 12 kWh
   - Total loss: 15 kWh

Total energy output = 250 + 400 + 600 = 1250 kWh Total energy lost = 5.125 + 8 + 15 = 28.125 kWh

All-day efficiency = 1250 / (1250 + 28.125) × 100% = 97.8%

### 6.6.4 Importance of All-Day Efficiency

All-day efficiency is particularly important for:

1. **Distribution Transformers**: These typically operate at varying loads throughout the day and may spend significant time at light loads where core losses dominate.

2. **Economic Evaluation**: When comparing transformers, all-day efficiency provides a better basis for economic evaluation than conventional efficiency.

3. **Energy Conservation**: Improving all-day efficiency can lead to significant energy savings over the transformer's lifetime.

4. **Environmental Impact**: Higher all-day efficiency reduces the carbon footprint associated with transformer losses.

### 6.6.5 Improving All-Day Efficiency

To improve all-day efficiency, designers focus on:

1. **Reducing Core Losses**: Since core losses are present 24 hours a day regardless of load, reducing them has a significant impact on all-day efficiency. This is why distribution transformers often use premium core materials like amorphous metals.

2. **Optimizing the Design**: Balancing core and copper losses based on the expected load profile rather than just the rated load.

3. **Proper Sizing**: Selecting a transformer with appropriate capacity for the actual load profile rather than oversizing, which can lead to operating predominantly at light loads where efficiency may be lower.

4. **Load Management**: In some cases, load management strategies can be employed to optimize the loading pattern and improve overall efficiency.

## 6.7 Temperature Rise and Cooling Systems

Transformer losses manifest as heat, which raises the temperature of the windings, core, and insulating oil. Excessive temperatures accelerate the aging of insulation materials and can lead to premature failure. Therefore, effective cooling is essential for reliable transformer operation.

### 6.7.1 Heat Generation and Temperature Rise

The heat generated in a transformer is directly proportional to the losses: - Core losses generate heat in the magnetic core - Copper losses generate heat in the windings - Stray losses generate heat in structural components

The temperature rise depends on: 1. The magnitude of the losses 2. The thermal resistance of the cooling path 3. The ambient temperature 4. The effectiveness of the cooling system

### 6.7.2 Temperature Limits

International standards specify maximum temperature limits for different transformer components:

1. **Winding Hot Spot**: Typically limited to 120°C for standard paper insulation (thermally upgraded paper can withstand higher temperatures)
2. **Average Winding Temperature Rise**: Usually limited to 65°C above ambient
3. **Top Oil Temperature Rise**: Typically limited to 60°C above ambient
4. **Core and Structural Parts**: Should not reach temperatures that could damage adjacent insulation

### 6.7.3 Cooling Methods

Transformers employ various cooling methods, classified according to IEC standards using a four-letter code:

1. **First Letter**: Internal cooling medium in contact with the windings
   - O: Mineral oil or synthetic insulating liquid with fire point ≤ 300°C
   - K: Insulating liquid with fire point > 300°C
   - L: Insulating liquid with no measurable fire point
2. **Second Letter**: Circulation mechanism for internal cooling medium
   - N: Natural circulation
   - F: Forced circulation through cooling equipment, natural circulation in windings
   - D: Forced circulation through cooling equipment, directed from cooling equipment into windings
3. **Third Letter**: External cooling medium
   - A: Air
   - W: Water
4. **Fourth Letter**: Circulation mechanism for external cooling medium
   - N: Natural convection
   - F: Forced circulation

Common cooling methods include:

1. **ONAN (Oil Natural, Air Natural)**: Natural circulation of oil within the transformer and natural air cooling of the radiators. Suitable for small to medium transformers.

2. **ONAF (Oil Natural, Air Forced)**: Natural circulation of oil with forced air cooling using fans on the radiators. Increases cooling capacity compared to ONAN.

3. **OFAF (Oil Forced, Air Forced)**: Oil is pumped through the windings and radiators, with forced air cooling of the radiators. Used for larger transformers.

4. **ODAF (Oil Directed, Air Forced)**: Oil is pumped and directed through the windings, with forced air cooling of the radiators. Provides more efficient cooling for large transformers.

5. **OFWF/ODWF (Oil Forced/Directed, Water Forced)**: Oil is pumped (and possibly directed) through the windings, with water-cooled heat exchangers. Used for very large transformers or in space-constrained installations.

### 6.7.4 Thermal Modeling and Monitoring

Modern transformer design and operation involve sophisticated thermal modeling and monitoring:

1. **Thermal Models**: These predict temperature distribution within the transformer based on losses, cooling system performance, and ambient conditions.

2. **Temperature Monitoring**: Transformers are equipped with various temperature sensors:

   - Top oil temperature indicators
   - Winding temperature indicators (using thermal images)
   - Fiber optic sensors for direct hot-spot measurement in critical applications

3. **Dynamic Loading**: Based on real-time temperature monitoring, transformers can be dynamically loaded beyond their nameplate rating when conditions permit (e.g., during cool ambient temperatures).

4. **Cooling System Control**: Advanced cooling systems adjust fan and pump operation based on load and temperature measurements to optimize cooling efficiency.

### 6.7.5 Impact of Cooling on Efficiency

The cooling system itself consumes energy (for fans, pumps, etc.), which affects the overall efficiency of the transformer system. Modern designs aim to balance effective cooling with minimal auxiliary power consumption.

For example, variable speed drives for cooling fans and pumps can adjust their operation based on actual cooling needs, reducing energy consumption during periods of light load or cool ambient temperatures.

# 6.8 Economic Evaluation of Transformer Losses

Transformer losses represent a significant economic cost over the lifetime of the transformer. When purchasing transformers, it is important to consider not just the initial capital cost but also the cost of losses over the transformer's service life.

## 6.8.1 Capitalization of Losses

The total owning cost (TOC) of a transformer is the sum of its purchase price and the present value of future losses:

TOC = Purchase Price + A × P_core + B × P_cu_rated

Where: - A is the cost per watt of core losses (/*W*) − *Bisthecostperwattofcopperlossesatratedload*(/W) - P_core is the core loss in watts - P_cu_rated is the copper loss at rated load in watts

The factors A and B are calculated based on: - Expected service life of the transformer - Energy cost ($/kWh) - Load factor and load growth - Interest rate - Inflation rate - Operating hours per year

## 6.8.2 Calculation of A and B Factors

The A factor (for core losses) is calculated as:

A = Energy Cost × 8760 hours/year × Present Value Factor

Since core losses are constant regardless of load, they occur continuously throughout the transformer's life.

The B factor (for copper losses) is calculated as:

B = Energy Cost × 8760 hours/year × Load Factor² × Present Value Factor

The Load Factor² term accounts for the fact that copper losses are proportional to the square of the load current.

The Present Value Factor accounts for the time value of money over the transformer's service life.

## 6.8.3 Example of Economic Evaluation

Consider two transformer options: - Transformer 1: Purchase price $50,000, core loss 5 kW, copper loss 20 kW - Transformer 2: Purchase price $60,000, core loss 3 kW, copper loss 18 kW

Given: - A = $8,000/kW (cost of core losses) - B = $2,000/kW (cost of copper losses)

Total Owning Cost: - Transformer 1: $50,000 + $8,000 × 5 + $2,000 × 20 = $90,000 - Transformer 2: $60,000 + $8,000 × 3 + $2,000 × 18 = $100,000

In this example, despite its higher purchase price, Transformer 1 has a lower total owning cost and would be the more economical choice.

### 6.8.4 Regulatory Aspects

Many countries have established minimum efficiency standards for transformers to promote energy conservation:

1. **United States**: Department of Energy (DOE) standards specify minimum efficiency levels for distribution transformers.
2. **European Union**: Ecodesign Directive sets minimum efficiency requirements for power transformers.
3. **China**: National standards define minimum efficiency levels for various transformer types.

These standards often use a Total Owning Cost approach or specify maximum allowable losses for different transformer ratings.

### 6.8.5 Life Cycle Assessment

Beyond direct economic costs, a comprehensive evaluation may include environmental impacts through Life Cycle Assessment (LCA):

1. **Manufacturing Phase**: Energy and resources used in production
2. **Use Phase**: Energy losses during operation
3. **End-of-Life Phase**: Disposal or recycling impacts

The use phase typically dominates the environmental impact due to the long service life and continuous energy losses. High-efficiency transformers generally have lower overall environmental impact despite potentially requiring more materials in their construction.

## 6.9 Recent Advances in Loss Reduction

Ongoing research and development continue to improve transformer efficiency through various innovations:

### 6.9.1 Advanced Core Materials

1. **High-Grade CRGO Steel**: Modern grain-oriented silicon steel with thinner laminations (0.23-0.18 mm) and better grain orientation reduces core losses.

2. **Amorphous Metal Cores**: These materials can reduce core losses by 70-80% compared to conventional silicon steel but are more expensive and have lower saturation flux density.

3. **Nanocrystalline Materials**: Offering even lower losses than amorphous metals, these materials are being developed for specialized applications.

4. **Laser-Scribed Laminations**: Laser treatment creates stress patterns that refine the domain structure and reduce hysteresis loss.

### 6.9.2 Winding Innovations

1. **Continuously Transposed Conductors (CTC)**: These reduce eddy current losses in large windings by minimizing circulating currents.

2. **Hexaformer Technology**: Hexagonal-shaped windings that better match the circular core window, improving material utilization and reducing losses.

3. **Advanced Insulation Materials**: Thinner insulation with better thermal properties allows for more copper in the same space, reducing resistance and losses.

4. **Superconducting Windings**: High-temperature superconducting (HTS) transformers virtually eliminate winding resistance and copper losses but require cryogenic cooling systems.

### 6.9.3 Design Optimization

1. **Finite Element Analysis (FEA)**: Advanced computational tools allow for more precise modeling of electromagnetic fields and losses, leading to optimized designs.

2. **Multi-Objective Optimization**: Algorithms that simultaneously optimize multiple parameters (efficiency, cost, size, etc.) to find the best overall design.

3. **Reduced Flux Density Operation**: Some designs intentionally operate at lower flux densities to reduce core losses, especially for applications where the transformer operates continuously.

4. **Step-Lap Core Joints**: Improved core joint designs reduce localized flux concentration and associated losses.

### 6.9.4 Smart Transformers

1. **On-Load Monitoring**: Real-time monitoring of temperatures, loads, and losses allows for optimized operation.
2. **Adaptive Cooling**: Intelligent cooling systems that adjust based on actual load and ambient conditions.
3. **Power Electronic Integration**: Solid-state transformers that combine conventional transformer technology with power electronics for improved control and efficiency.
4. **Phase-Shifting Capability**: Built-in phase shifting to optimize power flow and reduce system losses.

### 6.9.5 Future Directions

Research continues in several promising directions:

1. **Quantum Materials**: Exploring quantum effects in magnetic materials to develop cores with even lower losses.
2. **Bioinspired Design**: Using principles from nature to optimize transformer geometry and cooling systems.
3. **Additive Manufacturing**: 3D printing of core components with optimized geometries that would be impossible to produce with conventional methods.
4. **Integrated Design**: Holistic approaches that consider the transformer as part of a larger system, optimizing overall system efficiency rather than just the transformer itself.

These advances continue to push the boundaries of transformer efficiency, with modern designs achieving significantly lower losses than those of just a few decades ago.# Chapter 7: Transformer Testing and Diagnostics

# 7.1 Open Circuit Test

The open circuit test, also known as the no-load test, is one of the fundamental tests performed on transformers to determine the core losses and magnetizing characteristics. This test is conducted with one winding (typically the low-voltage winding) open-circuited while rated voltage is applied to the other winding.

### 7.1.1 Test Setup and Procedure

The open circuit test is typically performed as follows:

1. **Test Configuration**: The high-voltage (HV) winding is left open-circuited, and the rated voltage is applied to the low-voltage (LV) winding. This arrangement is preferred for safety reasons, as it involves working with lower voltages.

2. **Instrumentation**: The test setup includes:

   - A voltmeter to measure the applied voltage
   - An ammeter to measure the no-load current
   - A wattmeter to measure the power input
   - Optionally, a power factor meter or power analyzer

3. **Procedure**:

   - Connect the instruments as shown in the test circuit diagram
   - Gradually increase the applied voltage to the rated value
   - Record the readings of voltage ($V_0$), current ($I_0$), and power ($P_0$)
   - Optionally, take readings at different voltage levels to study the magnetization characteristics

4. **Safety Precautions**:

   - Ensure all connections are secure before applying voltage
   - Use properly rated instruments and cables
   - Maintain safe distances from energized parts
   - Follow standard electrical safety procedures

### 7.1.2 Measured Parameters and Calculations

From the open circuit test, several important parameters can be determined:

1. **Core Loss**: The wattmeter reading ($P_0$) directly gives the core loss, which includes both hysteresis and eddy current losses. A small component of copper loss in the energized winding is also included, but this is typically negligible compared to the core loss.

   $P_core \approx P_0$

2. **No-Load Current**: The ammeter reading ($I_0$) gives the no-load current, which has two components:

   - Magnetizing component ($I_m$): The reactive component that establishes the magnetic flux
   - Core loss component ($I_v$): The active component that supplies the core losses

3. **No-Load Power Factor**: The power factor under no-load conditions can be calculated as:

   $\cos \varphi_0 = P_0 / (V_0 \times I_0)$

4. **Magnetizing Current**: The magnetizing component of the no-load current can be calculated as:

   $I_m = I_0 \times \sin \varphi_0 = \sqrt{(I_0^2 - I_v^2)}$

5. **Core Loss Component**: The active component of the no-load current can be calculated as:

   $I_v = I_0 \times \cos \varphi_0 = P_0 / V_0$

6. **Magnetizing Reactance**: The magnetizing reactance can be determined as:

   $X_m = V_0 / I_m$

7. **Core Loss Resistance**: The equivalent resistance representing core losses can be calculated as:

   $R^c = V_0 / I_v = V_0^2 / P_0$

### 7.1.3 Equivalent Circuit Parameters

The open circuit test provides the parameters for the magnetizing branch of the transformer equivalent circuit:

1. **Magnetizing Reactance ($X_m$)**: Represents the magnetizing current required to establish the flux in the core.
2. **Core Loss Resistance ($R^c$)**: Represents the hysteresis and eddy current losses in the core.

These parameters are placed in parallel in the equivalent circuit and are typically referred to the side on which the test was conducted.

### 7.1.4 Significance and Limitations

The open circuit test provides valuable information about the transformer’s core characteristics and no-load performance:

1. **Core Quality Assessment**: The core loss and magnetizing current indicate the quality of the core material and construction. Lower values indicate better quality.
2. **Efficiency Calculation**: The core loss is a constant loss component that affects the transformer’s efficiency, especially at light loads.
3. **Excitation Characteristics**: By taking readings at different voltage levels, the magnetization curve of the core can be plotted, which is useful for studying saturation effects.

Limitations of the open circuit test include:

1. **Winding Parameters**: The test does not provide information about the winding resistances or leakage reactances.
2. **Load Performance**: The test does not indicate how the transformer will perform under load conditions.
3. **Temperature Effects**: Core losses are temperature-dependent, and the test results may need to be corrected for the operating temperature.

# 7.2 Short Circuit Test

The short circuit test, also known as the impedance test, is performed to determine the winding impedances and copper losses of a transformer. This test is conducted with one winding short-circuited while a reduced voltage is applied to the other winding to circulate the rated current.

## 7.2.1 Test Setup and Procedure

The short circuit test is typically performed as follows:

1. **Test Configuration**: The low-voltage (LV) winding is short-circuited using a heavy conductor with negligible resistance, and a reduced voltage is applied to the high-voltage (HV) winding. This arrangement is preferred as it requires a lower test voltage and power.
2. **Instrumentation**: The test setup includes:
    - A voltmeter to measure the applied voltage
    - An ammeter to measure the current
    - A wattmeter to measure the power input
    - Optionally, a power factor meter or power analyzer
3. **Procedure**:
    - Connect the instruments as shown in the test circuit diagram
    - Gradually increase the applied voltage until the rated current flows in the windings
    - Record the readings of voltage (Vsc), current (Isc), and power (Psc)
    - Note the winding temperature for temperature correction
4. **Safety Precautions**:
    - Ensure the short circuit connection has negligible resistance and can carry the rated current
    - Start with a low voltage and increase gradually
    - Monitor the current continuously to prevent overheating

- Be prepared to quickly reduce the voltage if the current exceeds the rated value

### 7.2.2 Measured Parameters and Calculations

From the short circuit test, several important parameters can be determined:

1. **Copper Loss**: The wattmeter reading (Psc) directly gives the copper loss at rated current, which includes the $I^2R$ losses in both windings.

   $P_{cu} = P_{sc}$

2. **Equivalent Impedance**: The equivalent impedance referred to the energized side can be calculated as:

   $Z_{eq} = V_{sc} / I_{sc}$

3. **Equivalent Resistance**: The equivalent resistance representing copper losses can be calculated as:

   $R_{eq} = P_{sc} / I_{sc}^2$

4. **Equivalent Reactance**: The equivalent reactance can be calculated using the impedance triangle:

   $X_{eq} = \sqrt{(Z_{eq}^2 - R_{eq}^2)}$

5. **Impedance Voltage**: The percentage impedance voltage, an important parameter for transformer specification, is calculated as:

   $\%Z = (V_{sc} / V_{rated}) \times 100\%$

   Where $V_{rated}$ is the rated voltage of the energized winding.

6. **Short Circuit Power Factor**: The power factor during the short circuit test can be calculated as:

   $\cos \varphi_{sc} = P_{sc} / (V_{sc} \times I_{sc}) = R_{eq} / Z_{eq}$

### 7.2.3 Equivalent Circuit Parameters

The short circuit test provides the parameters for the series branch of the transformer equivalent circuit:

1. **Equivalent Resistance (Req)**: Represents the combined effect of primary and secondary winding resistances.

2. **Equivalent Reactance (Xeq)**: Represents the combined effect of primary and secondary leakage reactances.

These parameters are placed in series in the equivalent circuit and are typically referred to the side on which the test was conducted.

For a more detailed equivalent circuit, the total resistance and reactance can be split between the primary and secondary sides based on design data or additional tests.

### 7.2.4 Significance and Applications

The short circuit test provides valuable information about the transformer's winding characteristics and load performance:

1. **Voltage Regulation Calculation**: The impedance parameters are essential for calculating the voltage regulation of the transformer under different load conditions.
2. **Efficiency Calculation**: The copper loss at rated current is used in efficiency calculations, as it varies with the square of the load current.
3. **Short Circuit Current Estimation**: The percentage impedance is used to estimate the short circuit current that would flow if a fault occurs.
4. **Parallel Operation**: The impedance parameters are crucial for determining how transformers will share load when connected in parallel.
5. **Temperature Rise Estimation**: The copper loss is directly related to the temperature rise in the windings and can be used to estimate the temperature rise at different loads.

### 7.2.5 Temperature Correction

Since the winding resistance varies with temperature, the copper loss measured during the short circuit test may need to be corrected to the reference temperature (usually 75°C for oil-immersed transformers):

$P_{cu}(75°C) = P_{cu}(t) \times [(235 + 75) / (235 + t)]$

Where: - $P_{cu}(75°C)$ is the copper loss at 75°C - $P_{cu}(t)$ is the measured copper loss at temperature t°C - 235 is the temperature coefficient for copper (225 for aluminum)

## 7.3 Sumpner Test (Back-to-Back Test)

The Sumpner test, also known as the back-to-back test or the regenerative test, is an efficient method for testing a pair of identical transformers. It allows for full-load testing without requiring the full

rated power from the supply, as the power circulates between the two transformers.

### 7.3.1 Test Setup and Procedure

The Sumpner test is set up as follows:

1. **Test Configuration**:
   - Two identical transformers are connected with their primary windings in parallel across a supply voltage
   - The secondary windings are connected in series opposition (or parallel opposition, depending on the variant)
   - A variable voltage source is connected across the secondary circuit to circulate current
2. **Instrumentation**:
   - Voltmeters to measure the primary and secondary voltages
   - Ammeters to measure the primary and secondary currents
   - Wattmeters to measure the power input to the primary and secondary circuits
3. **Procedure**:
   - Connect the transformers as shown in the test circuit diagram
   - Apply rated voltage to the primary windings
   - Adjust the secondary voltage source to circulate rated current in the secondary windings
   - Record all meter readings
4. **Safety Precautions**:
   - Verify the correct phasing before connecting the transformers
   - Ensure all connections can handle the rated currents
   - Start with low voltages and increase gradually
   - Monitor temperatures to prevent overheating

### 7.3.2 Measured Parameters and Calculations

The Sumpner test allows for the simultaneous measurement of both core and copper losses:

1. **Core Losses**: The wattmeter in the primary circuit measures the total core losses of both transformers, as the copper losses in the primary are negligible due to the small exciting current.

   $P_{core(total)} = W_1$

   The core loss per transformer is:

   $P_{core} = W_1 / 2$

2. **Copper Losses**: The wattmeter in the secondary circuit measures the total copper losses of both transformers, as there is no core loss component in the secondary circuit.

$P_{cu(total)} = W_2$

The copper loss per transformer is:

$P_{cu} = W_2 / 2$

3. **Total Losses**: The total losses per transformer are:

   $P_{total} = P_{core} + P_{cu}$

4. **Efficiency**: The efficiency at any load can be calculated as:

   $\eta = \text{Output} / (\text{Output} + \text{Losses}) = \text{Output} / (\text{Output} + P_{core} + P_{cu} \times (\text{Load}/\text{Rated Load})^2)$

### 7.3.3 Advantages and Limitations

The Sumpner test offers several advantages:

1. **Energy Efficiency**: Only the losses need to be supplied from the source, making it energy-efficient for testing large transformers.
2. **Full-Load Testing**: Allows testing at full load or even overload conditions without requiring the full power capacity.
3. **Continuous Operation**: Can be run for extended periods to study temperature rise and thermal performance.
4. **Comprehensive Results**: Provides both core and copper losses simultaneously.

Limitations include:

1. **Identical Transformers**: Requires two identical transformers, which may not always be available.
2. **Complex Setup**: More complex to set up than standard open circuit and short circuit tests.
3. **Accuracy Concerns**: Any imbalance between the transformers can affect the accuracy of the results.
4. **Limited Parameters**: Some parameters, like impedance voltage, need to be determined separately.

## 7.4 Polarity Test

The polarity test is performed to determine the relative instantaneous direction of the induced voltages in the primary and secondary windings of a transformer. This information is crucial for proper

parallel operation of transformers and for connecting transformers in various configurations.

## 7.4.1 Test Methods

There are several methods to determine transformer polarity:

#### 7.4.1.1 DC Method (Kick Test)

1. **Test Configuration**:
   - Connect a DC source (battery) in series with a center-zero DC ammeter to the primary winding
   - Connect a center-zero DC voltmeter across one primary and one secondary terminal
2. **Procedure**:
   - Close the primary circuit momentarily and observe the initial deflection of the voltmeter
   - If the voltmeter deflects positively, the terminals connected to the voltmeter have the same polarity
   - If the voltmeter deflects negatively, the terminals have opposite polarity
3. **Principle**: When the DC circuit is closed or opened, the changing flux induces a momentary voltage in both windings. The relative direction of this induced voltage indicates the polarity.

#### 7.4.1.2 AC Method

1. **Test Configuration**:
   - Apply a low AC voltage to the primary winding
   - Connect a voltmeter across one primary terminal and one secondary terminal
   - Connect another voltmeter to measure the primary voltage
   - Connect a third voltmeter to measure the secondary voltage
2. **Procedure**:
   - Measure the primary voltage ($V_1$), secondary voltage ($V_2$), and the voltage across the connected terminals ($V_3$)
   - If $V_3 > V_1$ or $V_3 > V_2$, the connected terminals have opposite polarity
   - If $V_3 < V_1$ and $V_3 < V_2$, the connected terminals have the same polarity
3. **Principle**: The voltage across the connected terminals is the phasor sum or difference of the primary and secondary voltages, depending on the relative polarity.

## 7.4.2 Polarity Markings

Transformer terminals are marked to indicate polarity:

1. **Additive Polarity**: When the primary and secondary voltages add up when measured across the terminals with the same polarity marking.

2. **Subtractive Polarity**: When the primary and secondary voltages subtract when measured across the terminals with the same polarity marking.

In standard practice: - Distribution transformers typically have additive polarity - Power transformers typically have subtractive polarity

The terminals are marked with dots, $H_1$, $H_2$, $X_1$, $X_2$, etc., according to industry standards (ANSI, IEC, etc.).

### 7.4.3 Importance of Polarity

Knowing the correct polarity is essential for:

1. **Parallel Operation**: Transformers connected in parallel must have the same polarity to avoid circulating currents.

2. **Three-Phase Connections**: Proper polarity is crucial for establishing the correct phase relationships in three-phase transformer banks.

3. **Autotransformer Connections**: Incorrect polarity in autotransformer connections can lead to short circuits.

4. **Instrument Transformers**: Correct polarity ensures proper direction of power flow measurement.

5. **Protection Systems**: Differential protection schemes rely on correct polarity for proper operation.

## 7.5 Ratio Test

The ratio test is performed to verify the turns ratio of a transformer, which is a fundamental parameter that determines the voltage transformation. This test ensures that the transformer has been manufactured according to specifications and that there are no shorted turns or other winding defects.

### 7.5.1 Test Methods

Several methods are used to measure the transformer ratio:

#### 7.5.1.1 Voltage Ratio Method

1. **Test Configuration**:
   - Apply a low AC voltage (typically 1-10% of rated voltage) to the primary winding
   - Measure the voltages on both primary and secondary sides using accurate voltmeters
2. **Procedure**:
   - Apply the test voltage to the primary winding
   - Measure the primary voltage ($V_1$) and secondary voltage ($V_2$)
   - Calculate the voltage ratio: $V_1/V_2$
   - Compare with the nameplate turns ratio
3. **Accuracy Considerations**:
   - Use high-accuracy voltmeters
   - Ensure no load is connected to the secondary
   - Consider the effect of magnetizing current on the ratio
   - Take measurements at different voltage levels to check for consistency

#### 7.5.1.2 Current Ratio Method

1. **Test Configuration**:
   - Short-circuit the secondary winding
   - Apply a low voltage to the primary to circulate current
   - Measure the currents on both primary and secondary sides
2. **Procedure**:
   - Apply sufficient voltage to circulate about 10% of rated current
   - Measure the primary current ($I_1$) and secondary current ($I_2$)
   - Calculate the current ratio: $I_2/I_1$
   - Compare with the nameplate turns ratio (the current ratio should be the inverse of the turns ratio)

#### 7.5.1.3 Turns Ratio Tester

1. **Test Equipment**: A specialized turns ratio tester that applies a voltage to one winding and measures the induced voltage in the other winding.

2. **Procedure**:

   - Connect the tester to the transformer terminals
   - The tester automatically applies a test voltage and measures the ratio
   - Some testers can also check for polarity and phase angle

3. **Advantages**:

   - High accuracy (typically 0.1% or better)
   - Automatic operation
   - Digital display of results
   - Some models can test all phases of a three-phase transformer

in one operation

### 7.5.2 Interpretation of Results

The measured ratio should be compared with the nameplate ratio:

1. **Acceptable Tolerance**: Typically ±0.5% for distribution transformers and ±0.1% for instrument transformers.
2. **Deviations**: Significant deviations may indicate:
    - Shorted turns
    - Open circuits
    - Incorrect tap settings
    - Manufacturing defects
    - Incorrect nameplate information
3. **Phase Relationship**: In three-phase transformers, the ratio test should also verify the phase relationships according to the vector group.

### 7.5.3 Applications

The ratio test is performed:

1. **During Manufacturing**: As part of quality control.
2. **During Commissioning**: To verify the transformer before putting it into service.
3. **After Repairs**: To ensure the windings have been properly restored.
4. **During Maintenance**: As part of routine diagnostic testing.
5. **After Fault Events**: To check for possible damage to the windings.

## 7.6 Insulation Resistance Test

The insulation resistance test, often called the Megger test, measures the resistance of the insulation between the transformer windings and between the windings and ground. This test is crucial for assessing the condition of the insulation system and detecting potential insulation failures.

### 7.6.1 Test Equipment and Setup

1. **Test Equipment**:
    - Insulation resistance tester (Megger) with appropriate voltage

rating
    - Test leads with proper insulation
    - Temperature measuring device
2. **Test Voltages**:
    - For low-voltage windings (<600V): 500V or 1000V DC
    - For medium-voltage windings (600V-5kV): 1000V or 2500V DC
    - For high-voltage windings (>5kV): 2500V or 5000V DC
3. **Test Connections**:
    - Winding to ground: Connect one terminal to the winding and the other to the grounded tank
    - Between windings: Connect one terminal to one winding and the other to another winding
    - Guard connection: Used to eliminate surface leakage currents when necessary

### 7.6.2 Test Procedure

1. **Preparation**:
    - Disconnect all external connections to the transformer
    - Ensure the transformer tank is properly grounded
    - Clean the bushings to minimize surface leakage
    - Record the ambient temperature and winding temperature
2. **Measurement Sequence**:
    - HV winding to ground (with LV winding grounded)
    - LV winding to ground (with HV winding grounded)
    - HV winding to LV winding (with tank grounded)
3. **Time-Resistance Method**:
    - Apply the test voltage for a specified duration (typically 1 minute)
    - Record the insulation resistance at 15 seconds, 30 seconds, and 60 seconds
    - Calculate the polarization index (PI) and dielectric absorption ratio (DAR)
4. **Safety Precautions**:
    - Ensure all personnel are clear of the transformer during testing
    - Discharge the windings before and after testing
    - Use proper personal protective equipment
    - Follow standard electrical safety procedures

### 7.6.3 Interpretation of Results

Several parameters are used to evaluate insulation condition:

1. **Insulation Resistance (IR)**:
    - The absolute value of resistance measured after 1 minute
    - Minimum acceptable values depend on the voltage class and size of the transformer
    - Typically, values above 1000 MΩ are considered good for new

transformers

2. **Polarization Index (PI)**:
   - Ratio of 10-minute resistance to 1-minute resistance: PI = $R_{10}/R_1$
   - Indicates the dryness and cleanliness of the insulation
   - PI < 1.0: Poor insulation condition
   - 1.0 < PI < 1.5: Questionable insulation
   - 1.5 < PI < 2.0: Fair insulation
   - 2.0 < PI < 4.0: Good insulation
   - PI > 4.0: Excellent insulation
3. **Dielectric Absorption Ratio (DAR)**:
   - Ratio of 60-second resistance to 30-second resistance: DAR = $R_{60}/R_{30}$
   - DAR < 1.1: Poor insulation
   - 1.1 < DAR < 1.25: Acceptable insulation
   - DAR > 1.25: Good insulation
4. **Temperature Correction**:
   - Insulation resistance decreases with increasing temperature
   - Measurements should be corrected to a standard temperature (typically 20°C)
   - Rule of thumb: Insulation resistance halves for every 10°C increase in temperature

### 7.6.4 Factors Affecting Insulation Resistance

Several factors can influence insulation resistance measurements:

1. **Temperature**: Higher temperatures reduce insulation resistance.
2. **Humidity**: High humidity can reduce surface resistance, especially on dirty bushings.
3. **Contamination**: Oil, carbon, and other contaminants can create leakage paths.
4. **Aging**: Insulation deteriorates over time, reducing its resistance.
5. **Moisture**: Moisture absorption significantly reduces insulation resistance.
6. **Test Voltage**: Higher test voltages may give different results due to nonlinear behavior of defects.

### 7.6.5 Applications and Limitations

The insulation resistance test is used for:

1. **Acceptance Testing**: To establish baseline values for new transformers.

2. **Preventive Maintenance**: To track insulation condition over time.
3. **Troubleshooting**: To identify potential insulation problems.
4. **Pre-energization Checks**: To ensure the transformer is safe to energize after transportation or storage.

Limitations include:

1. **Localization**: The test cannot pinpoint the exact location of insulation weaknesses.
2. **Sensitivity**: Some types of insulation defects may not be detected.
3. **Interpretation**: Results must be compared with previous measurements or standards for meaningful evaluation.

# 7.7 Dissolved Gas Analysis (DGA)

Dissolved Gas Analysis (DGA) is one of the most valuable diagnostic tools for assessing the internal condition of oil-filled transformers. It involves analyzing the gases dissolved in the transformer oil to detect and identify various types of faults before they lead to failure.

## 7.7.1 Principle and Methodology

1. **Basic Principle**:
   - Electrical and thermal stresses in a transformer decompose the insulating oil and paper, generating various gases
   - These gases dissolve in the oil
   - The types and concentrations of gases indicate specific fault conditions
2. **Sampling Methods**:
   - Syringe Method: Oil is drawn into a gas-tight syringe
   - Vacuum Container Method: Oil is collected in a vacuum-sealed container
   - Online DGA Monitors: Continuously sample and analyze gases
3. **Analysis Techniques**:
   - Gas Chromatography (GC): The most common method, separates and quantifies individual gases
   - Photo-Acoustic Spectroscopy (PAS): Used in some online monitoring systems
   - Infrared Spectroscopy: Used for specific gases like CO and $CO_2$
4. **Gases Analyzed**:
   - Hydrogen ($H_2$)
   - Methane ($CH_4$)
   - Ethane ($C_2H_6$)
   - Ethylene ($C_2H_4$)

- Acetylene ($C_2H_2$)
- Carbon Monoxide (CO)
- Carbon Dioxide ($CO_2$)
- Oxygen ($O_2$)
- Nitrogen ($N_2$)

## 7.7.2 Interpretation Methods

Several methods are used to interpret DGA results:

#### 7.7.2.1 Key Gas Method

This method identifies the predominant gas as an indicator of the type of fault:

1. **Thermal Faults in Oil**:
   - Ethylene ($C_2H_4$) is the key gas
   - Also produces significant amounts of methane and ethane
   - Low hydrogen levels
2. **Thermal Faults in Cellulose**:
   - Carbon Monoxide (CO) is the key gas
   - Also produces carbon dioxide
   - $CO_2$/CO ratio indicates severity
3. **Partial Discharge**:
   - Hydrogen ($H_2$) is the key gas
   - Also produces methane
   - Low levels of other gases
4. **Arcing**:
   - Acetylene ($C_2H_2$) is the key gas
   - Also produces hydrogen and ethylene
   - High energy discharge

#### 7.7.2.2 Rogers Ratio Method

This method uses ratios of certain gas concentrations to diagnose faults:

1. **Ratio 1**: $CH_4/H_2$
2. **Ratio 2**: $C_2H_6/CH_4$
3. **Ratio 3**: $C_2H_4/C_2H_6$
4. **Ratio 4**: $C_2H_2/C_2H_4$

Different combinations of these ratios indicate specific fault types according to standardized tables.

#### 7.7.2.3 Duval Triangle Method

This graphical method plots the relative proportions of methane, ethylene, and acetylene on a triangular chart. The position within the triangle indicates the type of fault:

1. **PD**: Partial Discharge
2. **T1**: Thermal Fault < 300°C
3. **T2**: Thermal Fault 300-700°C
4. **T3**: Thermal Fault > 700°C
5. **D1**: Low Energy Discharge
6. **D2**: High Energy Discharge
7. **DT**: Mixed Thermal and Electrical Fault

#### 7.7.2.4 IEEE C57.104 Standard

This standard provides guidelines for gas concentration limits and rates of change:

1. **Condition 1**: Normal operation
2. **Condition 2**: Elevated gas levels, requires additional testing
3. **Condition 3**: High gas levels, indicates probable fault
4. **Condition 4**: Excessive gas levels, indicates active fault

### 7.7.3 Fault Types and Gas Patterns

Different fault conditions produce characteristic gas patterns:

1. **Normal Aging**:
   - Low levels of all gases
   - Gradual increase over time
   - $CO_2$/CO ratio > 7
2. **Overheating of Oil (< 300°C)**:
   - Increased methane and ethane
   - Low levels of ethylene and acetylene
   - Moderate hydrogen
3. **Overheating of Oil (300-700°C)**:
   - Significant ethylene
   - Increased methane and ethane
   - Low acetylene
4. **Overheating of Oil (> 700°C)**:
   - High ethylene
   - Significant acetylene
   - High hydrogen
5. **Overheating of Cellulose**:
   - Increased CO and $CO_2$
   - $CO_2$/CO ratio decreases with severity
   - Furans may be present in oil
6. **Partial Discharge**:
   - Predominantly hydrogen

    - Some methane
    - Very low acetylene
7. **Low Energy Arcing**:
    - Increased hydrogen and acetylene
    - Moderate ethylene
    - Low methane and ethane
8. **High Energy Arcing**:
    - High acetylene
    - High hydrogen
    - Significant ethylene

### 7.7.4 Sampling Frequency and Trending

The frequency of DGA sampling depends on the transformer's importance, age, and condition:

1. **New Transformers**:
    - Initial sample at commissioning
    - Follow-up sample after 3-6 months
2. **Normal Operation**:
    - Annual sampling for critical transformers
    - Every 2-3 years for less critical units
3. **Abnormal Conditions**:
    - After any protective device operation
    - After overloading events
    - When other tests indicate potential problems
4. **Trending**:
    - Regular sampling and trending are more valuable than isolated measurements
    - Rate of gas generation often indicates fault severity
    - Sudden increases require immediate attention

### 7.7.5 Limitations and Complementary Tests

DGA has some limitations that should be considered:

1. **Interpretation Challenges**:
    - Multiple faults can produce complex gas patterns
    - Different interpretation methods may give different diagnoses
    - Expert judgment is often required
2. **Sampling Issues**:
    - Improper sampling can introduce air or lose gases
    - Oil circulation patterns can affect gas distribution
    - Stagnant oil may not represent the entire transformer
3. **Complementary Tests**:
    - Furan Analysis: Indicates paper degradation
    - Oil Quality Tests: Acidity, interfacial tension, moisture content
    - Power Factor Testing: Indicates overall insulation condition

- Frequency Response Analysis: Detects winding movement

# 7.8 Frequency Response Analysis (FRA)

Frequency Response Analysis (FRA) is an advanced diagnostic technique used to detect mechanical deformations and displacements in transformer windings. It is particularly valuable for assessing transformer condition after transportation, seismic events, or short-circuit incidents.

## 7.8.1 Principle and Methodology

1. **Basic Principle**:
   - The transformer winding acts as a complex RLC network with a unique frequency response
   - Any mechanical change in the winding structure alters this frequency response
   - By comparing current and baseline frequency responses, mechanical deformations can be detected
2. **Test Methods**:
   - **Sweep Frequency Response Analysis (SFRA)**: Applies a sinusoidal voltage with varying frequency and measures the response
   - **Impulse Frequency Response Analysis (IFRA)**: Applies an impulse voltage and analyzes the frequency spectrum of the response
3. **Test Configuration**:
   - **End-to-End Test**: Measures the response between the ends of the same winding
   - **Capacitive Inter-winding Test**: Measures the capacitive coupling between different windings
   - **Inductive Inter-winding Test**: Measures the inductive coupling between different windings
   - **Transfer Function Test**: Measures the response between different windings
4. **Frequency Range**:
   - Typically from 20 Hz to 2 MHz
   - Different frequency bands reveal different aspects of the winding condition

## 7.8.2 Test Procedure

1. **Preparation**:
   - Disconnect all external connections to the transformer
   - Ensure the transformer is de-energized and properly grounded
   - Record the tap position and other relevant settings

2. **Equipment Setup**:
    - Connect the FRA analyzer to the transformer terminals
    - Use short, shielded cables to minimize interference
    - Ensure proper grounding of the test equipment
3. **Measurement Sequence**:
    - Perform end-to-end measurements on all windings
    - Perform inter-winding measurements as required
    - Record the frequency response curves
    - Compare with baseline or reference measurements
4. **Documentation**:
    - Record test conditions (temperature, humidity, etc.)
    - Document all connections and test configurations
    - Save raw data and processed results

### 7.8.3 Interpretation of Results

The interpretation of FRA results involves comparing the current response with a reference:

1. **Reference Types**:
    - **Baseline**: Previous measurement of the same transformer
    - **Sister Unit**: Measurement from an identical transformer
    - **Phase Comparison**: Comparison between phases of the same transformer
    - **Simulated Response**: Theoretical response from a model
2. **Frequency Bands and Their Significance**:
    - **Low Frequency (20 Hz - 5 kHz)**: Core and magnetic circuit characteristics
    - **Medium Frequency (5 kHz - 100 kHz)**: Interaction between windings
    - **High Frequency (100 kHz - 2 MHz)**: Winding structure and deformation
3. **Analysis Methods**:
    - **Visual Comparison**: Direct comparison of response curves
    - **Correlation Coefficient**: Mathematical comparison of curve similarity
    - **Deviation Factor**: Quantifies differences between curves
    - **Spectral Deviation**: Analyzes differences in specific frequency bands
4. **Fault Indicators**:
    - **Frequency Shifts**: Indicate changes in inductance or capacitance
    - **Amplitude Changes**: Indicate changes in resistance or resonance conditions
    - **New Resonance Points**: Indicate structural changes
    - **Damping Changes**: Indicate changes in losses or coupling

### 7.8.4 Types of Detectable Faults

FRA can detect various mechanical problems:

1. **Winding Deformation**:
   - Axial displacement
   - Radial deformation
   - Hoop buckling
   - Tilting of conductors
2. **Core Problems**:
   - Core movement
   - Joint loosening
   - Shorted laminations
3. **Connection Issues**:
   - Loose connections
   - Broken leads
   - Poor contacts
4. **Other Issues**:
   - Partial winding collapse
   - Failed turn insulation
   - Shorted turns
   - Clamping structure problems

### 7.8.5 Advantages and Limitations

FRA offers several advantages:

1. **Non-Invasive**: Does not require opening the transformer
2. **Sensitive**: Can detect subtle mechanical changes
3. **Comprehensive**: Evaluates the entire winding structure
4. **Recordable**: Provides permanent records for future comparison

Limitations include:

1. **Interpretation Complexity**: Requires expertise to analyze results
2. **Reference Dependency**: Most valuable when baseline measurements are available
3. **Standardization Issues**: Different equipment and procedures may give slightly different results
4. **Environmental Sensitivity**: Temperature and moisture can affect results

### 7.8.6 Applications

FRA is particularly valuable in the following situations:

1. **After Transportation**: To detect shipping damage
2. **After Short Circuits**: To assess mechanical integrity
3. **After Seismic Events**: To detect earthquake damage

4. **During Factory Testing**: To establish baseline measurements
5. **During Major Maintenance**: To verify winding condition
6. **For Aging Transformers**: To detect progressive deformation

# 7.9 Other Important Tests

In addition to the major tests described in previous sections, several other tests are performed on transformers for various purposes. These tests provide additional information about the transformer's condition and performance.

## 7.9.1 Winding Resistance Measurement

This test measures the DC resistance of transformer windings to detect connection problems, joint issues, or tap changer defects.

1. **Test Method**:
   - Apply a DC current to the winding
   - Measure the voltage drop across the winding
   - Calculate the resistance using Ohm's law
   - Correct the resistance to a standard temperature (usually 75°C)
2. **Significance**:
   - Detects broken strands in windings
   - Identifies poor connections or high contact resistance
   - Verifies tap changer operation
   - Provides data for calculating $I^2R$ losses
3. **Acceptance Criteria**:
   - Resistance values should match design specifications
   - Phase-to-phase variation should be less than 2%
   - Comparison with factory test results should show minimal changes

## 7.9.2 Power Factor / Dissipation Factor Test

This test measures the dielectric losses in the insulation system, indicating its overall condition.

1. **Test Method**:
   - Apply an AC voltage to the insulation
   - Measure the phase angle between the applied voltage and the resulting current
   - Calculate the power factor ($\cos \theta$) or dissipation factor ($\tan \delta$)
2. **Measurements**:
   - Winding-to-ground insulation
   - Winding-to-winding insulation
   - Bushing insulation

- Oil insulation

3. **Significance**:
   - Detects moisture in insulation
   - Identifies contamination
   - Indicates aging and deterioration
   - Helps assess overall insulation condition
4. **Acceptance Criteria**:
   - New transformers: Power factor < 0.5%
   - Service-aged transformers: Power factor < 1.0%
   - Significant increase from previous measurements indicates deterioration

### 7.9.3 Excitation Current Test

This test measures the current required to magnetize the core at rated voltage.

1. **Test Method**:
   - Apply rated voltage to one winding with others open-circuited
   - Measure the current drawn
   - Compare between phases and with previous measurements
2. **Significance**:
   - Detects shorted turns
   - Identifies core problems
   - Reveals magnetic circuit issues
   - Verifies core quality
3. **Acceptance Criteria**:
   - Current should be within manufacturer's specifications
   - Phase-to-phase variation typically less than 10%
   - Significant increase from previous measurements indicates problems

### 7.9.4 Magnetic Balance Test

This test verifies the magnetic symmetry of the core and windings in three-phase transformers.

1. **Test Method**:
   - Apply balanced three-phase voltage at reduced level
   - Measure the exciting current in each phase
   - Compare the current magnitudes and phase angles
2. **Significance**:
   - Detects core asymmetry
   - Identifies unbalanced magnetic circuits
   - Reveals problems in core joints
3. **Acceptance Criteria**:
   - Current imbalance typically less than 10%
   - Significant imbalance indicates core problems

### 7.9.5 Oil Quality Tests

These tests assess the condition of the insulating oil, which is crucial for transformer cooling and insulation.

1. **Dielectric Strength**:
   - Measures the oil's ability to withstand electrical stress
   - Indicates presence of moisture or contaminants
   - Minimum acceptable value: 30 kV for new oil, 25 kV for service-aged oil (2.5 mm gap)
2. **Acidity (Neutralization Number)**:
   - Measures the acid content of the oil
   - Indicates oil aging and oxidation
   - Maximum acceptable value: 0.1 mg KOH/g for new oil, 0.2 mg KOH/g for service-aged oil
3. **Interfacial Tension**:
   - Measures the tension at the oil-water interface
   - Indicates presence of polar contaminants
   - Minimum acceptable value: 40 mN/m for new oil, 25 mN/m for service-aged oil
4. **Water Content**:
   - Measures moisture content in the oil
   - Indicates insulation degradation or leaks
   - Maximum acceptable value: 10 ppm for new oil, 25 ppm for service-aged oil
5. **Particle Count**:
   - Measures the number and size of particles in the oil
   - Indicates contamination or internal degradation
   - Should meet ISO cleanliness standards

### 7.9.6 Partial Discharge Test

This test detects and measures partial discharges within the transformer insulation.

1. **Test Method**:
   - Apply high voltage to the transformer
   - Detect and measure partial discharge pulses
   - Analyze the pattern and magnitude of discharges
2. **Significance**:
   - Detects insulation defects
   - Identifies void and gas bubbles
   - Reveals tracking and surface discharges
   - Early warning of potential insulation failure
3. **Acceptance Criteria**:
   - New transformers: PD level < 100 pC at 1.5 times rated voltage
   - Service-aged transformers: Comparison with previous measurements

### 7.9.7 Furan Analysis

This test measures the concentration of furanic compounds in the oil, which are byproducts of paper insulation degradation.

1. **Test Method**:
   - Extract oil sample
   - Analyze using high-performance liquid chromatography (HPLC)
   - Measure concentrations of various furanic compounds
2. **Compounds Measured**:
   - 2-furfural (2FAL): Most common and significant
   - 5-hydroxymethyl-2-furfural (5HMF)
   - 2-acetylfuran (2ACF)
   - 5-methyl-2-furfural (5MEF)
   - 2-furfurol (2FOL)
3. **Significance**:
   - Indicates degree of paper insulation degradation
   - Estimates remaining insulation life
   - Correlates with degree of polymerization (DP) of paper
4. **Interpretation**:
   - 2FAL < 0.1 mg/kg: Good condition
   - 0.1 < 2FAL < 0.5 mg/kg: Moderate degradation
   - 0.5 < 2FAL < 1.0 mg/kg: Significant degradation
   - 2FAL > 1.0 mg/kg: Extensive degradation

### 7.9.8 Thermal Imaging

This non-invasive technique uses infrared cameras to detect temperature anomalies in the transformer.

1. **Test Method**:
   - Scan the transformer with an infrared camera
   - Identify hot spots and temperature gradients
   - Compare with normal operating temperatures
2. **Areas Examined**:
   - Bushings and connections
   - Cooling system components
   - Tank surfaces
   - Tap changers
   - Auxiliary equipment
3. **Significance**:
   - Detects loose connections
   - Identifies cooling problems
   - Reveals internal hot spots
   - Early warning of developing faults
4. **Acceptance Criteria**:
   - Temperature differentials typically less than 10°C for similar components

- Significant hot spots indicate problems requiring investigation

# 7.10 Diagnostic Testing Programs

A comprehensive transformer testing program combines various tests to provide a complete assessment of the transformer's condition. Such programs are essential for effective asset management and reliability-centered maintenance.

## 7.10.1 Types of Testing Programs

Different testing programs serve different purposes:

1. **Acceptance Testing**:
   - Performed when a new transformer is received
   - Verifies compliance with specifications
   - Establishes baseline measurements
   - Detects shipping damage
   - Tests include: ratio, polarity, insulation resistance, oil quality, DGA, etc.
2. **Commissioning Testing**:
   - Performed before putting a transformer into service
   - Ensures proper installation
   - Verifies all systems are functioning correctly
   - Tests include: all acceptance tests plus functional tests of accessories
3. **Routine Maintenance Testing**:
   - Performed at regular intervals during service
   - Monitors condition trends
   - Detects developing problems
   - Tests include: oil quality, DGA, insulation resistance, power factor, etc.
4. **Diagnostic Testing**:
   - Performed when problems are suspected
   - Identifies specific issues
   - Determines severity of problems
   - Tests include: specialized tests based on symptoms
5. **End-of-Life Assessment**:
   - Performed on aging transformers
   - Evaluates remaining life
   - Supports replacement decisions
   - Tests include: comprehensive suite of electrical and chemical tests

## 7.10.2 Test Frequency and Scheduling

The frequency of testing depends on several factors:

1. **Transformer Importance**:
   - Critical transformers: More frequent testing
   - Non-critical transformers: Less frequent testing
2. **Age and Condition**:
   - New transformers: Less frequent testing
   - Aging transformers: More frequent testing
   - Transformers with known issues: More frequent testing
3. **Operating Environment**:
   - Harsh environments: More frequent testing
   - Stable environments: Less frequent testing
4. **Loading History**:
   - Heavily loaded transformers: More frequent testing
   - Lightly loaded transformers: Less frequent testing
5. **Typical Testing Intervals**:
   - DGA: 6 months to 1 year
   - Oil quality: 1 to 3 years
   - Insulation resistance: 1 to 3 years
   - Power factor: 1 to 3 years
   - Winding resistance: 3 to 5 years
   - FRA: After events or 5 to 10 years

### 7.10.3 Risk-Based Maintenance

Modern maintenance strategies often use risk-based approaches:

1. **Risk Assessment Factors**:
   - Transformer criticality
   - Age and condition
   - Failure consequences
   - Historical performance
   - Environmental factors
2. **Risk Categories**:
   - High-risk transformers: Comprehensive, frequent testing
   - Medium-risk transformers: Standard testing program
   - Low-risk transformers: Basic testing program
3. **Cost-Benefit Analysis**:
   - Testing costs vs. failure costs
   - Optimization of maintenance resources
   - Balancing reliability and economics

### 7.10.4 Data Management and Analysis

Effective testing programs require robust data management:

1. **Test Data Collection**:
   - Standardized formats
   - Electronic records
   - Complete documentation

2. **Trend Analysis**:
    - Tracking parameters over time
    - Identifying deterioration rates
    - Predicting future conditions
3. **Comparative Analysis**:
    - Comparing similar transformers
    - Benchmarking against population
    - Identifying outliers
4. **Integrated Analysis**:
    - Combining results from multiple tests
    - Correlating different parameters
    - Holistic condition assessment

### 7.10.5 Health Indices and Condition Assessment

Many utilities and industries use health indices to quantify transformer condition:

1. **Health Index Components**:
    - DGA results
    - Oil quality parameters
    - Electrical test results
    - Age and loading history
    - Observed defects
2. **Scoring System**:
    - Weighted scoring of various parameters
    - Normalization to a standard scale (e.g., 0-100)
    - Classification into condition categories
3. **Decision Support**:
    - Maintenance prioritization
    - Replacement planning
    - Resource allocation
    - Risk management
4. **Benefits**:
    - Objective condition assessment
    - Consistent evaluation across fleet
    - Clear communication to management
    - Effective asset management

### 7.10.6 Online Monitoring Systems

Modern transformers increasingly use online monitoring systems:

1. **Parameters Monitored**:
    - Dissolved gases
    - Oil temperature
    - Winding temperature
    - Load current

    - Moisture content
    - Partial discharges
    - Bushing condition
2. **Benefits**:
    - Continuous assessment
    - Early fault detection
    - Reduced manual testing
    - Dynamic loading capability
    - Extended transformer life
3. **Integration with Testing**:
    - Validation of online data with periodic tests
    - Triggering of additional tests based on online alarms
    - Comprehensive condition assessment
4. **Future Trends**:
    - Artificial intelligence for diagnostics
    - Predictive maintenance algorithms
    - Remote monitoring and diagnostics
    - Integration with smart grid systems# Chapter 8: Three-Phase Transformers

# 8.1 Introduction to Three-Phase Transformers

Three-phase transformers are essential components in three-phase power systems, which form the backbone of modern electrical power generation, transmission, and distribution networks. They offer several advantages over banks of single-phase transformers, including reduced cost, smaller footprint, and higher efficiency.

## 8.1.1 Comparison with Single-Phase Transformers

Three-phase transformers differ from single-phase transformers in several key aspects:

1. **Core Structure**: Three-phase transformers have a common magnetic core for all three phases, which results in better utilization of the core material.

2. **Winding Arrangement**: The windings are arranged to accommodate the three phases, with specific phase relationships maintained between them.

3. **Size and Weight**: For the same power rating, a three-phase transformer is typically smaller and lighter than three single-phase transformers.

4. **Efficiency**: Three-phase transformers generally have higher efficiency due to better core utilization and reduced losses.
5. **Cost**: A three-phase transformer is usually less expensive than three single-phase transformers of equivalent total capacity.

### 8.1.2 Applications of Three-Phase Transformers

Three-phase transformers are used in various applications:

1. **Power Generation**: Step-up transformers at power plants to increase voltage for transmission.
2. **Transmission Systems**: Interconnecting different voltage levels in the transmission network.
3. **Distribution Systems**: Step-down transformers to reduce voltage for distribution to industrial and commercial consumers.
4. **Industrial Applications**: Providing power for three-phase motors and other industrial equipment.
5. **Railway Electrification**: Converting three-phase power to single-phase power for traction systems.

## 8.2 Construction of Three-Phase Transformers

Three-phase transformers can be constructed in different ways, each with its own advantages and limitations.

### 8.2.1 Core Types

#### 8.2.1.1 Three-Limb Core Type

The three-limb core type is the most common construction for three-phase transformers:

1. **Structure**: Three vertical limbs connected by horizontal yokes at the top and bottom.
2. **Winding Arrangement**: Each limb carries the windings for one phase.
3. **Flux Path**: The magnetic flux in each limb returns through the other two limbs and the yokes.
4. **Advantages**:
    - Economical use of core material

- Compact design
- Lower weight

5. **Limitations**:
   - Asymmetry in the magnetic circuit (the center limb has a shorter flux path)
   - Limited space for insulation between phases

#### 8.2.1.2 Five-Limb Core Type

The five-limb core type offers improved performance for certain applications:

1. **Structure**: Five vertical limbs, with the three main limbs carrying the phase windings and two outer limbs providing return paths for the magnetic flux.
2. **Advantages**:
   - Symmetrical magnetic circuit for all three phases
   - Better handling of unbalanced loads
   - Reduced zero-sequence impedance
3. **Limitations**:
   - Higher material cost
   - Larger size and weight

#### 8.2.1.3 Shell Type

The shell-type construction encloses the windings with the core material:

1. **Structure**: Multiple core sections surrounding the windings.
2. **Advantages**:
   - Better mechanical strength
   - Improved short-circuit withstand capability
   - Better containment of magnetic flux
3. **Limitations**:
   - More complex construction
   - Higher manufacturing cost

### 8.2.2 Winding Arrangements

Three-phase transformers can have various winding arrangements:

1. **Concentric Windings**: The low-voltage and high-voltage windings are arranged concentrically around each limb.
2. **Sandwich Windings**: The low-voltage and high-voltage windings are divided into sections and arranged alternately.
3. **Helical Windings**: Used for high-current, low-voltage applications, with conductors wound in a helical pattern.
4. **Disc Windings**: Used for high-voltage applications, with the winding divided into multiple disc-shaped sections.

### 8.2.3 Cooling Systems

Three-phase transformers, especially large units, require effective cooling systems:

1. **Oil-Immersed with Natural Cooling (ONAN)**: The core and windings are immersed in oil, which circulates naturally and dissipates heat through the tank walls and radiators.
2. **Oil-Immersed with Forced Air Cooling (ONAF)**: Fans are added to enhance the cooling of radiators.
3. **Oil-Immersed with Forced Oil Circulation (OFAF)**: Oil pumps are used to circulate the oil through external coolers.
4. **Oil-Immersed with Water Cooling (OFWF)**: Water-cooled heat exchangers are used to cool the oil.
5. **Dry-Type with Air Cooling**: Used for indoor installations where fire safety is a concern.

## 8.3 Three-Phase Transformer Connections

The primary and secondary windings of a three-phase transformer can be connected in different configurations, each with specific characteristics and applications.

### 8.3.1 Star (Wye) Connection

In a star connection, one end of each phase winding is connected to a common point (the neutral point), and the other ends form the line terminals.

1. **Characteristics**:
   - Line voltage = √3 × Phase voltage
   - Line current = Phase current
   - Neutral point available for grounding

- Suitable for providing both three-phase and single-phase power

2. **Applications**:
   - Distribution transformers
   - Step-down transformers in substations
   - Systems requiring a neutral connection
3. **Advantages**:
   - Lower insulation requirements for the windings
   - Ability to handle unbalanced loads when neutral is provided
   - Reduced harmonics with proper grounding

### 8.3.2 Delta Connection

In a delta connection, the phase windings are connected in series to form a closed loop, with the line terminals connected to the junctions between windings.

1. **Characteristics**:
   - Line voltage = Phase voltage
   - Line current = √3 × Phase current
   - No neutral point
   - Circulating current path for third harmonics
2. **Applications**:
   - Industrial power systems
   - Generator step-up transformers
   - Systems where third harmonic suppression is important
3. **Advantages**:
   - No neutral displacement under unbalanced conditions
   - Suppression of third harmonic currents
   - Continued operation (at reduced capacity) if one phase is damaged

### 8.3.3 Zigzag Connection

The zigzag connection is a special connection where each phase winding is divided into two parts and connected to different core limbs.

1. **Characteristics**:
   - Provides phase shift
   - High zero-sequence impedance
   - Neutral point available
2. **Applications**:
   - Grounding transformers
   - Harmonic mitigation
   - Phase conversion systems
3. **Advantages**:
   - Suppression of zero-sequence currents
   - Reduction of harmonics

- Improved stability under unbalanced conditions

### 8.3.4 Open-Delta (V-V) Connection

The open-delta connection uses only two phases of a three-phase system.

1. **Characteristics**:
   - Operates with only two transformer units
   - Delivers 57.7% of the capacity of a full delta-delta connection
   - Unbalanced operation
2. **Applications**:
   - Emergency operation when one unit of a delta-delta bank fails
   - Temporary installations
   - Light three-phase loads
3. **Advantages**:
   - Continued three-phase service with two units
   - Lower initial cost for light loads
   - Easily expanded to full delta-delta

## 8.4 Vector Groups

Vector groups describe the phase displacement between the primary and secondary voltages in a three-phase transformer.

### 8.4.1 Vector Group Notation

The vector group notation consists of two letters and a number:

1. **First Letter**: Indicates the primary winding connection (Y, D, or Z for star, delta, or zigzag).

2. **Second Letter**: Indicates the secondary winding connection (y, d, or z for star, delta, or zigzag).

3. **Number**: Indicates the phase displacement in clock positions (1 to 12), where each position represents 30 degrees.

Examples: - Dyn11: Delta primary, star secondary with neutral, 330° phase displacement - YNd5: Star primary with neutral, delta secondary, 150° phase displacement - Yzn1: Star primary, zigzag secondary with neutral, 30° phase displacement

### 8.4.2 Common Vector Groups

Some vector groups are more commonly used than others:

1. **Dyn11**: Most common for distribution transformers in many countries.

2. **YNd5**: Common for generator step-up transformers.
3. **Dd0**: Used in industrial applications.
4. **Yzn1**: Used for creating artificial neutrals and handling unbalanced loads.

### 8.4.3 Selection Criteria for Vector Groups

The selection of a vector group depends on several factors:

1. **System Requirements**: Compatibility with existing system vector groups.
2. **Fault Level Control**: Some vector groups limit fault currents.
3. **Harmonic Handling**: Delta connections trap third harmonics.
4. **Load Characteristics**: Star connections are better for unbalanced loads.
5. **Grounding Requirements**: Availability of a neutral point for grounding.
6. **Phase Shift Requirements**: Some applications require specific phase shifts.

## 8.5 Parallel Operation of Three-Phase Transformers

Parallel operation of three-phase transformers is often necessary to meet load demands, provide redundancy, or improve system reliability.

### 8.5.1 Conditions for Parallel Operation

For successful parallel operation, transformers should meet the following conditions:

1. **Same Voltage Ratio**: The voltage ratios must be identical (or very close).
2. **Same Vector Group**: The vector groups must be identical to avoid circulating currents.
3. **Same Percentage Impedance**: The percentage impedances should be as close as possible to ensure proper load sharing.
4. **Same X/R Ratio**: The X/R ratios should be similar for proper sharing of active and reactive power.

5. **Same Phase Sequence**: The phase sequence must be identical.
6. **Adequate Short-Circuit Capacity**: The transformers must be able to withstand the increased fault level.

### 8.5.2 Load Sharing Between Parallel Transformers

The load sharing between parallel transformers depends on their relative impedances:

1. **Active Power Sharing**: Inversely proportional to the resistive component of the impedance.
2. **Reactive Power Sharing**: Inversely proportional to the reactive component of the impedance.
3. **Total Load Sharing**: For transformers with similar X/R ratios, approximately inversely proportional to their impedances.

The load sharing can be expressed as: $S_1/S_2 = Z_2/Z_1$

Where: - $S_1$, $S_2$ are the apparent powers of transformers 1 and 2 - $Z_1$, $Z_2$ are the impedances of transformers 1 and 2

### 8.5.3 Circulating Currents

Circulating currents can flow between parallel transformers due to:

1. **Different Voltage Ratios**: Causes circulating currents proportional to the difference in voltage ratios.
2. **Different Vector Groups**: Causes significant circulating currents that can overload the transformers.
3. **Different Tap Settings**: Causes circulating currents proportional to the difference in tap positions.
4. **Zero-Sequence Paths**: In certain connections, zero-sequence currents can circulate between transformers.

### 8.5.4 Practical Considerations

When operating transformers in parallel, consider the following practical aspects:

1. **Tap Changers**: Coordinate tap changer operations to maintain similar voltage ratios.
2. **Protection Systems**: Adjust protection settings to account for parallel operation.

3. **Unbalanced Loading**: Monitor for uneven load distribution.
4. **Fault Levels**: Account for increased fault levels in the system.
5. **Switching Operations**: Develop proper procedures for connecting and disconnecting parallel units.

# 8.6 Three-Phase Transformer Banks

A three-phase transformer bank consists of three single-phase transformers connected to form a three-phase unit.

## 8.6.1 Advantages and Disadvantages

Compared to three-phase transformers, three-phase banks have specific advantages and disadvantages:

**Advantages:**

1. **Redundancy**: The system can operate at reduced capacity if one unit fails.
2. **Transportation**: Easier to transport individual units.
3. **Spare Parts**: Only one spare unit needed for backup.
4. **Flexibility**: Can be reconfigured for different connections.
5. **Maintenance**: One unit can be maintained while others remain in service.

**Disadvantages:**

1. **Cost**: Generally more expensive than an equivalent three-phase transformer.
2. **Space Requirements**: Requires more space for installation.
3. **Connections**: More external connections, increasing the risk of faults.
4. **Losses**: Typically higher losses due to less efficient core utilization.
5. **Installation**: More complex installation process.

## 8.6.2 Common Connections for Transformer Banks

Three-phase transformer banks can be connected in various configurations:

1. **Delta-Delta (Dd0)**: All primary windings in delta, all secondary windings in delta.
2. **Delta-Star (Dy1, Dy5, Dy7, Dy11)**: Primary windings in delta, secondary windings in star.

3. **Star-Delta (Yd1, Yd5, Yd7, Yd11)**: Primary windings in star, secondary windings in delta.
4. **Star-Star (Yy0, Yy6)**: All primary windings in star, all secondary windings in star.
5. **Open-Delta (V-V)**: Uses only two single-phase transformers to provide three-phase power.

### 8.6.3 Special Configurations

Some special configurations of transformer banks serve specific purposes:

1. **Scott Connection**: Converts three-phase power to two-phase power.
2. **T-Connection**: Uses two single-phase transformers to provide three-phase power with balanced voltages.
3. **Zig-Zag Connection**: Provides a neutral point and suppresses harmonics.
4. **Le Blanc Connection**: Converts three-phase power to single-phase power for special applications.

## 8.7 Testing of Three-Phase Transformers

Three-phase transformers require specific testing procedures to verify their performance and condition.

### 8.7.1 Routine Tests

Routine tests are performed on all manufactured units:

1. **Winding Resistance Measurement**: Measures the DC resistance of each winding.
2. **Voltage Ratio Test**: Verifies the voltage ratio and phase displacement.
3. **Vector Group Verification**: Confirms the correct vector group.
4. **No-Load Loss and Current Measurement**: Measures core losses and magnetizing current.
5. **Load Loss and Impedance Measurement**: Determines copper losses and impedance.
6. **Insulation Resistance Test**: Checks the insulation condition.

7. **Dielectric Tests**: Includes applied voltage and induced voltage tests.

### 8.7.2 Type Tests

Type tests are performed on representative samples:

1. **Temperature Rise Test**: Determines the temperature rise under full load.
2. **Impulse Test**: Verifies the ability to withstand lightning impulses.
3. **Sound Level Measurement**: Measures the acoustic noise.
4. **Short-Circuit Withstand Test**: Verifies mechanical strength under fault conditions.
5. **Zero-Sequence Impedance Measurement**: Determines the zero-sequence impedance.

### 8.7.3 Special Tests

Special tests are performed as required:

1. **Harmonic Analysis of No-Load Current**: Analyzes the harmonic content.
2. **Measurement of Zero-Sequence Impedance**: For transformers with neutral connections.
3. **Determination of Capacitances**: Measures winding-to-winding and winding-to-ground capacitances.
4. **Measurement of Frequency Response**: Detects mechanical deformations.
5. **Partial Discharge Measurement**: Detects insulation defects.

## 8.8 Applications and Practical Considerations

### 8.8.1 Selection Criteria

When selecting a three-phase transformer, consider:

1. **Power Rating**: Based on load requirements and future growth.
2. **Voltage Levels**: Primary and secondary voltages.

3. **Connection Type**: Based on system requirements and load characteristics.
4. **Impedance**: Based on fault level requirements and voltage regulation.
5. **Efficiency**: Especially important for continuously loaded transformers.
6. **Cooling Method**: Based on installation environment and load profile.
7. **Special Requirements**: Noise level, overload capability, harmonic handling, etc.

### 8.8.2 Installation Considerations

Proper installation is crucial for reliable operation:

1. **Location**: Consider accessibility, ventilation, and safety.
2. **Foundation**: Must support the weight and withstand vibrations.
3. **Clearances**: Adequate clearances for safety and cooling.
4. **Connections**: Proper sizing and installation of cables.
5. **Protection**: Appropriate protective devices.
6. **Grounding**: Proper grounding for safety and operation.
7. **Oil Containment**: For oil-filled transformers, to prevent environmental contamination.

### 8.8.3 Maintenance Practices

Regular maintenance ensures long service life:

1. **Oil Testing**: Regular analysis of insulating oil.
2. **Insulation Testing**: Periodic checks of insulation resistance.
3. **Thermal Imaging**: Detection of hot spots.
4. **Acoustic Monitoring**: Detection of unusual sounds.
5. **Visual Inspections**: Checking for oil leaks, rust, and other visible issues.
6. **Bushing Maintenance**: Cleaning and testing of bushings.
7. **Cooling System Maintenance**: Ensuring proper operation of fans, pumps, and radiators.

# 8.9 Case Studies and Examples

## 8.9.1 Power Transmission Substation

A case study of a typical power transmission substation with three-phase transformers:

1. **Transformer Specifications**: Typically 100-500 MVA, YNd1 or YNyn0 vector group.
2. **Cooling Systems**: ONAF or OFAF for large units.
3. **Protection Schemes**: Differential protection, overcurrent protection, etc.
4. **Monitoring Systems**: Online DGA, temperature monitoring, etc.

## 8.9.2 Distribution Network

A case study of distribution transformers in a three-phase network:

1. **Transformer Specifications**: Typically 25-2500 kVA, Dyn11 vector group.
2. **Installation Types**: Pole-mounted, pad-mounted, or vault-type.
3. **Protection**: Fuses, reclosers, or circuit breakers.
4. **Maintenance Practices**: Regular oil testing and visual inspections.

## 8.9.3 Industrial Application

A case study of three-phase transformers in an industrial setting:

1. **Transformer Specifications**: Typically 500-5000 kVA, Dyn11 or Dd0 vector group.
2. **Special Requirements**: Harmonic handling, overload capability, etc.
3. **Integration with Motor Control Centers**: Coordination with motor starters and drives.
4. **Energy Efficiency Considerations**: Selection of high-efficiency units.

# 8.10 Future Trends in Three-Phase Transformer Technology

### 8.10.1 Advanced Materials

1. **Amorphous Core Materials**: Reducing no-load losses.
2. **High-Temperature Superconductors**: For highly efficient transformers.
3. **Advanced Insulation Materials**: Improving thermal performance and lifespan.

### 8.10.2 Smart Features

1. **Integrated Monitoring Systems**: Real-time condition monitoring.
2. **Self-Diagnostic Capabilities**: Early fault detection.
3. **Communication Interfaces**: Integration with smart grid systems.

### 8.10.3 Environmental Considerations

1. **Biodegradable Insulating Fluids**: Environmentally friendly alternatives to mineral oil.
2. **Dry-Type Designs**: Eliminating oil-related environmental risks.
3. **Recycling and End-of-Life Management**: Sustainable disposal practices.

### 8.10.4 Efficiency Improvements

1. **Higher Efficiency Standards**: Meeting or exceeding regulatory requirements.
2. **Optimized Designs**: Using computational methods for design optimization.
3. **Loss Reduction Techniques**: Innovative approaches to minimize losses.# Planned Chapters

The following chapters are planned for future development:

## Chapter 9: Special Transformers

This chapter will cover autotransformers, instrument transformers, welding transformers, pulse transformers, and high-frequency transformers.

## Chapter 10: Applications of Transformers

This chapter will explore applications in power generation, transmission, distribution, industrial processes, commercial buildings, and specialized fields.

## Chapter 11: Modern Trends and Future Developments

This chapter will examine smart transformers, advanced materials, energy efficiency improvements, solid-state transformers, and integration with renewable energy systems. # Glossary of Transformer Terminology

## A

**All-day efficiency**: The ratio of energy output to energy input over a 24-hour period, considering the actual load cycle rather than efficiency at a single load point. Particularly important for distribution transformers that operate at varying loads throughout the day.

**Amorphous core**: A transformer core made from amorphous metal (metallic glass) that has no crystalline structure, resulting in significantly lower hysteresis losses compared to conventional silicon steel cores.

**Ampere-turns**: The product of current in amperes and the number of turns in a winding, representing the magnetomotive force (MMF) produced by the winding.

**Autotransformer**: A transformer in which part of the winding is common to both primary and secondary circuits, resulting in electrical connection between the circuits rather than just magnetic coupling. Offers advantages in size, weight, and cost for applications where galvanic isolation is not required.

## B

**Buchholz relay**: A protective device installed in the pipe connecting the main tank and conservator of oil-immersed transformers that detects gas accumulation or oil surges resulting from internal faults.

**Burden**: The load connected to the secondary of an instrument transformer, usually expressed in volt-amperes and power factor at a specified current or voltage.

**Bushing**: An insulating structure that allows a conductor to pass through a grounded barrier (such as a transformer tank) while maintaining electrical isolation.

## C

**Conservator**: An oil reservoir mounted above the main tank of a transformer that allows for thermal expansion and contraction of the insulating oil while minimizing contact with air.

**Core**: The magnetic circuit of a transformer, typically constructed of laminated electrical steel, that provides a path for the magnetic flux.

**Core form transformer**: A transformer design where the windings surround the core limbs, with the magnetic circuit forming a simple rectangular or cruciform shape.

**Core loss**: Power loss occurring in the magnetic core of a transformer, comprising hysteresis loss and eddy current loss. Also called iron loss or no-load loss.

**Copper loss**: Power loss due to current flowing through the resistance of the transformer windings. Proportional to the square of the current ($I^2R$ loss). Also called load loss.

**Current transformer (CT)**: An instrument transformer designed to produce in its secondary winding a current that is proportionally related to the current in its primary winding, used for measurement and protection purposes.

## D

**Delta connection**: A three-phase connection arrangement where the three windings are connected in series to form a closed loop, with the three line connections made at the junctions of the windings.

**Dielectric strength**: The maximum electric field that an insulating material can withstand without experiencing failure of its insulating properties.

**Dissolved gas analysis (DGA)**: A diagnostic technique that analyzes the concentration of specific gases dissolved in transformer oil to detect and identify potential faults within the transformer.

**Distribution transformer**: A transformer used in electrical distribution systems to step down the voltage from primary distribution level to utilization level, typically serving end users.

**Dry-type transformer**: A transformer that uses air or gas for cooling and insulation rather than liquid, commonly used in indoor applications where fire safety is a concern.

## E

**Eddy current**: Circulating currents induced in conductive materials by a varying magnetic field, causing power losses and heating.

**Efficiency**: The ratio of output power to input power of a transformer, typically expressed as a percentage.

**EMF equation**: The fundamental equation relating the induced electromotive force in a transformer winding to the number of turns and the rate of change of magnetic flux.

**Equivalent circuit**: A circuit model representing the electrical behavior of a transformer, including ideal transformer elements and components representing various losses and imperfections.

**Excitation current**: The current drawn by a transformer when its secondary is open-circuited, consisting of a magnetizing component and a core loss component.

## F

**Frequency response analysis (FRA)**: A diagnostic technique that measures the transfer function of a transformer winding across a wide frequency range to detect mechanical deformations or displacements.

**Flux density**: The amount of magnetic flux per unit area perpendicular to the direction of the magnetic field, typically measured in tesla (T) or gauss (G).

**Flux leakage**: Magnetic flux that does not link both primary and secondary windings, reducing the coupling between windings and contributing to leakage reactance.

## G

**Grain-oriented silicon steel**: A specialized electrical steel with crystal grains aligned in the rolling direction to improve magnetic properties in that direction, commonly used in transformer cores.

**Grounding transformer**: A transformer specifically designed to provide a neutral point for grounding purposes in an otherwise ungrounded system.

## H

**Harmonics**: Sinusoidal components of a periodic wave having frequencies that are integral multiples of the fundamental frequency.

**Hot spot temperature**: The highest temperature in a transformer winding, typically 10-15°C higher than the average winding temperature, which is critical for insulation life expectancy.

**Hysteresis loss**: Power loss in magnetic materials due to the energy required to reorient magnetic domains during each cycle of magnetization.

## I

**Impedance voltage**: The voltage required to circulate rated current through one winding of a transformer when the other winding is short-circuited, expressed as a percentage of rated voltage. Also called impedance drop or Z%.

**Impulse test**: A high-voltage test that simulates lightning strikes or switching surges to verify the ability of transformer insulation to withstand transient overvoltages.

**Induced overvoltage test**: A test in which a voltage higher than rated voltage is applied to verify the insulation between turns and between windings.

**Inrush current**: A transient current of high magnitude that flows when a transformer is energized, caused by core saturation.

**Insulation resistance**: The resistance offered by the insulation between conductors or between conductors and ground.

**Instrument transformer**: A transformer designed to accurately transform current or voltage for measurement or protection purposes, including current transformers (CTs) and potential transformers (PTs).

## K

**K-factor**: A rating that indicates a transformer’s ability to handle harmonic currents without exceeding its temperature rise limits.

**kVA rating**: The apparent power rating of a transformer, expressed in kilovolt-amperes, which determines its load-carrying capacity.

## L

**Laminations**: Thin sheets of magnetic material stacked to form the transformer core, with insulation between layers to reduce eddy current losses.

**Leakage inductance**: The inductance associated with magnetic flux that does not link both primary and secondary windings, causing voltage drop under load conditions.

**Load loss**: Power loss that occurs when a transformer is loaded, primarily consisting of $I^2R$ losses in the windings. Also called copper loss.

## M

**Magnetizing current**: The component of excitation current that produces the magnetic flux in the core.

**Mineral oil**: A refined petroleum product commonly used as an insulating and cooling medium in liquid-filled transformers.

**Mutual inductance**: The property of two circuits whereby a change in current in one circuit induces a voltage in the other circuit due to their magnetic coupling.

## N

**Natural ester fluid**: A biodegradable insulating fluid derived from vegetable oils, used as an environmentally friendly alternative to mineral oil in transformers.

**No-load current**: The current drawn by a transformer when rated voltage is applied to one winding with all other windings open-circuited. Also called excitation current.

**No-load loss**: Power loss occurring in a transformer when rated voltage is applied to one winding with all other windings open-circuited, primarily consisting of core losses. Also called iron loss.

## O

**ONAN**: Oil Natural Air Natural - a cooling class designation for transformers where oil circulation and external cooling occur by natural convection.

**ONAF**: Oil Natural Air Forced - a cooling class designation for transformers where oil circulates by natural convection but external cooling is enhanced by fans.

**OFAF**: Oil Forced Air Forced - a cooling class designation for transformers where oil is circulated by pumps and external cooling is provided by fans.

**Open-circuit test**: A transformer test performed with one winding energized at rated voltage and all other windings open-circuited, used to determine core losses and excitation characteristics.

## P

**Parallel operation**: The operation of two or more transformers with their primary windings connected to the same source and their secondary windings connected to a common load.

**Partial discharge**: A localized electrical discharge that only partially bridges the insulation between conductors, indicating insulation deterioration.

**Per-unit system**: A system of normalized values where actual quantities are expressed as decimal fractions of reference values, simplifying calculations in power systems.

**Phase displacement**: The angular difference between corresponding voltages or currents on the primary and secondary sides of a transformer, particularly important in three-phase transformers.

**Polarization index**: The ratio of insulation resistance measured at 10 minutes to that measured at 1 minute, used as an indicator of insulation condition.

**Potential transformer (PT)**: An instrument transformer designed to produce in its secondary winding a voltage that is proportionally related to the voltage in its primary winding, used for measurement and protection purposes. Also called voltage transformer (VT).

**Power factor**: The ratio of active power to apparent power, indicating the phase difference between voltage and current.

**Power transformer**: A transformer used in transmission and sub-transmission systems to change voltage levels, typically handling power from generators to distribution circuits.

## R

**Ratio test**: A test to verify the turns ratio of a transformer by comparing the voltages or currents on the primary and secondary sides.

**Reactance**: The opposition to the flow of alternating current due to inductance or capacitance in a circuit, measured in ohms.

**Regulation**: The change in secondary voltage from no-load to full-load, expressed as a percentage of the full-load voltage.

## S

**Scott connection**: A special transformer connection that converts three-phase power to two-phase power.

**Shell form transformer**: A transformer design where the core surrounds the windings, with the magnetic circuit forming a shell around the coils.

**Short-circuit test**: A transformer test performed with one winding energized at reduced voltage and another winding short-circuited, used to determine impedance and load losses.

**Silica gel breather**: A device containing silica gel that absorbs moisture from air entering the transformer, protecting the insulating oil from water contamination.

**Solid-state transformer**: A power electronic device that uses high-frequency switching and a high-frequency transformer to achieve voltage transformation, often with additional functionality such as power quality improvement.

**Stray loss**: Power loss caused by leakage flux inducing eddy currents in windings, core clamps, tank walls, and other structural parts.

**Sumpner test**: A back-to-back test method for determining transformer losses using two identical transformers, allowing full-load testing at reduced power input.

## T

**Tap changer**: A device for changing the turns ratio of a transformer by connecting to different taps on a winding, either when de-energized (off-load tap changer) or while energized (on-load tap changer).

**Thermal class**: A classification system for insulating materials based on their maximum operating temperature.

**Three-phase transformer**: A transformer designed for use in three-phase systems, either as a single unit with a three-limb or five-limb core or as a bank of three single-phase units.

**Toroidal transformer**: A transformer with a ring-shaped core around which the windings are wound, offering advantages in size and reduced external magnetic field.

**Transformer oil**: An insulating and cooling medium used in liquid-filled transformers, typically mineral oil or synthetic alternatives.

**Turns ratio**: The ratio of the number of turns in the primary winding to the number of turns in the secondary winding, which determines the voltage ratio.

## V

**Vector group**: A designation system for three-phase transformers that indicates the connection type (Y, D, Z) and phase displacement between primary and secondary voltages using clock notation.

**Voltage ratio**: The ratio of the primary voltage to the secondary voltage of a transformer, approximately equal to the turns ratio in an ideal transformer.

**Voltage regulation**: The change in secondary terminal voltage from no-load to full-load, expressed as a percentage of the full-load voltage.

## W

**Winding**: An assembly of turns of conductor forming an electrical circuit associated with one of the voltage systems of a transformer.

**Winding resistance**: The DC resistance of a transformer winding, contributing to copper losses.

## Y

**Yoke**: The portion of a transformer core that connects the limbs and completes the magnetic circuit.

## Z

**Zero-sequence impedance**: The impedance offered by a transformer to zero-sequence currents, important for ground fault analysis.

**Zigzag connection**: A special winding connection where each phase consists of two parts wound on different core limbs, used primarily in grounding transformers and for harmonic mitigation.